



16 Exploded Views & Replacement Parts List


16.1. Exploded Views




16.2. Packing Exploded Views (1)




16.3. Packing Exploded Views (2)




16.4. Packing Exploded Views (PX70B ONLY)



16.5. Packing Exploded Views (Except PX70B)



16.6. Packing Exploded Views (Stand) (Except PX70B)



16.7. Replacement Parts List Notes

Important Safety Notice

*Components identified by Δ mark have special characteristics important for safety.
When replacing any of these components, use only manufacturer's specified parts.*

RTL (Retention Time Limited)

Note: The marking (RTL) indicates that the Retention Time is Limited for this item.

After the discontinuation of this assembly in production, the item will continue to be available for a specific period of time. The retention period of availability is dependant on the type of assembly, and in accordance with the laws governing part and product retention.

After the end of this period, the assembly will no longer be available.

Abbreviation of part name and description

1. Resistor

Example:

ERD25TJ104 C 100KOHM, J, 1/4W

Type Allowance

2. Capacitor

Example:

ECKF1H103ZF C 0.01UF, Z, 50V

Type Allowance

Type	Allowance
C : Carbon	F : $\pm 1\%$
F : Fuse	G : $\pm 2\%$
M : Metal Oxide	J : $\pm 5\%$
Metal Film	K : $\pm 10\%$
S : Solid	M : $\pm 20\%$
W : Wire Wound	

Type	Allowance
C : Ceramic	C : $\pm 0.25\text{pF}$
E : Electrolytic	D : $\pm 0.5\text{pF}$
P : Polyester	F : $\pm 1\text{pF}$
Polypropylene	G : $\pm 3\text{pF}$
T : Tantalum	J : $\pm 5\text{pF}$
	K : $\pm 10\text{pF}$
	L : $\pm 15\text{pF}$
	M : $\pm 20\text{pF}$
	P : +100%, -0%
	Z : +80%, -20%

16.8. Mechanical Replacement Parts List (PDD TV)

Note:

All parts except parts mentioned [PAVCCZ] in the Remarks column are supplied by PAVC-CSG.

Parts mentioned [PAVCCZ] are supplied by PAVCCZ.

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
1	EAS16S06A	SPEAKER (PED)	2	PAVCCZ
2	EUR7737Z50	REMOTE CONTROL	1	PAVCCZ TH-37/42PX70B/E
2	EUR7737Z60	REMOTE CONTROL	1	PAVCCZ TH-37/42PV70F/P
	J2ZZ00000083	RF-CABLE	1	PAVCCZ TH-37/42PX70B/E
	K1ZZ00001424	3 PIECE CONNECTOR PLUG	1	PAVCCZ
3	K2AHYH000010	AC-INLET	1	PAVCCZ △
4	K2CN3DH00006	AC CORD	1	TH-37/42PV70F/P TH-37/42PX70E △
4	K2CT3DH00018	AC CORD	1	TH-37/42PX70B △
5	MD37H10A1J	PLASMA DISPLAY PANEL	1	37 INCH △
5	MD42H10A1J	PLASMA DISPLAY PANEL	1	42 INCH △
6	TBX0E82301	CONTROL BUTTON	1	PAVCCZ
7	TBX0E82501	POWER BUTTON	1	PAVCCZ
8	TESD078	BUTTON SPRING	1	
	THEL0429	SCREW	29	
	THEL044N	SCREW	10	
	THEL047J	SCREW (HDMI : 2)	2	
	THTD011J	SCREW	2	
	THTF011N	SCREW	54	
9	TKGA5327	FRONT GLASS	1	PAVCCZ 37 INCH
9	TKGA5328	FRONT GLASS	1	PAVCCZ 42 INCH
10	TKK0E9520	ADJUSTMENT COVER	1	PAVCCZ
11	TKKC5270	PANEL LIGHT	1	PAVCCZ TH-37/42PV70F/P
11	TKKC5291	PANEL LIGHT	1	PAVCCZ TH-37/42PX70B/E
12	TKP0E21902	DOOR LID	1	PAVCCZ
	TKP0E22002	BOTTOM COVER	1	PAVCCZ
	TKP0E22102	SHEET HOLDER LEFT	1	PAVCCZ 42 INCH
	TKP0E22202	SHEET HOLDER RIGHT	1	PAVCCZ 42 INCH
	TKP0E22302	SHEET HOLDER LEFT	1	PAVCCZ 37 INCH
	TKP0E22402	SHEET HOLDER RIGHT	1	PAVCCZ 37 INCH
13	TKR0E0101-1	REAR COVER HANDLE	2	PAVCCZ
14	TKR0E0202	M8 SPACER CAP	4	PAVCCZ
15	TKR0E0402	INLET COVER	1	PAVCCZ △
	TKR0E0801	REAR COVER HOOK LEFT	1	PAVCCZ
	TKR0E0901	REAR COVER HOOK RIGHT	1	PAVCCZ
16	TKZ0E9423	STAND BRACKET	2	PAVCCZ
	TMK0E722	SPONGE (TKG/LEFT/RIGHT)	2	PAVCCZ 42 INCH
	TMK0E724	SPONGE (TKG/UPPER/BOTTOM)	2	PAVCCZ 37 INCH
	TMK0E729	SPONGE (TKG/UPPER/BOTTOM)	2	PAVCCZ 42 INCH
	TMK0E730	SPONGE (TKG/UPPER/BOTTOM)	2	PAVCCZ 37 INCH
	TMM0E301	M8 SPACER	4	PAVCCZ
17	TMM0E901	DOOR SPRING	1	PAVCCZ
	TMM17499	CLAMPER	1	△
	TMM25401	CLAMPER	1	42 INCH

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
	TMM7468-1	CLAMPER	1	
	TMME061	CLAMPER	5	42 INCH
	TMME061	CLAMPER	6	37 INCH
	TMME084	CLAMPER	1	
	TMME088	CLAMPER	1	
	TMME226	AC CORD CLAMPER	1	
	TMME260	CLAMPER	8	
	TMME289	CLAMPER	2	
	TMME292	CLAMPER	1	
	TMZ0E9804	SD CARD BRACKET	1	PAVCCZ
18	TPC0E69001	CARTON BOX TOP	1	PAVCCZ TH-42PX70B △
18	TPC0E69201	CARTON BOX TOP	1	PAVCCZ TH-37PX70B △
18	TPC0E69701	CARTON BOX TOP	1	PAVCCZ TH-37PV70F/P TH-37PX70E △
19	TPC0E69801	CARTON BOX BOTTOM	1	PAVCCZ TH-37PV70F/P TH-37PX70E
18	TPC0E80101	CARTON BOX TOP	1	PAVCCZ TH-42PV70F/P TH-42PX70E △
19	TPC0E80201	CARTON BOX BOTTOM	1	PAVCCZ TH-42PV70F/P TH-42PX70E
19	TPC0E81101	CARTON BOX BOTTOM	1	PAVCCZ TH-37PX70B
19	TPC0E81301	CARTON BOX BOTTOM	1	PAVCCZ TH-42PX70B
20	TPD0E0152	TOP CUSHION	1	PAVCCZ
21	TPD0E0153	BOTTOM CUSHION	1	PAVCCZ
22	TPD0E8007	STAND SPACER CUSHION	2	PAVCCZ TH-42PV70F/P TH-42PX70E
23	TPD0E9062	TOP PAD	1	PAVCCZ 37 INCH
23	TPD0E9063	TOP PAD	1	PAVCCZ 42 INCH
24	TPD0E9067	ACCESSORIES BOX	1	PAVCCZ
25	TPD0E9082	SPACER PAD	1	PAVCCZ TH-37PV70F/P TH-37PX70E
25	TPD0E9083	SPACER PAD	1	PAVCCZ TH-42PV70F/P TH-42PX70E
26	TPD169487	JOINT	4	
27	TPE0E4019-1	SET BAG	1	PAVCCZ
28	TQB0E0364	INSTRUCTION BOOK (ENGLISH)	1	PAVCCZ TH-37/42PX70B △
28	TQB0E0368A	INSTRUCTION BOOK (GERMAN)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368C	INSTRUCTION BOOK (ITALIAN)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368D	INSTRUCTION BOOK (FRENCH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368E	INSTRUCTION BOOK (SPANISH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368F	INSTRUCTION BOOK (SWEDISH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368H	INSTRUCTION BOOK (FINNISH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368K	INSTRUCTION BOOK (DANISH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368R	INSTRUCTION BOOK (CZECH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0368U	INSTRUCTION BOOK (ENGLISH)	1	PAVCCZ TH-37/42PX70E △
28	TQB0E0422A	INSTRUCTION BOOK (GERMAN)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0422B	INSTRUCTION BOOK (DUTCH)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0422C	INSTRUCTION BOOK (ITALIAN)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0422D	INSTRUCTION BOOK (FRENCH)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0422E	INSTRUCTION BOOK (SPANISH)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0422F	INSTRUCTION BOOK (SWEDISH)	1	PAVCCZ TH-37/42PV70F △

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
28	TQB0E0422K	INSTRUCTION BOOK (DANISH)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0422U	INSTRUCTION BOOK (ENGLISH)	1	PAVCCZ TH-37/42PV70F △
28	TQB0E0423M	INSTRUCTION BOOK (BILGARIA)	1	PAVCCZ TH-37/42PV70P △
28	TQB0E0423N	INSTRUCTION BOOK (ROMANIAN)	1	PAVCCZ TH-37/42PV70P △
28	TQB0E0423P	INSTRUCTION BOOK (POLISH)	1	PAVCCZ TH-37/42PV70P △
28	TQB0E0423Q	INSTRUCTION BOOK (HUNGARIA)	1	PAVCCZ TH-37/42PV70P △
28	TQB0E0423R	INSTRUCTION BOOK (CZECH)	1	PAVCCZ TH-37/42PV70P △
28	TQB0E0423U	INSTRUCTION BOOK (ENGLISH)	1	PAVCCZ TH-37/42PV70P △
	TQB0E0441	INSTRUCTION BOOK (PEDESTAL)	1	PAVCCZ TH-37/42PV70F TH-37/42PX70E △
	TQB0E0442	INSTRUCTION BOOK (PEDESTAL)	1	PAVCCZ TH-37/42PV70P △
	TSXL519	CABLE (C10-C20)	1	
	TSXL562	CABLE (D31-C11/D32-C21)	2	
	TSXL604	CABLE (SC20-D20)	1	
29	TTU0E0046	REAR COVER	1	PAVCCZ TH-37PX70B △
29	TTU0E0047	REAR COVER	1	PAVCCZ TH-42PX70B △
29	TTU0E0052	REAR COVER	1	PAVCCZ TH-37PV70F △
29	TTU0E0053	REAR COVER	1	PAVCCZ TH-42PV70F △
29	TTU0E0061	REAR COVER	1	PAVCCZ TH-37PX70E △
29	TTU0E0062	REAR COVER	1	PAVCCZ TH-42PX70E △
29	TTU0E0107	REAR COVER	1	PAVCCZ TH-37PV70P △
29	TTU0E0108	REAR COVER	1	PAVCCZ TH-42PV70P △
30	TTY0E0145	CABINET ASSY	1	PAVCCZ TH-37PX70B △
30	TTY0E0146	CABINET ASSY	1	PAVCCZ TH-42PX70B △
30	TTY0E0154	CABINET ASSY	1	PAVCCZ TH-37PX70E △
30	TTY0E0155	CABINET ASSY	1	PAVCCZ TH-42PX70E △
30	TTY0E0160	CABINET ASSY	1	PAVCCZ TH-37PV70F/P △
30	TTY0E0161	CABINET ASSY	1	PAVCCZ TH-42PV70F/P △
	TXJH12HNTB	SPEAKER LEAD (H12-SP)	1	PAVCCZ 42 INCH
	TXJH12HPTB	SPEAKER LEAD (H12-SP)	1	PAVCCZ 37 INCH
	XTB4+12GFJ	SCREW	45	
	XTB4+12GFJK	SCREW	12	
	XTB4+16GFJ	SCREW	2	
	XTV3+10JFJK	SCREW	6	
	XTW3+10TFJ	SCREW	3	
	XYN3+F10FJ	SCREW	1	
	XYN3+F8FJ	SCREW	24	
	XYN3+J12FJ	SCREW	26	
	XYN3+J6FJ	SCREW	1	
	XYN4+E8FJ	SCREW	1	
	XYN4+F10FJ	SCREW	9	
	XYN4+F10FJK	SCREW	6	
	XYN4+F30FJK	SCREW (BC)	6	
	XYN5+C15FJ	SCREW	8	
31	XZBT6506	POLY BAG	1	

16.9. Mechanical Replacement Parts List (stand)

Note:

All parts except parts mentioned [PAVCCZ] in the Remarks column are supplied by PAVC-CSG.

Parts mentioned [PAVCCZ] are supplied by PAVCCZ.

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
51	THEL051N	SCREW (FOR STAND POLE)	4	PAVCCZ
52	TPCC19401	CARTON BOX (STAND)	1	PAVCCZ
53	TPDA1589	CUSHION TOP L (STAND)	1	PAVCCZ
54	TPDA1590	CUSHION BOTTOM	1	PAVCCZ
55	TPEB305	EPE SHEET (STAND)	1	PAVCCZ
56	TXFBL010ZCS	STAND POLE A ASSY	1	PAVCCZ
57	TXFBL01HNTD	STAND BODY ASSY	1	PAVCCZ
58	TXFBL020ZCS	STAND POLE B ASSY	1	PAVCCZ
59	TXFBL02HNTD	SCREW ASSY	1	PAVCCZ
60	TXFBL03LPTU	SUPPORT METAL ASSY	1	PAVCCZ
61	TXFMM010ZCS	BAND ASSY	1	PAVCCZ
62	TXFMM01HNTD	TIP-PREVENTION PARTS	1	PAVCCZ
63	TXFPD01HNTD	CUSHION BOTTOM ASSY (STAND)	1	PAVCCZ
	XSS5+15FNK	SCREW (SUP-BRA)	4	PAVCCZ
	XTS4+12JFN	SCREW M4X12	7	
64	XYN5+F30FNK	SCREW (STAND-TV)	4	
	XYN5+J12FN	SCREW (BASE-BRA)	4	PAVCCZ
65	XZB9X16A04B	BAG	1	

16.10. Electrical Replacement Parts List (37inch)

Note:

All parts except parts mentioned [PAVCCZ] in the Remarks column are supplied by PAVC-CSG.

Parts mentioned [PAVCCZ] are supplied by PAVCCZ.

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
F401.402	K5D802BNA005	TIME LAG FUSE HIGH	2	△
C10	K1MN20BA0231	20P CONNECTOR	1	
C11	K1MN55BA0076	55P CONNECTOR	1	
C20	K1MN20BA0231	20P CONNECTOR	1	
C21	K1MN55BA0076	55P CONNECTOR	1	
C23	K1KA12BA0107	12P CONNECTOR	1	
C1102	F1J1A106A043	C 0.010UF, K, 16V	1	
C1103,04	F1G1C104A081	C 0.10UF, K, 16V	2	
C1106	F1H1H2700008	E 27UF, 50V	1	
C1107	F1H1H2200008	E 22UF, 50V	1	
C1108	F1G1C104A081	C 0.10UF, K, 16V	1	
C1109	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C1111	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C1112	F1G1C104A081	C 0.10UF, K, 16V	1	
C1114	F1G1C104A081	C 0.10UF, K, 16V	1	
C1117	F1G1C104A081	C 0.10UF, K, 16V	1	
C1122	F1G1E1030005	C 0.01UF, Z, 25V	1	
C1123	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C2005-08	F1H1H5610007	E 560UF, 50V	4	PAVCCZ
C2010-15	F1H1H5610007	E 560UF, 50V	6	PAVCCZ
C2021,22	F1H1H5610007	E 560UF, 50V	2	PAVCCZ
C2023	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2048-50	ECJ1XB1H104K	C 10PF, J, 50V	3	
C2052,53	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2054	F1J1A106A043	C 0.010UF, K, 16V	1	
C2055	ECJ1VC1H120J	C 12PF, J, 50V	1	
C2056	ECJ1VC1H080C	C 8PF, C, 50V	1	TH-37PX70B/E
C2056	ECJ1VC1H120J	C 12PF, J, 50V	1	TH-37PV70F/P
C2057,58	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2059	F2G0J470A019	E 47UF 6.3V	1	
C2060	F2G0J470A019	E 47UF 6.3V	1	TH-37PX70B/E
C2061	ECJ1XB1H104K	C 10PF, J, 50V	1	TH-37PX70B/E
C2062-64	F1J0J106A021	C 0.010UF, K, 16V	3	PAVCCZ TH-37PX70B/E
C2065	ECJ1XB1H104K	C 10PF, J, 50V	1	TH-37PX70B/E
C2068,69	ECJ1VB1H102K	C 1000UF, Z, 50V	2	TH-37PX70B/E
C2088	ECJ2FB1A475K	C 4.7UF, K, 10V	1	
C2089	F1H1H5610007	E 560UF, 50V	1	PAVCCZ
C2091	ECJ1VC1H100C	C 10PF, C, 50V	1	
C2092	F1H1H2200008	E 22UF, 50V	1	
C2096,97	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2100	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2101	F1J1A106A043	C 0.010UF, K, 16V	1	
C2102	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2103,04	F1J1A106A043	C 0.010UF, K, 16V	2	
C2105,06	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2107,08	F2G0J470A019	E 47UF 6.3V	2	
C2109,10	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2111	F1H0J2250008	C 2.2UF, K, 16V	1	
C2112,13	F2G0J470A019	E 47UF 6.3V	2	
C2114,15	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2116	F1H1H471A792	E 470UF, 50V	1	
C2117	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2118	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C2119	EEH1B1A221P	C 220PF, J, 10V	1	
C2120,21	F1H1H5600007	E 56UF, 50V	2	PAVCCZ
C2122,23	F1J1A106A043	C 0.010UF, K, 16V	2	
C2124	ECJ1XB1H104K	C 10PF, J, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C2126	F1J1A106A043	C 0.010UF, K, 16V	1	
C2127	ECJ1VB1C105K	C 0.01UF, K, 16V	1	TH-37PX70B/E
C2129	ECJ1VB1C105K	C 0.01UF, K, 16V	1	TH-37PX70B/E
C2130	F1J0J106A021	C 0.010UF, K, 16V	1	PAVCCZ
C2131	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2133	EEH1B1H4R7R	C 4.7PF, J, 50V	1	
C2134	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2135,36	ECJ1VB1C105K	C 0.01UF, K, 16V	2	
C2137	F2G0J470A019	E 47UF 6.3V	1	
C2138	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2139-42	F1J1A106A043	C 0.010UF, K, 16V	4	
C2143	F1H1H181A792	E 180UF, 50V	1	
C2146	F1H1H181A792	E 180UF, 50V	1	
C2147	EEH1B1C220R	C 22PF, J, 16V	1	
C2151	F2G0J470A019	E 47UF 6.3V	1	
C2153	ECJ1VC1H330J	C 33PF, J, 50V	1	
C2154	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2159,60	ECJ1VB1C105K	C 0.01UF, K, 16V	2	
C2161	EEH1B1C101UP	C 100PF, J, 16V	1	
C2162-65	ECJ1VB1C105K	C 0.01UF, K, 16V	4	
C2170	ECJ1VC1H330J	C 33PF, J, 50V	1	
C2171	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2173	ECJ2FF1C475Z	C 0.047UF, Z, 16V	1	
C2183	F1J1A106A043	C 0.010UF, K, 16V	1	
C2185	F1J1A106A043	C 0.010UF, K, 16V	1	
C2186	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2187	F1H0J2250008	C 2.2UF, K, 16V	1	
C2188	F1H1H471A792	E 470UF, 50V	1	
C2189	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C2190,91	F1J1A106A043	C 0.010UF, K, 16V	2	
C2192	F2G0J470A019	E 47UF 6.3V	1	
C2213	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2216	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2244	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2245	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2246	F1J1A106A043	C 0.010UF, K, 16V	1	
C2251	F1J1A106A043	C 0.010UF, K, 16V	1	
C2261-64	F1J1A106A043	C 0.010UF, K, 16V	4	
C2265-68	ECJ1XC1H101J	C 100PF, J, 50V	4	
C2272	ECJ2FF1C475Z	C 0.047UF, Z, 16V	1	
C2274	ECJ1XB1H104K	C 10PF, J, 50V	1	TH-37PX70B/E
C2280	ECJ2FB1A475K	C 4.7UF, K, 10V	1	
C2281	F1H1H5610007	E 560UF, 50V	1	PAVCCZ
C2288,89	F1J1A106A043	C 0.010UF, K, 16V	2	
C2301,02	ECJ1XB1C104K	C 0.1UF, Z, 16V	2	
C2303	F1J1E105A171	E 1 UF 25V	1	
C2305	F1J1E105A171	E 1 UF 25V	1	
C2307	F1J1E105A171	E 1 UF 25V	1	
C2309	F1J1E105A171	E 1 UF 25V	1	
C2311	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2313	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2315	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2317	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2319	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2321	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2323	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2325	F1J1H474A757	C 0.47UF, 50V	1	
C2327	ECJ1XB1H104K	C 10PF, J, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C2329	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2331	FLJ1H474A757	C 0.47UF, 50V	1	
C2333	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2335	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2337	FLH1H223A219	E 0.022UF, 50V	1	
C2339	FLH1H223A219	E 0.022UF, 50V	1	
C2341	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2343	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2345	FLH1H223A219	E 0.022UF, 50V	1	
C2347	FLH1H223A219	E 0.022UF, 50V	1	
C2349	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2352	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C2353	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2355	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2357	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2359	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2361	EEFGL1E471P	E 470UF, 25V	1	
C2363	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2365	EEHBC1C221UP	C 220PF, J, 16V	1	
C2375	FLH1H223A219	E 0.022UF, 50V	1	
C2377	FLH1H223A219	E 0.022UF, 50V	1	
C2379	FLH1H223A219	E 0.022UF, 50V	1	
C2381	FLH1H223A219	E 0.022UF, 50V	1	
C2383	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2385	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2387	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2389	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2502,03	ECJ2XB1H102K	C 1000PF, K, 50V	2	
C2512	FLK0J1060020	C 10UF, K, 6.3V	1	
C2515	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2517	ECJ1VB1H103K	C 0.001UF, K, 50V	1	TH-37PX70B/E
C2521	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2522-27	ECJ1VB1H102K	C 1000UF, Z, 50V	6	
C2601,02	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2801	ECJ3XB1C106M	C 1.0UF, K, 16V	1	
C2802,03	FLJ1H474A757	C 0.47UF, 50V	2	
C2813	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2814	ECJ1VB1H472K	C 4700PF, K, 50V	1	
C2815	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2816	EEHBC1V220P	E 22UF, 35V	1	
C2817	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2819	EEHBC1E470P	C 47PF, J, 25V	1	
C3001,02	ECJ1VB1H102K	C 1000UF, Z, 50V	2	
C3021	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C3024,25	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C3026	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3040	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3043	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C3047	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C3049-56	ECJ1VB1A105K	C 0.01UF, Z, 50V	8	
C3066	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	TH-37PX70B/E
C3068	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3070	EEHBC1C471UP	C 470PF, J, 16V	1	
C3071	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3072	EEHBC1C471UP	C 470PF, J, 16V	1	
C3075,76	EEHBC1C221UP	C 220PF, J, 16V	2	
C3081	F2H0J1010009	C 100UF, 6.3V	1	PAVCCZ
C3100-02	ECJ1VB1A105K	C 0.01UF, Z, 50V	3	
C3103	EEHBC1C100R	C 10PF, J, 16V	1	
C3115-17	ECJ1XB1H104K	C 10PF, J, 50V	3	
C3118	EEHBC1C470P	C 47PF, J, 16V	1	
C3119	EEHBC1C100R	C 10PF, J, 16V	1	
C3120	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3201	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3214	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3216	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3226-28	ECJ1XB1H104K	C 10PF, J, 50V	3	
C3230	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3263	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3265-68	ECJ1XB1H104K	C 10PF, J, 50V	4	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C3270	EEHBC0J102UP	C 1100PF, J, 6.3V	1	PAVCCZ
C3271	EEHBC1C100R	C 10PF, J, 16V	1	
C3272	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3273	F2G1H100A031	E 10UF, 50V	1	PAVCCZ
C3274-76	ECJ1XB1C104K	C 0.1UF, Z, 16V	3	
C3279	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C3280	ECJ1XC1H101J	C 100PF, J, 50V	1	
C3281	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C3750	FLJ1H102A721	E 1000UF, 50V	1	PAVCCZ
C4500-03	FLG1C104A081	C 0.10UF, K, 16V	4	
C4506,07	FLG1C104A081	C 0.10UF, K, 16V	2	
C4508,09	EEHBC0J330R	C 33PF, J, 6.3V	2	
C4510,11	FLG1C104A081	C 0.10UF, K, 16V	2	
C4515	FLG1C104A081	C 0.10UF, K, 16V	1	
C4527	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4528	FLG1C104A081	C 0.10UF, K, 16V	1	
C4531	FLG1C104A081	C 0.10UF, K, 16V	1	
C4533	FLG1H680A565	E 68UF, 50V	1	
C4534,35	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4537	ECJ1XB1H104K	C 10PF, J, 50V	1	
C4538	F2G0J470A019	E 47UF 6.3V	1	
C4539	FLJ1A106A043	C 0.010UF, K, 16V	1	
C4541	FLH1H471A219	E 470UF, 50V	1	
C4543-45	FLG1C104A081	C 0.10UF, K, 16V	3	
C4546	FLH0J2250008	C 2.2UF, K, 16V	1	
C4547	FLG1C104A081	C 0.10UF, K, 16V	1	
C4548,49	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4550	FLG1C104A081	C 0.10UF, K, 16V	1	
C4551,52	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4553	FLG1H1020008	E 1000UF, 50V	1	
C4555,56	FLJ1A106A043	C 0.010UF, K, 16V	2	
C4557	FLG1C104A081	C 0.10UF, K, 16V	1	
C4559,60	FLG1C104A081	C 0.10UF, K, 16V	2	
C4562	FLH1H822A219	E 8200UF, 50V	1	
C4563	ECJ1VB1C823K	C 0.082UF, K, 16V	1	
C4564,65	FLG1E1030005	C 0.01UF, Z, 25V	2	
C4566	ECJ1XB1C393K	C 0.039UF, K, 16V	1	
C4567	ECJ1XB1H104K	C 10PF, J, 50V	1	
C4568	FLG1C104A081	C 0.10UF, K, 16V	1	
C4569	FLJ1C684A097	C 0.68UF, Z, 16V	1	
C4570	F2G0J470A019	E 47UF 6.3V	1	
C4572,73	FLG1C104A081	C 0.10UF, K, 16V	2	
C4574	FLG1E1030005	C 0.01UF, Z, 25V	1	
C4575	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4576	F2G0J470A019	E 47UF 6.3V	1	
C4577,78	FLG1C104A081	C 0.10UF, K, 16V	2	
C4580	FLG1E1030005	C 0.01UF, Z, 25V	1	
C4581	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4582,83	FLG1C104A081	C 0.10UF, K, 16V	2	
C4584,85	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C4586	FLG1E1030005	C 0.01UF, Z, 25V	1	
C4587	FLG1C104A081	C 0.10UF, K, 16V	1	
C4588	ECJ1VB1C823K	C 0.082UF, K, 16V	1	
C4589	FLG1H150A565	E 15UF, 50V	1	
C4590	ECJ0EC1H180J	C 180PF, K, 50V	1	
C4591,92	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C4593	FLG1E1030005	C 0.01UF, Z, 25V	1	
C4595	FLG1E1030005	C 0.01UF, Z, 25V	1	
C4596	FLG1C104A081	C 0.10UF, K, 16V	1	
C4598	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4600,01	FLG1E1030005	C 0.01UF, Z, 25V	2	
C4602	FLG1C104A081	C 0.10UF, K, 16V	1	
C4604	FLH0J2250008	C 2.2UF, K, 16V	1	
C4605	FLG1C104A081	C 0.10UF, K, 16V	1	
C4607	F2G0J470A019	E 47UF 6.3V	1	
C4609	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4611	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C4612	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4613	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4614	F1G1C104A081	C 0.10UF, K, 16V	1	
C4615	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4616,17	F1G1C104A081	C 0.10UF, K, 16V	2	
C4618	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4619	F1G1C104A081	C 0.10UF, K, 16V	1	
C4620	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4623	F1G1C104A081	C 0.10UF, K, 16V	1	
C4624,25	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4628	F1G1C104A081	C 0.10UF, K, 16V	1	
C4629	F1J1A106A043	C 0.010UF, K, 16V	1	
C4807	F1G1C104A081	C 0.10UF, K, 16V	1	
C5501	F2A1C471A537	E 470UF, 16V	1	PAVCCZ
C5502	ECJ2VB1C104K	C 0.1UF, K, 16V	1	
C5503	F2A1C471A537	E 470UF, 16V	1	PAVCCZ
C5504	ECJ2VB1C104K	C 0.1UF, K, 16V	1	
C5521,22	ECJ2VB1C104K	C 0.1UF, K, 16V	2	
C5551	F2A1H331A257	E 330UF, 50V	1	
C5552	ECJ2VB1E104K	C 0.1UF, K, 25V	1	
C5595	ECA1HM220	E 22UF, 50V	1	
C5600	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C5601	F1G1C104A081	C 0.10UF, K, 16V	1	
C5602	ECGRLO680ER	C 68PF, J, 4V	1	
C5603,04	F1G1E1030005	C 0.01UF, Z, 25V	2	
C5605	F1J1A475A039	C 4.7UF, K, 10V	1	
C5606	F1H1H471A219	E 470UF, 50V	1	
C5607	F1G1H221A459	E 220UF, 50V	1	
C5608	F1G1C104A081	C 0.10UF, K, 16V	1	
C5609,10	EEEB1C470P	C 47PF, J, 16V	2	
C5615	F1J1A106A043	C 0.010UF, K, 16V	1	
C5616	ECJ0EB1A473K	C 0.047UF, K, 10V	1	
C5617	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C5618,19	F1J1A106A043	C 0.010UF, K, 16V	2	
C5620	ECJ1XB1H104K	C 10PF, J, 50V	1	
C5621	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5622	F1J1A475A039	C 4.7UF, K, 10V	1	
C5623	ECJ0EB1H471K	C 470PF, K, 50V	1	
C5624	F1G1H221A459	E 220UF, 50V	1	
C5625	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5626,27	F1G1C104A081	C 0.10UF, K, 16V	2	
C5628,29	ECGRLO680ER	C 68PF, J, 4V	2	
C5630,31	EEEB1C470P	C 47PF, J, 16V	2	
C5632	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C5636-41	F1G1C104A081	C 0.10UF, K, 16V	6	
C5643	ECJ1XB1H104K	C 10PF, J, 50V	1	
C5644	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5645	F1H1A225A051	E 22UF, 50V	1	
C5661	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5662	ECJ0EB1A473K	C 0.047UF, K, 10V	1	
C5663	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5670	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C5673,74	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C5676	F1G1C104A081	C 0.10UF, K, 16V	1	
C5690,91	F2G0J470A019	E 47UF 6.3V	2	
C5692,93	ECJ1XB1H104K	C 10PF, J, 50V	2	
C5694,95	F2G0J470A019	E 47UF 6.3V	2	
C5710-16	ECJ2VF1C104Z	C 0.1UF, Z, 16V	7	
C6001	F1L2J562A022	C 5600UF, K, 6.3V	1	
C6011-14	F2A2T201A002	E 200UF,	4	
C6021	F1L2J562A022	C 5600UF, K, 6.3V	1	
C6031	F0C2E225A218	E 0.022UF, 250V	1	
C6037	F1L1E4750004	C 4.7UF, 25V	1	
C6091	F1L2J1020001	C 1000UF, K, 6.3V	1	
C6111,12	F2A2D221A022	E 220UF, 200V	2	
C6132	F1L1E4750004	C 4.7UF, 25V	1	
C6134,35	F1L1E4750004	C 4.7UF, 25V	2	
C6151	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6152-54	F1L1E4750004	C 4.7UF, 25V	3	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C6193-95	F1L1E4750004	C 4.7UF, 25V	3	
C6197	F1L1E4750004	C 4.7UF, 25V	1	
C6201,02	F0C2E405A176	E 0.040UF, 250V	2	
C6209	F1L1E4750004	C 4.7UF, 25V	1	
C6211,12	F1L1E4750004	C 4.7UF, 25V	2	
C6213	F2A1E102A220	E 1000UF, 25V	1	
C6220	F1L2J1020001	C 1000UF, K, 6.3V	1	
C6221	ECJ2XB1H104K	C 0.1UF, K, 50V	1	
C6241	F2A1A101A439	E 100UF, 10V	1	
C6242	F1H1C105A072	C 1UF, K, 16V	1	
C6243	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6251	F1H1C105A072	C 1UF, K, 16V	1	
C6252	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6261,62	F2A2A221A073	E 220UF, 100V	2	
C6272,73	F2A1E221A487	E 220UF, 25V	2	
C6276	F1L1E4750004	C 4.7UF, 25V	1	
C6286-89	ECJ2XB1H104K	C 0.1UF, K, 50V	4	
C6401	F1L2J562A022	C 5600UF, K, 6.3V	1	
C6412-15	F2A2T201A002	E 200UF,	4	
C6421	F1L2J562A022	C 5600UF, K, 6.3V	1	
C6431	F0C2E405A176	E 0.040UF, 250V	1	
C6440	F1E2J102A002	C 1000PF, 600V	1	
C6460	F1E2J102A002	C 1000PF, 600V	1	
C6480	ECJ2XB1H104K	C 0.1UF, K, 50V	1	
C6502	F1L1E4750004	C 4.7UF, 25V	1	
C6504,05	F1L1E4750004	C 4.7UF, 25V	2	
C6521	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6522	F1L1E4750004	C 4.7UF, 25V	1	
C6524,25	F1L1E4750004	C 4.7UF, 25V	2	
C6527	F1L1E4750004	C 4.7UF, 25V	1	
C6531,32	F0C2E405A176	E 0.040UF, 250V	2	
C6561	F2A1A101A439	E 100UF, 10V	1	
C6562	F1H1C105A072	C 1UF, K, 16V	1	
C6563	F2A1A101A439	E 100UF, 10V	1	
C6564	F1H1C105A072	C 1UF, K, 16V	1	
C6565,66	ECJ2VB1H103K	C 0.01UF, K, 50V	2	
C6581	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6582	F1H1C105A072	C 1UF, K, 16V	1	
C6592	F2A1E221A487	E 220UF, 25V	1	
C6593	ECJ2XC1H102J	C 1000PF, J, 50V	1	
C6603,04	F1K2J102A014	C 1000UF, K, 6.3V	2	
C6605,06	F1L2J472A022	C 4700UF, K, 6.3V	2	
C6620,21	F1E2J222A002	C 2200PF, 600V	2	
C6641	ECQE2224KF3	P 2.2UF, K, 250V	1	PAVCCZ
C6661,62	F1K2J102A014	C 1000UF, K, 6.3V	2	
C6671	F1L1E4750004	C 4.7UF, 25V	1	
C6691	ECA2CM101	E 100UF, 160V	1	
C6694	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6695	ECJ2XC1H102J	C 1000PF, J, 50V	1	
C6702-06	ECJ2XB1H104K	C 0.1UF, K, 50V	5	
C6708	ECJ2XB1H104K	C 0.1UF, K, 50V	1	
C6721	ECA1HM101	E 100UF, 50V	1	
C6722	ECJ2XC1H101J	C 100PF, J, 50V	1	
C6723-25	F1L1E4750004	C 4.7UF, 25V	3	
C6726,27	F1H1C105A072	C 1UF, K, 16V	2	
C6740	ECJ2XC1H101J	C 100PF, J, 50V	1	
C6752	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6753	F1L1E4750004	C 4.7UF, 25V	1	
C6755,56	F1L1E4750004	C 4.7UF, 25V	2	
C6771	F1H1C105A072	C 1UF, K, 16V	1	
C6772,73	F1L1E4750004	C 4.7UF, 25V	2	
C6775	F1L1E4750004	C 4.7UF, 25V	1	
C6776,77	ECJ2XB1H104K	C 0.1UF, K, 50V	2	
C6791	F2A1E221A487	E 220UF, 25V	1	
C6795,96	F2A1E221A487	E 220UF, 25V	2	
C6801	F2A2E470A022	E 47UF, 250V	1	
C6803	ECKD3D221KBP	C 220PF, K, 2KV	1	
C6804	F2A2E100A022	E 10UF, 250V	1	
C6805	ECJ2XC1H331J	C 330PF, J, 50V	1	
C6806	ECA2CM101	E 100UF, 160V	1	
C6811	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6812	F1L1E4750004	C 4.7UF, 25V	1	
C6813	ECA2CM101	E 100UF, 160V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C6814	F2A1E221A487	E 220UF, 25V	1	
C6815	ECJ2XC1H102J	C 1000PF, J, 50V	1	
C6822	F2A2G470A018	E 470UF, 400V	1	
C6823	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6832	ECJ2XB1H392K	C 3900PF, K, 50V	1	
C6841	F2A2E470A022	E 47UF, 250V	1	
C6842	ECA2CM101	E 100UF, 160V	1	
C6845	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6861	F1H1C105A072	C 1UF, K, 16V	1	
C6862	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6863	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6871	F1H1C105A072	C 1UF, K, 16V	1	
C6872	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6873	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6901	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6902	TCUY1C105ZFN	C 1UF, 16V	1	
C6904	TCUY1C105ZFN	C 1UF, 16V	1	
C6906	TCUY1C105ZFN	C 1UF, 16V	1	
C6908	TCUY1C105ZFN	C 1UF, 16V	1	
C6910	TCUY1C105ZFN	C 1UF, 16V	1	
C6912	TCUY1C105ZFN	C 1UF, 16V	1	
C6921-26	F1L2E1040002	E 1000UF, 25V	6	
C6931	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6936	ECJ2XB1H681K	C 680PF, K, 50V	1	
C6937	ECJ2VB1H221K	C 220PF, K, 50V	1	
C6951	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6952	TCUY1C105ZFN	C 1UF, 16V	1	
C6954	TCUY1C105ZFN	C 1UF, 16V	1	
C6956	TCUY1C105ZFN	C 1UF, 16V	1	
C6958	TCUY1C105ZFN	C 1UF, 16V	1	
C6960	TCUY1C105ZFN	C 1UF, 16V	1	
C6962	TCUY1C105ZFN	C 1UF, 16V	1	
C6971-76	F1L2E1040002	E 1000UF, 25V	6	
C6981	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6986	ECJ2XB1H681K	C 680PF, K, 50V	1	
C6987	ECJ2VB1H221K	C 220PF, K, 50V	1	
C7110	F1H1C105A072	C 1UF, K, 16V	1	
C7114	F1H1C105A072	C 1UF, K, 16V	1	
C7116	F1H1C105A072	C 1UF, K, 16V	1	
C7117	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7118	F1K2A474A006	C 0.47UF, 6.3V	1	
C7121	F1H1C105A072	C 1UF, K, 16V	1	
C7123	F1H1C105A072	C 1UF, K, 16V	1	
C7124	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7125	F1K2A474A006	C 0.47UF, 6.3V	1	
C7126	F1H1C105A072	C 1UF, K, 16V	1	
C7127	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7128	F1K2A474A006	C 0.47UF, 6.3V	1	
C7130	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C7140	F1H1C105A072	C 1UF, K, 16V	1	
C7141	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7142	F1K2A474A006	C 0.47UF, 6.3V	1	
C7145	F1H1C105A072	C 1UF, K, 16V	1	
C7148	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C7150-53	F1K2A474A006	C 0.47UF, 6.3V	4	
C7203	F1H1C105A072	C 1UF, K, 16V	1	
C7207	F1H1C105A072	C 1UF, K, 16V	1	
C7209	F1H1C105A072	C 1UF, K, 16V	1	
C7210	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7211	F1K2A474A006	C 0.47UF, 6.3V	1	
C7214	F1H1C105A072	C 1UF, K, 16V	1	
C7216	F1H1C105A072	C 1UF, K, 16V	1	
C7217	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7218	F1K2A474A006	C 0.47UF, 6.3V	1	
C7219	F1H1C105A072	C 1UF, K, 16V	1	
C7220	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7221	F1K2A474A006	C 0.47UF, 6.3V	1	
C7229	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C7230-33	F1K2A474A006	C 0.47UF, 6.3V	4	
C7235	F1H1C105A072	C 1UF, K, 16V	1	
C7236	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7237	F1K2A474A006	C 0.47UF, 6.3V	1	
C7240	F1H1C105A072	C 1UF, K, 16V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C7242	F1K2A474A006	C 0.47UF, 6.3V	1	
C7244,45	ECJ1XB1C104K	C 0.1UF, Z, 16V	2	
C8001	F1G1C104A081	C 0.10UF, K, 16V	1	
C8002-05	F1H0J1050012	C 1UF, K, 16V	4	
C8006-08	F1G1C104A081	C 0.10UF, K, 16V	3	
C8009,10	F1J1A106A043	C 0.010UF, K, 16V	2	
C8011-14	F1G1C104A081	C 0.10UF, K, 16V	4	
C8015,16	F1H0J1050012	C 1UF, K, 16V	2	
C8017	F1J1A106A043	C 0.010UF, K, 16V	1	
C8018-21	F1G1C104A081	C 0.10UF, K, 16V	4	
C8022	F1H0J1050012	C 1UF, K, 16V	1	
C8023,24	F1J1A106A043	C 0.010UF, K, 16V	2	
C8025-29	F1G1C104A081	C 0.10UF, K, 16V	5	
C8030,31	F1H0J1050012	C 1UF, K, 16V	2	
C8032	F1J1A106A043	C 0.010UF, K, 16V	1	
C8033,34	F1G1C104A081	C 0.10UF, K, 16V	2	
C8035,36	F1J1A106A043	C 0.010UF, K, 16V	2	
C8037-41	F1G1C104A081	C 0.10UF, K, 16V	5	
C8042	ECGR10G680ER	C 68PF, J, 4V	1	
C8043-51	F1G1C104A081	C 0.10UF, K, 16V	9	
C8052	F1H0J1050012	C 1UF, K, 16V	1	
C8053	F1G1E1030005	C 0.01UF, Z, 25V	1	
C8056,57	F1G1C104A081	C 0.10UF, K, 16V	2	
C8058	F1J1A106A043	C 0.010UF, K, 16V	1	
C8067	F1G1E1030005	C 0.01UF, Z, 25V	1	
C8068	F1G1C104A081	C 0.10UF, K, 16V	1	
C8069	F1G1H820A565	E 82UF, 50V	1	
C8070-74	F1G1C104A081	C 0.10UF, K, 16V	5	
C8075	F1J0G2260001	C 0.001UF, 6.3V	1	PAVCCZ
C8076-80	F1G1C104A081	C 0.10UF, K, 16V	5	
C8301	F1G1E1030005	C 0.01UF, Z, 25V	1	TH-37PX70B/E
C8304	F1G1C104A081	C 0.10UF, K, 16V	1	TH-37PX70B/E
C8306	F1G1H1020008	E 1000UF, 50V	1	TH-37PX70B/E
C8307	F1G1C104A081	C 0.10UF, K, 16V	1	TH-37PX70B/E
C8309	F1G1C104A081	C 0.10UF, K, 16V	1	TH-37PX70B/E
C8310	EEH80G101R	C 100PF, J, 4V	1	TH-37PX70B/E
C8311,12	F1G1H100A565	C 100PF, K, 50V	2	TH-37PX70B/E
C8313,14	F1G1E1030005	C 0.01UF, Z, 25V	2	TH-37PX70B/E
C8316	F2G0J470A019	E 47UF 6.3V	1	TH-37PX70B/E
C8319-21	F1G1E1030005	C 0.01UF, Z, 25V	3	TH-37PX70B/E
C8322	F1G1C104A081	C 0.10UF, K, 16V	1	TH-37PX70B/E
C8323,24	F1G1H220A565	E 22UF, 50V	2	TH-37PX70B/E
C8325	F1G1E1030005	C 0.01UF, Z, 25V	1	TH-37PX70B/E
C8327,28	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	TH-37PX70B/E
C8329-36	F1G1E1030005	C 0.01UF, Z, 25V	8	TH-37PX70B/E
C8338,39	F1G1H220A565	E 22UF, 50V	2	TH-37PX70B/E
C8340	F1G1E1030005	C 0.01UF, Z, 25V	1	TH-37PX70B/E
C8402-10	F1G1C104A081	C 0.10UF, K, 16V	9	TH-37PX70B/E
C8411	F2G1A101A019	E 100UF, 10V	1	TH-37PX70B/E
C8412-14	F1G1C104A081	C 0.10UF, K, 16V	3	TH-37PX70B/E
C8416,17	F1G1E1030005	C 0.01UF, Z, 25V	2	TH-37PX70B/E
C8551,52	F1G1C104A081	C 0.10UF, K, 16V	2	
C8555	F1G1C104A081	C 0.10UF, K, 16V	1	
C8601	F1G1C104A081	C 0.10UF, K, 16V	1	
C8621,22	F1G1C104A081	C 0.10UF, K, 16V	2	
C8731	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9028,29	F1J1A106A043	C 0.010UF, K, 16V	2	
C9033,34	F1G1C104A083	C 0.10UF, K, 16V	2	
C9035,36	F1J1A106A043	C 0.010UF, K, 16V	2	
C9037	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9039	F1J1A106A043	C 0.010UF, K, 16V	1	
C9040	F1G1C104A083	C 0.10UF, K, 16V	1	
C9044	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9045-53	F1G1C104A083	C 0.10UF, K, 16V	9	
C9055-57	F1G1C104A083	C 0.10UF, K, 16V	3	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C9058	F1J1A106A043	C 0.010UF, K, 16V	1	
C9061	F1G1C104A077	C 0.10UF, K, 16V	1	
C9062	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9063	F1G1C104A083	C 0.10UF, K, 16V	1	
C9468	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9469	F1G1C104A083	C 0.10UF, K, 16V	1	
C9500	F1G1C104A077	C 0.10UF, K, 16V	1	
C9505	F1G1C104A077	C 0.10UF, K, 16V	1	
C9508	F1G1C104A077	C 0.10UF, K, 16V	1	
C9509,10	F1G1H120A565	E 12UF, 50V	2	
C9511	F1J1A106A043	C 0.010UF, K, 16V	1	
C9516-25	F1G1C104A077	C 0.10UF, K, 16V	10	
C9526	F1J1A106A043	C 0.010UF, K, 16V	1	
C9527,28	F1G1C104A077	C 0.10UF, K, 16V	2	
C9531	F1J1A106A043	C 0.010UF, K, 16V	1	
C9559-64	F1G1C104A077	C 0.10UF, K, 16V	6	
C9823	ECJ3YB1E106M	C 10 UF, K, 25V	1	
C9825	F1G1H101A565	C 100PF, K, 50V	1	
C9832	F1J1A106A043	C 0.010UF, K, 16V	1	
C9837	F1J1A106A043	C 0.010UF, K, 16V	1	
C9838	F1G1C104A083	C 0.10UF, K, 16V	1	
C9840	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9841-43	F1G1C104A083	C 0.10UF, K, 16V	3	
C9844	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9845,46	F1G1C104A083	C 0.10UF, K, 16V	2	
C9858	ECJ3YB1E106M	C 10 UF, K, 25V	1	
C9859	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9860	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9861,62	ECJ1VB1E104K	C 0.10UF, K, 25V	2	
C9863	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9864	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C9865,66	ECGR10G680ER	C 68PF, J, 4V	2	
C9867-72	ECJ3YB1E106M	C 10 UF, K, 25V	6	
C9873	ECGR10G680ER	C 68PF, J, 4V	1	
C9874	F1G1H680A565	E 68UF, 50V	1	
C9877	F1G1H680A565	E 68UF, 50V	1	
C9878	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9879,80	F1G1E822A086	C 8200UF, Z, 25V	2	
C9881	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9882	F1G1E822A086	C 8200UF, Z, 25V	1	
C9883	F1G1H101A565	C 100PF, K, 50V	1	
C9884,85	F1G1H1020008	E 1000UF, 50V	2	
C9886,87	ECJ1VB1E104K	C 0.10UF, K, 25V	2	
C9888	F1G1H361A565	E 360UF, 50V	1	
C9900-25	F1G1C104A077	C 0.10UF, K, 16V	26	
C9927-51	F1G1C104A077	C 0.10UF, K, 16V	25	
C9955-59	F1G1C104A077	C 0.10UF, K, 16V	5	
C9960-64	F1J1A106A043	C 0.010UF, K, 16V	5	
C9966,67	F1G1C104A077	C 0.10UF, K, 16V	2	
CB1-B8	K1MN68BA0052	68P CONNECTOR	8	
D5	K1KB31BA0064	31P CONNECTOR	1	
D6	K1KA21A00011	21P CONNECTOR	1	
D9	K1KA07A00292	7P CONNECTOR	1	
D20	K1KY30BA0090	30P CONNECTOR	1	
D25	K1KA13B00069	13P CONNECTOR	1	
D31,32	K1MN55BA0257	55P CONNECTOR	2	
D1100	MA704A	DIODE	1	
D1102	MA704A	DIODE	1	
D1107	MA704A	DIODE	1	
D2026	MA2J11100L	DIODE	1	
D2028,29	MA2J11100L	DIODE	2	
D2031-34	MA2J11100L	DIODE	4	
D2119	B0BC01100001	ZENER DIODE	1	
D2301,02	MA2J11100L	DIODE	2	
D2303	MA3056H	ZENER DIODE	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D2304	MA2J11100L	DIODE	1	
D2512	MA8043LTX	ZENER DIODE	1	
D2520	LNJ107W5PRW	LED	1	
D2524	MAZ80560ML	ZENER DIODE	1	
D2525B	LN1471YTR	LED	1	TH-37PX70B/E
D2526	MAZ80560ML	ZENER DIODE	1	TH-37PX70B/E
D2632,33	MA2J11100L	DIODE	2	
D2634	MA3X78900L	ZENER DIODE	1	
D2635	MA2J11100L	DIODE	1	
D2636	MA3047H	ZENER DIODE	1	
D2637	MA2J11100L	DIODE	1	
D2638	B0BC03900015	ZENER DIODE	1	
D3003-06	MA8140M	ZENER DIODE	4	
D3008-12	MA8140M	ZENER DIODE	5	
D3013,14	MAZ80560ML	ZENER DIODE	2	
D3025	MA8140M	ZENER DIODE	1	
D3027,28	MA8140M	ZENER DIODE	2	
D3030-32	MA8140M	ZENER DIODE	3	
D3038,39	MA8140M	ZENER DIODE	2	
D3044	B0BC01100001	ZENER DIODE	1	
D3100	MA8140M	ZENER DIODE	1	
D3102	MA2J11100L	DIODE	1	
D3334-38	MA2J11100L	DIODE	5	
D4500-12	EZAEG2A50AX	DIODE	13	
D4513	MA3056MTX	ZENER DIODE	1	
D4514	EZAEG2A50AX	DIODE	1	
D4515	MA3056MTX	ZENER DIODE	1	
D4516-23	EZAEG2A50AX	DIODE	8	
D4524-27	B0HCMM000014	DIODE	4	
D4528	EZAEG2A50AX	DIODE	1	
D4532	B0HCMM000014	DIODE	1	
D5517	MTZJ10B	ZENER DIODE	1	
D5518	MTZJT-7712B	ZENER DIODE	1	PAVCCZ
D5519	MTZJT-776.8B	ZENER DIODE	1	
D5521	MA2J11100L	DIODE	1	
D5522	MA3X152A0L	DIODE	1	
D5526	MA3X152A0L	DIODE	1	
D5528	MA8120M	ZENER DIODE	1	
D5529	MAZ80680LL	ZENER DIODE	1	
D5530	MA2J11100L	DIODE	1	
D5601,02	MA22D3900L	DIODE	2	
D5603,04	B0JCDD000002	DIODE	2	
D5605	MA22D3900L	DIODE	1	
D5606	B0JCDD000002	DIODE	1	
D5607,08	MA8024LTX	ZENER DIODE	2	
D5609	MA8056LTX	ZENER DIODE	1	
D5670	MA2J11100L	DIODE	1	
D5671	B0HCMM000014	DIODE	1	
D5673	B0HCMM000014	DIODE	1	
D5690,91	B0BC6R600005	ZENER DIODE	2	
D6001	B0HBSN000008	DIODE	1	
D6021	MA3DF30000LZ	ZENER DIODE	1	
D6024,25	B0ECP000003	DIODE	2	
D6032	MA2J11100L	DIODE	1	
D6061,62	MA3DF30000LZ	ZENER DIODE	2	
D6071,72	B0HBSN000008	DIODE	2	
D6082	MA3DF30000LZ	ZENER DIODE	1	
D6091	B0HBSN000008	DIODE	1	
D6092	B0ECP000003	DIODE	1	
D6101	B0JCME000037	DIODE	1	
D6104	B0JCME000037	DIODE	1	
D6131,32	B0ECP000003	DIODE	2	
D6151-53	B0ECP000003	DIODE	3	
D6191	B0ECP000003	DIODE	1	
D6193	B0ECP000003	DIODE	1	
D6211	B0JCME000037	DIODE	1	
D6221	B0ECP000003	DIODE	1	
D6222,23	MA2J11100L	DIODE	2	
D6253	LNJ301MPUJA	LED	1	
D6254	MAZ80510LL	ZENER DIODE	1	
D6255	MA2J11100L	DIODE	1	
D6273	MA2J11100L	DIODE	1	
D6275	MA8068M	ZENER DIODE	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D6276	MA3X152A0L	DIODE	1	
D6278	MA3X152A0L	DIODE	1	
D6280	MAZ80510LL	ZENER DIODE	1	
D6281	B0JCME000037	DIODE	1	
D6401,02	B0HBSN000008	DIODE	2	
D6422	MA3DF40000LZ	ZENER DIODE	1	
D6441	B0EHP000003	DIODE	1	
D6451	B0EHP000003	DIODE	1	
D6461,62	MA3DF30000LZ	ZENER DIODE	2	
D6466	MA2J11100L	DIODE	1	
D6471	B0HBSN000008	DIODE	1	
D6472	B0EHP000003	DIODE	1	
D6477	MA2J11100L	DIODE	1	
D6478	B0HCKS000002	DIODE	1	
D6480	MA2J11100L	DIODE	1	
D6481	MA3DF30000LZ	ZENER DIODE	1	
D6491	MA3DF40000LZ	ZENER DIODE	1	
D6497	B0EHP000003	DIODE	1	
D6501	B0EHP000003	DIODE	1	
D6503	B0EHP000003	DIODE	1	
D6521-23	B0EHP000003	DIODE	3	
D6583	LNJ301MPUJA	LED	1	
D6584	MAZ80510LL	ZENER DIODE	1	
D6585	MA2J11100L	DIODE	1	
D6604	MA2J11100L	DIODE	1	
D6605	MAZ80510LL	ZENER DIODE	1	
D6606	B0HCMM000014	DIODE	1	
D6607	MA2J11100L	DIODE	1	
D6619	B0HCKS000002	DIODE	1	
D6621	B0HDSM000006	DIODE	1	
D6623,24	B0HDSM000006	DIODE	2	
D6631,32	MA8240MTX	ZENER DIODE	2	
D6641,42	B0HCKS000002	DIODE	2	
D6643	B0JCME000037	DIODE	1	
D6644	B0HCKS000002	DIODE	1	
D6661	MA2J11100L	DIODE	1	
D6662-64	MA8330M	ZENER DIODE	3	
D6665	MAZ80510LL	ZENER DIODE	1	
D6666,67	MA2J11100L	DIODE	2	
D6670,71	B0JCME000037	DIODE	2	
D6690	MA2J11100L	DIODE	1	
D6691,92	MA8200M	ZENER DIODE	2	
D6701	MA8056H	ZENER DIODE	1	
D6702,03	MA2J11100L	DIODE	2	
D6721	B0HCKS000002	DIODE	1	
D6722	MA2J11100L	DIODE	1	
D6725	B0EHP000003	DIODE	1	
D6726-33	MA8056H	ZENER DIODE	8	
D6761	B0JCME000037	DIODE	1	
D6763	B0EHP000003	DIODE	1	
D6764	B0HCKS000002	DIODE	1	
D6765,66	B0EHP000003	DIODE	2	
D6773	B0HCKS000002	DIODE	1	
D6791	MA8200M	ZENER DIODE	1	
D6802	B0BC01000044	ZENER DIODE	1	
D6804	B0EHP000003	DIODE	1	
D6805	MA8240MTX	ZENER DIODE	1	
D6806	B0HCKS000002	DIODE	1	
D6809	B0HCMM000014	DIODE	1	
D6820-23	MA2J11100L	DIODE	4	
D6824,25	MA8330M	ZENER DIODE	2	
D6826	MA2J11100L	DIODE	1	
D6827,28	MA8330M	ZENER DIODE	2	
D6830	MA8056H	ZENER DIODE	1	
D6836	MAZ81500ML	ZENER DIODE	1	
D6837	MA2J11100L	DIODE	1	
D6838	B0BC027A0234	ZENER DIODE	1	
D6839	B0EHP000003	DIODE	1	
D6841	B0HCKS000002	DIODE	1	
D6842,43	MA2J11100L	DIODE	2	
D6859	B0EHP000003	DIODE	1	
D6860	B0HCKS000002	DIODE	1	
D6861	MAZ80510LL	ZENER DIODE	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D6862	MA2J11100L	DIODE	1	
D6871	MAZ80510LL	ZENER DIODE	1	
D6872	MA2J11100L	DIODE	1	
D6901,02	MA8056H	ZENER DIODE	2	
D6903,04	B0HCMM000013	DIODE	2	
D6951,52	MA8056H	ZENER DIODE	2	
D6953,54	B0HCMM000013	DIODE	2	
D7103-10	B0HCMM000014	DIODE	8	
D7201-08	B0HCMM000014	DIODE	8	
D9017-19	MA3033	ZENER DIODE	3	
D9020	B0JCCE000008	DIODE	1	
D9110	B0JCGD000002	DIODE	1	
D9802	B0JCCE000008	DIODE	1	
D9804	B0JCCE000008	DIODE	1	
D9807,08	B0JCCE000008	DIODE	2	
D9811	B0JCCE000008	DIODE	1	
D9812	MA22D3900L	DIODE	1	
D9813-15	B0JCGD000002	DIODE	3	
D9816,17	MA22D3900L	DIODE	2	
DG1	K1KA12B00151	12P CONNECTOR	1	PAVCCZ
DG2	K1KB23A00003	23P CONNECTOR	1	
DG5	K1KB31AA0140	31P CONNECTOR	1	
DG6	K1KB80AA0218	80P CONNECTOR	1	PAVCCZ
DG32	K1KA07AA0266	7P CONNECTOR	1	
DG33	K1KA11AA0153	11P CONNECTOR	1	
DG34	K1KA30AA0009	30P CONNECTOR	1	
FL2001,02	J0HABB000004	LC FILTER	2	
FL3001,02	J0HABB000003	LC FILTER	2	
FL3003-05	J0HABB000004	LC FILTER	3	
FL4800-02	J0JAD0000028	CHIP INDUCTOR	3	
FL5730	J0HABH000013	LC FILTER	1	
FL5732-34	J0HABH000013	LC FILTER	3	
FL7101	J0HABH000013	LC FILTER	1	
FL7201	J0HABH000013	LC FILTER	1	
FL9300,01	FLJ1E104A148	C 0.10UF, Z, 25V	2	
FL9504	FLJ1E104A148	C 0.10UF, Z, 25V	1	
FL9803	FLJ1E104A148	C 0.10UF, Z, 25V	1	
FL9805,06	FLJ1E104A148	C 0.10UF, Z, 25V	2	
FL9900-04	FLJ1E104A148	C 0.10UF, Z, 25V	5	
GK1	K1KY12B00001	12P CONNECTOR	1	
GK2	K1KY14B00002	14P CONNECTOR	1	PAVCCZ
H2	K1KA23A00003	23P CONNECTOR	1	
H3,H4	K1KA23A00005	23P CONNECTOR	2	
H6	K1KB80AA0218	80P CONNECTOR	1	PAVCCZ
H12	K1KA04AA0190	4P CONNECTOR	1	
H15	K1KA04AA0150	4P CONNECTOR	1	
IC1100	MNZSFD7GP42	IC	1	
IC1101	TVRP464	IC	1	PAVCCZ
IC2002	C0FBBY000027	IC	1	TH-37PX70B/E
IC2006	C0JBAZ002261	IC	1	TH-37PX70B/E
IC2008	C0CBCBE00001	IC	1	
IC2010	C0CBCBC00190	IC	1	
IC2011	C0ABBB000230	IC	1	
IC2106	C1AB00002746	IC	1	PAVCCZ
IC2107	C0DBFFD00003	IC	1	
IC2301	C1AB00002730	IC	1	
IC2303	C0DBGYY00202	IC	1	
IC2601	C0JBAU000034	IC	1	
IC2610	C0DBAJB00004	IC	1	
IC3001	AN15876A-VT	IC	1	
IC3101	AN15862A-VT	IC	1	
IC4500	TVRP317	IC	1	PAVCCZ
IC4501	TVRP316	IC	1	PAVCCZ
IC4504	C3EBEY000009	IC	1	
IC4506	C0DBGGF00001	IC	1	
IC4507	C0CBCBC00190	IC	1	
IC4508,09	C0CBCAD00082	IC	2	
IC4510	C1AB00002753	IC	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
IC4515	NJM2903V	IC	1	
IC4800	C1ZBZ0003577	IC	1	
IC5550	EHMDD9851	LINEAR IC	1	
IC5600	C0DBAYY00273	IC	1	
IC5601	C0DBAYY00274	IC	1	
IC5660	C0EBM0000026	IC	1	
IC5670	C0CBCBC00190	IC	1	
IC5671	C0EBF0000376	IC	1	
IC6131	C0ZBZ0000895	IC	1	
IC6151	C0ZBZ0001324	IC	1	
IC6191	C0ZBZ0000895	IC	1	
IC6211	C0ZBZ0001325	IC	1	
IC6221	C0DBEMC00043	IC	1	
IC6241	C0JBAZ000005	IC	1	
IC6251	NJM2903M	INTEGRATED CIRCUIT	1	
IC6471	C0DBEKA00003	IC	1	
IC6472	C0JBAA000377	IC	1	
IC6501	C0ZBZ0000895	IC	1	
IC6521	C0ZBZ0001324	IC	1	
IC6561,62	C0JBAZ000005	IC	2	
IC6581	NJM2903M	INTEGRATED CIRCUIT	1	
IC6671	C0ZBZ0001325	IC	1	
IC6721,22	C0JBAZ000994	IC	2	
IC6724,25	C0CBADC00072	IC	2	
IC6752	C0ZBZ0001324	IC	1	
IC6771	C0CBADC00072	IC	1	
IC6772	C0ZBZ0001325	IC	1	
IC6773,74	C0JBAA000377	IC	2	
IC6791	N0BF1FB00001	IC	1	
IC6801,02	C0DBEMC00043	IC	2	
IC6803	C5HABZZ00165	IC	1	
IC6821	C0DBEMC00043	IC	1	
IC6841	C0DBEMC00043	IC	1	
IC6861	NJM2903M	INTEGRATED CIRCUIT	1	
IC6871	NJM2903M	INTEGRATED CIRCUIT	1	
IC6901-06	AN16077A-VT	IC	6	PAVCCZ
IC6951-56	AN16077A-VT	IC	6	PAVCCZ
IC7101,02	C0JBAA0001120	IC	2	
IC7201,02	C0JBAZ0001120	IC	2	
IC7204	C0JBAZ0001120	IC	1	
IC8001	MN2WS0039A	IC	1	PAVCCZ
IC8002,03	C3ABRG000080	IC	2	
IC8004	C0ZBZ0001030	IC	1	
IC8301	C1AB00002710	IC	1	PAVCCZ TH-37PX70B/E
IC8302	C0CBCAD00082	IC	1	TH-37PX70B/E
IC8401	C0JBAZ002800	IC	1	TH-37PX70B/E
IC8402	C0JBAZ0001120	IC	1	TH-37PX70B/E
IC8403	C0ZBZ0001333	IC	1	TH-37PX70B/E
IC8404-07	C0JBAZ0001120	IC	4	TH-37PX70B/E
IC8408,09	C0JBAU0000025	IC	2	PAVCCZ TH-37PX70B/E
IC8554	TVRP280	IC	1	PAVCCZ
IC8601	TVRP301	IC	1	PAVCCZ TH-37PX70E
IC8601	TVRP299	IC	1	PAVCCZ TH-37PX70B
IC8601	TVRP300	IC	1	PAVCCZ TH-37PV70F
IC8601	TVRP473	IC	1	PAVCCZ TH-37PV70P
IC8621,22	C0JBAZ002845	IC	2	PAVCCZ
IC9001	TVRP206-1	IC	1	PAVCCZ
IC9002	C1ZBZ0003577	IC	1	
IC9003	MNZSFC9GPH2	IC	1	PAVCCZ
IC9007	TVRP210-1	IC	1	PAVCCZ
IC9011	C0EBF0000431	IC	1	
IC9013	C0JBAZ002060	IC	1	
IC9200	C1ZBZ0003600	IC	1	
IC9303	TVRP214	IC	1	PAVCCZ
IC9500	C1ZBZ0003575	IC	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
IC9802,03	C0JBAA0001120	IC	2	
IC9805	C0DBAYY00274	IC	1	
IC9806	C0DBAYY00273	IC	1	
IC9900	MN84524	IC	1	
IC9901	C3ABQJ0000055	IC	1	
JA2	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
JA4-A8	ERJ6GEY0R00V	M 0 OHM, 1/10W	5	
JK2002	K2HA204A0041	JACK	1	
JK3001	K1FB315A0006	CONNECTOR	1	
JK3002,03	K1FB121A0010	CONNECTOR	2	PAVCCZ
JK3005	K2HA511A0002	JACK	1	PAVCCZ
JK4500,01	K1FY119D0002	CONNECTOR	2	
JK8401	K1NA68B00044	68P CONNECTOR	1	PAVCCZ TH-37PX70B/E
JK8801	K1NA09D00004	9P CONNECTOR	1	
JS1100	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PV70F/P TH-37PX70E
JS1101	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PX70B
JS1106	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PX70E
JS1115	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PV70P
JS1116	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PV70F
JS2031-33	J0JCC0000100	CHIP INDUCTOR	3	
JS2046	J0JCC0000100	CHIP INDUCTOR	1	
JS2048,49	J0JCC0000100	CHIP INDUCTOR	2	
JS2051	J0JCC0000100	CHIP INDUCTOR	1	
JS2059-62	J0JCC0000100	CHIP INDUCTOR	4	
JS2064	J0JCC0000100	CHIP INDUCTOR	1	
JS2096	J0JCC0000100	CHIP INDUCTOR	1	
JS2515	J0JCC0000100	CHIP INDUCTOR	1	TH-37PV70F/P
JS2516	J0JCC0000100	CHIP INDUCTOR	1	TH-37PX70B/E
JS3002	J0JCC0000100	CHIP INDUCTOR	1	TH-37PX70B/E
JS3005	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
JS3007-16	ERJ6GEY0R00V	M 0 OHM, 1/10W	10	
JS3018-20	ERJ6GEY0R00V	M 0 OHM, 1/10W	3	
JS3023	J0JCC0000100	CHIP INDUCTOR	1	
JS3032	J0JCC0000100	CHIP INDUCTOR	1	
JS3040-43	ERJ6GEY0R00V	M 0 OHM, 1/10W	4	
JS3053	J0JCC0000100	CHIP INDUCTOR	1	TH-37PV70F/P
JS3206	J0JCC0000100	CHIP INDUCTOR	1	
JS3208	J0JCC0000100	CHIP INDUCTOR	1	
JS3213	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
JS4501	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
K1	K1KY12B00001	12P CONNECTOR	1	
L1100	J0JHC0000078	CHIP INDUCTOR	1	
L2001,02	J0JCC0000364	CHIP INDUCTOR	2	
L2003-10	J0JCC0000100	BEAD CHOKE	8	
L2015,16	J0JCC0000100	BEAD CHOKE	2	
L2021	J0JHC0000078	CHIP INDUCTOR	1	
L2022	J0JHC0000078	CHIP INDUCTOR	1	TH-37PX70B/E
L2022	J0JCC0000100	CHIP INDUCTOR	1	TH-37PV70F/P
L2026	G1C6R8MA0061	INDUCTION COIL	1	
L2027	J0JHC0000045	CHIP INDUCTOR	1	
L2029	J0JCC0000077	CHIP INDUCTOR	1	
L2039,40	J0JHC0000045	CHIP INDUCTOR	2	
L2300	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2302	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2304	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2306	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2308	J0JJC0000011	CHIP INDUCTOR	1	
L2310	J0JJC0000011	CHIP INDUCTOR	1	
L2647	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
L2648	G1C470MA0077	INDUCTION COIL	1	
L2649	G1C100MA0072	INDUCTION COIL	1	
L2650	G1C3R3ZA0083	INDUCTION COIL	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
L3001,02	J0JCC0000100	BEAD CHOKE	2	
L3004	G1C101M00018	INDUCTION COIL	1	
L3206-08	J0JCC0000241	CHIP INDUCTOR	3	
L3209	J0JGC0000021	CHIP INDUCTOR COIL	1	
L3210	J0JCC0000241	CHIP INDUCTOR	1	
L3211	J0JGC0000021	CHIP INDUCTOR COIL	1	
L4500-07	J0JHC0000078	CHIP INDUCTOR	8	
L4511	J0JHC0000078	CHIP INDUCTOR	1	
L4512	J0JCC0000077	CHIP INDUCTOR	1	
L4516-18	J0JHC0000078	CHIP INDUCTOR	3	
L4520,21	J0JHC0000078	CHIP INDUCTOR	2	
L4524	J0JHC0000078	CHIP INDUCTOR	1	
L5550	TALL08N2R7MA	INDUCTION COIL	1	
L5551,52	G0C150MA0056	PEAKING COIL	2	
L5564	TALL08N2R7MA	INDUCTION COIL	1	
L5565	G0A220GA0002	CHOKE COIL	1	
L5566	TALL08N2R7MA	INDUCTION COIL	1	
L5600,01	G1C2R2ZA0083	INDUCTION COIL	2	
L5602	G1C3R3ZA0083	INDUCTION COIL	1	
L5604	G1C100MA0077	INDUCTION COIL	1	
L5605	J0JCC0000241	CHIP INDUCTOR	1	
L5606	G1C100MA0077	INDUCTION COIL	1	
L5610,11	J0JHC0000035	CHIP INDUCTOR	2	
L5670	J0JHC0000078	CHIP INDUCTOR	1	
L5690,91	J0JHC0000078	CHIP INDUCTOR	2	
L5692	J0JCC0000241	CHIP INDUCTOR	1	
L5735	J0JHC0000078	CHIP INDUCTOR	1	
L6000	J0JJC0000015	CHIP INDUCTOR	1	
L6001-03	ELC12P2R2E	CHOKE COIL	3	
L6010	J0JJC0000015	CHIP INDUCTOR	1	
L6011-13	ELC12P2R2	CHOKE COIL	3	
L6061-64	J0JKB0000049	FLAT CORE	4	
L6083,84	J0JKB0000049	FLAT CORE	2	
L6101	J0JJC0000015	CHIP INDUCTOR	1	
L6103	G0ZZ00002183	PEAKING COIL	1	
L6106	J0JJC0000015	CHIP INDUCTOR	1	
L6212	J0JJC0000015	CHIP INDUCTOR	1	
L6221	G0ZZ00002183	PEAKING COIL	1	
L6241	G0ZZ00002183	PEAKING COIL	1	
L6262	G0ZZ00002183	PEAKING COIL	1	
L6271	G0ZZ00002183	PEAKING COIL	1	
L6401-03	ELC12P2R2E	CHOKE COIL	3	
L6411-13	ELC12P2R2	CHOKE COIL	3	
L6461-64	J0JKB0000049	FLAT CORE	4	
L6472	G0ZZ00002183	PEAKING COIL	1	
L6474	G0ZZ00002183	PEAKING COIL	1	
L6481,82	J0JKB0000049	FLAT CORE	2	
L6591,92	G0ZZ00002183	PEAKING COIL	2	
L6601,02	G0ZZ00002183	PEAKING COIL	2	
L6690	G0ZZ00002183	PEAKING COIL	1	
L8001-05	J0JHC0000045	CHIP INDUCTOR	5	
L8006	J0JCC0000100	CHIP INDUCTOR	1	
L8007-10	J0JHC0000045	CHIP INDUCTOR	4	
L8301,02	J0JHC0000045	CHIP INDUCTOR	2	TH-37PX70B/E
L8304	J0JHC0000045	CHIP INDUCTOR	1	TH-37PX70B/E
L8551	J0JCC0000241	CHIP INDUCTOR	1	
L8621	J0JCC0000241	CHIP INDUCTOR	1	
L9500	G1C150KA0038	INDUCTION COIL	1	
L9501,02	J0JHC0000078	CHIP INDUCTOR	2	
L9504,05	J0JHC0000078	CHIP INDUCTOR	2	
L9800	G1C2R2Z00007	INDUCTION COIL	1	
L9801	G1C1R5Z00006	INDUCTION COIL	1	
L9802	G1C2R2Z00007	INDUCTION COIL	1	
NP	TNPA4177AD	CIRCUIT BOARD H	1	PAVCCZ TH-37PX70B/E △
NP	TNPA4177AH	CIRCUIT BOARD H	1	PAVCCZ TH-37PV70F/P △
NP	TZTNP01HNTD	CIRCUIT BOARD DG	1	PAVCCZ TH-37PX70E △
NP	TXNDG1HNTB	CIRCUIT BOARD DG	1	PAVCCZ TH-37PX70B △

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
NP	TXNDG1KYTE	CIRCUIT BOARD DG	1	PAVCCZ TH-37PV70F △
NP	TZTNP01MFTE	CIRCUIT BOARD DG	1	PAVCCZ TH-37PV70P △
NP	TNPA4178AC	CIRCUIT BOARD PA	1	PAVCCZ △
NP	TNPA4167AB	CIRCUIT BOARD C1	1	PAVCCZ △
NP	TNPA4168AB	CIRCUIT BOARD C2	1	PAVCCZ △
NP	TZTNP01HPTB	CIRCUIT BOARD D	1	PAVCCZ △
NP	TNPA4268AE	CIRCUIT BOARD P	1	PAVCCZ △
NP	TNPA4182AE	CIRCUIT BOARD SC	1	PAVCCZ △
NP	TNPA4195AB	CIRCUIT BOARD SD	1	PAVCCZ △
NP	TNPA4183AE	CIRCUIT BOARD SS	1	PAVCCZ △
NP	TNPA4194AB	CIRCUIT BOARD SU	1	PAVCCZ △
NP	TNPA4283AB	CIRCUIT BOARD GK	1	PAVCCZ △
NP	TNPA4137AH	CIRCUIT BOARD K	1	PAVCCZ TH-37PX70B/E △
NP	TNPA4137AG	CIRCUIT BOARD K	1	PAVCCZ TH-37PV70F/P △
NP	TNPA4138AC	CIRCUIT BOARD S	1	PAVCCZ △
PA3,A4	K1KB23A00004	23P CONNECTOR	2	
PA5	K1KA23A00005	23P CONNECTOR	1	
PA9800	K5H4022A0023	FUSE	1	
PA9900	K5H5022A0023	FUSE	1	
PAMM3	TMME047	CLAMPER	1	
PAMM7	TMME047	CLAMPER	1	
PAMM11,12	TMME300	CLAMPER	2	
PC6480	B3PBA0000223	IC	1	
PC6701,02	B3PBA0000233	IC	2	
PC6704	B3PBA0000234	IC	1	
PC6705	B3PBA0000397	IC	1	
PC6801	B3PBA0000223	IC	1	
PC6861	B3PBA0000223	IC	1	
PC6871	B3PBA0000223	IC	1	
Q1107,08	2SD0601ARL	TRANSISTOR	2	
Q2000,01	2SD0601ARL	TRANSISTOR	2	
Q2002-07	2SC584500L	TRANSISTOR	6	
Q2015	2SA207700L	TRANSISTOR	1	
Q2016,17	2SC584500L	TRANSISTOR	2	
Q2021	2SA207700L	TRANSISTOR	1	
Q2031	2SA207700L	TRANSISTOR	1	
Q2033	2SA207700L	TRANSISTOR	1	
Q2034,35	2SC584500L	TRANSISTOR	2	
Q2039-41	2SC584500L	TRANSISTOR	3	
Q2101,02	2SC584500L	TRANSISTOR	2	
Q2301	2SA207700L	TRANSISTOR	1	
Q2510,11	2SD0601ARL	TRANSISTOR	2	
Q2513	2SD0601ARL	TRANSISTOR	1	
Q2518	2SD0601ARL	TRANSISTOR	1	TH-37PX70B/E
Q2635	2SC584500L	TRANSISTOR	1	
Q2636,37	2SA207700L	TRANSISTOR	2	
Q2638	2SC584500L	TRANSISTOR	1	
Q2639	2SK3065T100	FET	1	
Q3027,28	2SA207700L	TRANSISTOR	2	
Q3031,32	2SC584500L	TRANSISTOR	2	
Q3200	2SA207700L	TRANSISTOR	1	
Q4500-05	2SD0601ARL	TRANSISTOR	6	
Q4514-17	2SB0709ARL	TRANSISTOR	4	
Q4519	2SB0709ARL	TRANSISTOR	1	
Q5501	2SD0601ARL	TRANSISTOR	1	
Q5521,22	2SA207700L	TRANSISTOR	2	
Q5523,24	2SD0601ARL	TRANSISTOR	2	
Q5561	B1DHDC000028	TRANSISTOR	1	
Q5562	2SD0601ARL	TRANSISTOR	1	
Q5600-02	B1MBEDA00015	TRANSISTOR	3	
Q5603,04	2SD0601ARL	TRANSISTOR	2	
Q5690,91	2SD0601ARL	TRANSISTOR	2	
Q5692,93	B1DHDC000028	TRANSISTOR	2	
Q6001-03	B1JADN000001	TRANSISTOR	3	
Q6021-23	B1JADN000001	TRANSISTOR	3	
Q6031	B1ADRD000001	TRANSISTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
Q6041,42	B1JADN000003	TRANSISTOR	2	
Q6052	B1JADN000003	TRANSISTOR	1	
Q6101	B1DFKM000002	TRANSISTOR	1	
Q6103	B1ABNF000006	TRANSISTOR	1	
Q6104	B1ADNF000006	TRANSISTOR	1	
Q6106	B1DFKM000002	TRANSISTOR	1	
Q6111	B1DFKM000001	TRANSISTOR	1	
Q6114	B1DFKM000001	TRANSISTOR	1	
Q6141	B1ABNF000006	TRANSISTOR	1	
Q6142	B1ADNF000006	TRANSISTOR	1	
Q6146	B1ABNF000006	TRANSISTOR	1	
Q6147	B1ADNF000006	TRANSISTOR	1	
Q6171	B1ABRD000003	TRANSISTOR	1	
Q6172	B1ADRD000001	TRANSISTOR	1	
Q6181	B1ABRD000003	TRANSISTOR	1	
Q6222	2SC1473AEA	TRANSISTOR	1	
Q6251	2SD0601ARL	TRANSISTOR	1	
Q6256	2SD1263A	TRANSISTOR	1	
Q6271	2SD0601ARL	TRANSISTOR	1	
Q6401-03	B1JADN000001	TRANSISTOR	3	
Q6421-23	B1JADP000003	TRANSISTOR	3	
Q6441,42	B1JADN000003	TRANSISTOR	2	
Q6451	B1JADP000003	TRANSISTOR	1	
Q6501	B1ABNF000006	TRANSISTOR	1	
Q6502	B1ADNF000006	TRANSISTOR	1	
Q6521	B1ABNF000006	TRANSISTOR	1	
Q6522	B1ADNF000006	TRANSISTOR	1	
Q6531	B1ABRD000003	TRANSISTOR	1	
Q6532	B1ADRD000001	TRANSISTOR	1	
Q6551	B1ABRD000003	TRANSISTOR	1	
Q6552	B1ADRD000001	TRANSISTOR	1	
Q6581	2SD0601ARL	TRANSISTOR	1	
Q6601	B1DFES000003	TRANSISTOR	1	
Q6602	2SD0601ARL	TRANSISTOR	1	
Q6603	2SB0709ARL	TRANSISTOR	1	
Q6621,22	2SK399500L	FET	2	
Q6642-44	2SK399500L	FET	3	
Q6646-48	2SK399500L	FET	3	
Q6661	B1DEET000002	TRANSISTOR	1	
Q6662	2SD0601ARL	TRANSISTOR	1	
Q6665	B1ABNF000006	TRANSISTOR	1	
Q6671,72	B1DFDR000001	TRANSISTOR	2	
Q6679	B1ABNF000006	TRANSISTOR	1	
Q6680	B1ADNF000006	TRANSISTOR	1	
Q6690	2SA19610Q0HW	TRANSISTOR	1	
Q6742,43	2SD0601ARL	TRANSISTOR	2	
Q6762	B1ADNF000006	TRANSISTOR	1	
Q6781	B1ABNF000006	TRANSISTOR	1	
Q6782	B1ADNF000006	TRANSISTOR	1	
Q6791	2SD0601ARL	TRANSISTOR	1	
Q6805	2SC3063	TRANSISTOR	1	
Q6806	2SC1473AEA	TRANSISTOR	1	
Q6821,22	2SD1263A	TRANSISTOR	2	
Q6824	2SD0601ARL	TRANSISTOR	1	
Q6841	2SD1263A	TRANSISTOR	1	
Q6842	2SC1473AEA	TRANSISTOR	1	
Q8401,02	2SD0601ARL	TRANSISTOR	2	TH-37PX70B/E
Q9010	2SD0601ARL	TRANSISTOR	1	
Q9044	2SD0601ARL	TRANSISTOR	1	
Q9046	2SD0601ARL	TRANSISTOR	1	
Q9050-54	2SD0601ARL	TRANSISTOR	5	
Q9301,02	2SD0601ARL	TRANSISTOR	2	
Q9805,06	2SD0601ARL	TRANSISTOR	2	
Q9807-09	B1MBEDA00015	TRANSISTOR	3	
R1104	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1110	ERJ2GEJ273	M 27KOHM, J, 0.063W	1	
R1122	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1124,25	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R1126	ERJ2GEJ273	M 27KOHM, J, 0.063W	1	
R1134	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1140	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1144	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1146	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	
R1147	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1153	ERJ2GEJ821	M 820 OHM, J, 0.063W	1	
R1162	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1163	ERJ2GEJ105	M 1MOHM, J, 0.063W	1	
R1164	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R1165	ERJ2GEJ182	M 1.8KOHM, J, 0.063W	1	
R1166	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R1169	ERJ2GED563X	M 56KOHM, J, 0.063W	1	
R1170	ERJ2GEJ273	M 27KOHM, J, 0.063W	1	
R1171	ERJ2GED563X	M 56KOHM, J, 0.063W	1	
R1172	ERJ2GEJ273	M 27KOHM, J, 0.063W	1	
R1174,75	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R1179	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1181	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1182	ERJ2GEJ273	M 27KOHM, J, 0.063W	1	
R1183,84	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R1185,86	ERJ2GEJ101	M 100 OHM, J, 0.063W	2	
R1194	ERJ2GED563X	M 56KOHM, J, 0.063W	1	
R1195	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R1196	ERJ2GEJ333	M 33KOHM, J, 0.063W	1	
R1199	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1200,01	ERJ2GEJ562	M 5.6KOHM, J, 0.063W	2	
R1203	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1204	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R1205,06	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R1209	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R1216	ERJ2GEJ333	M 33KOHM, J, 0.063W	1	
R1217	ERJ2GED563X	M 56KOHM, J, 0.063W	1	
R1218-20	ERJ2GEJ103	M 10KOHM, J, 0.063W	3	
R1221	ERJ3EKF7151	M 7.15KOHM, 1/16W	1	
R1222-28	ERJ2GEJ473	M 47KOHM, J, 0.063W	7	
R1229	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1231-34	ERJ2GEJ473	M 47KOHM, J, 0.063W	4	
R1235	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R1236,37	ERJ2GEJ473	M 47KOHM, J, 0.063W	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R1239	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1241	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1243-47	ERJ2GEJ473	M 47KOHM, J, 0.063W	5	
R1255	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	
R2001	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R2006	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R2007	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2010-15	ERJ2GEJ473	M 47KOHM, J, 0.063W	6	
R2018	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2020	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2023	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2025	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2027	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	
R2029-32	ERJ6GEYJ223	M 22KOHM, J, 1/10W	4	
R2035,36	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2037,38	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	
R2039,40	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2041,42	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	
R2047	ERJ3GEYJ331	M 330 OHM, J, 1/16W	1	
R2048	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2049	ERJ3GEYJ331	M 330 OHM, J, 1/16W	1	
R2050	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2051,52	ERJ6GEYJ184	M 180KOHM, J, 1/10W	2	
R2053,54	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2056,57	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R2058	ERJ3GEYJ301	M 300 OHM, J, 1/16W	1	
R2059	D0GB105JA057	M 1MOHM, J, 1/16W	1	
R2066,67	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	TH-37PX70B/E
R2070,71	J0JCC0000100	CHIP INDUCTOR	2	TH-37PX70B/E
R2072	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	TH-37PX70B/E
R2073	ERJ3GEYJ330	M 33 OHM, J, 1/16W	1	TH-37PX70B/E
R2074,75	ERJ3GEYJ223	M 22KOHM, J, 1/16W	2	TH-37PX70B/E
R2084	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R2085	ERJ3GEYJ561	M 560 OHM, J, 1/16W	1	
R2086	ERJ3GEYJ471	M 470 OHM, J, 1/16W	1	
R2088	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R2089	ERJ3GEYJ561	M 560 OHM, J, 1/16W	1	
R2092	ERJ3GEYJ471	M 470 OHM, J, 1/16W	1	
R2093	ERJ3GEYJ332	M 3.3KOHM, J, 1/16W	1	
R2094	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2096	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2097	ERJ3GEYJ332	M 3.3KOHM, J, 1/16W	1	
R2100	ERJ3EKF2002	M 20KOHM, 1/16W	1	
R2101,02	ERJ3GEYJ331	M 330 OHM, J, 1/16W	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R2104	ERJ3EKF2001	M 2KOHM, 1/16W	1	
R2110	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2111	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R2112	D0GB105JA057	M 1MOHM, J, 1/16W	1	
R2113	ERJ3EKF1203	M 120KOHM, 1/16W	1	
R2114	ERJ3EKF7502	M 75KOHM, 1/16W	1	
R2118	D0GB105JA057	M 1MOHM, J, 1/16W	1	
R2119	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2122	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2123	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2124	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2125	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2127	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2128	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2129	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2131	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2132	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2133,34	ERJ3GEYJ221	M 220 OHM, J, 1/16W	2	TH-37PX70B/E
R2137,38	ERJ3GEYJ221	M 220 OHM, J, 1/16W	2	
R2144	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2145,46	ERJ3EKF2002	M 20KOHM, 1/16W	2	
R2149	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2150,51	ERJ3EKF2002	M 20KOHM, 1/16W	2	
R2152	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R2154	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R2156,57	ERJ3GEYJ331	M 330 OHM, J, 1/16W	2	
R2159	ERJ3GEYJ331	M 330 OHM, J, 1/16W	1	
R2164	ERJ3GEYJ221	M 220 OHM, J, 1/16W	1	
R2165	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2166	ERJ3EKF1602	M 16.0KOHM, 1/16W	1	
R2167	ERJ3GEYJ221	M 220 OHM, J, 1/16W	1	
R2168	ERJ3EKF1602	M 16.0KOHM, 1/16W	1	
R2169	ERJ3EKF2202	M 22KOHM, 1/16W	1	
R2170-73	ERJ3GEYJ221	M 220 OHM, J, 1/16W	4	
R2178	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R2179	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2180	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R2181	ERJ3EKF2202	M 22KOHM, 1/16W	1	
R2182,83	ERJ3EKF3602	M 36KOHM, 1/16W	2	
R2194	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R2195,96	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2197	ERJ3EKF6802	M 68KOHM, 1/16W	1	
R2198	ERJ3EKF1583	M 158KOHM, 1/16W	1	PAVCCZ
R2205	ERJ3GEYJ203	M 20KOHM, J, 1/16W	1	
R2206	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2208-10	D0GB103JA057	M 10KOHM, J, 1/16W	3	
R2216	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2217	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2219	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2220	D0GB123JA057	M 12KOHM, J, 1/16W	1	
R2223-25	J0JCC0000100	CHIP INDUCTOR	3	
R2227-31	J0JCC0000100	CHIP INDUCTOR	5	
R2233	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2234	ERJ3GEYJ330	M 33 OHM, J, 1/16W	1	TH-37PX70B/E
R2235	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2238	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2244	D0GB102JA057	M 1KOHM, J, 1/16W	1	TH-37PX70B/E
R2252-54	ERJ3GEYJ330	M 33 OHM, J, 1/16W	3	TH-37PX70B/E
R2257	J0JCC0000100	CHIP INDUCTOR	1	
R2263	J0JCC0000100	CHIP INDUCTOR	1	
R2265	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R2266	ERJ3GEYJ561	M 560 OHM, J, 1/16W	1	
R2271	EXB28V220J	RESISTOR ARRAY	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R2276	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2290,91	J0JCC0000100	CHIP INDUCTOR	2	
R2294-97	J0JCC0000100	CHIP INDUCTOR	4	
R2301,02	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	2	
R2303,04	J0JCC0000100	CHIP INDUCTOR	2	
R2305	ERJ3GEYJ471	M 470 OHM,J,1/16W	1	
R2306	ERJ3GEYJ683	M 68KOHM,J,1/16W	1	
R2308	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2311	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2313	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2315	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2317	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2319	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2321	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2323	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2325	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2330	D0GB102JA057	M 1KOHM,J,1/16W	1	
R2331	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2506,07	J0JHC0000096	CHIP INDUCTOR	2	
R2516	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	
R2517	ERJ6GEYJ470V	M 47 OHM,J,1/10W	1	
R2520	ERJ3GEYJ224	M 220KOHM,J,1/16W	1	
R2524	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	
R2525	ERJ3EKF5760	M 576 OHM, 1/16W	1	
R2530	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	
R2531	ERJ3GEYJ271	M 270 OHM,J,1/16W	1	
R2539	D0GB473JA057	M 47KOHM,J,1/16W	1	TH-37PX70B/E
R2540	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	TH-37PX70B/E
R2542	D0GB473JA057	M 47KOHM,J,1/16W	1	
R2554	ERJ6RED750	M 75 OHM, 1/10W	1	TH-37PX70B/E
R2556,57	ERJ3GEYJ562	M 5.6KOHM,J,1/16W	2	
R2558	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R2567	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	TH-37PX70B/E
R2572	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	TH-37PX70B/E
R2576,77	J0JCC0000241	CHIP INDUCTOR	2	
R2578	J0JCC0000100	CHIP INDUCTOR	1	
R2579	J0JCC0000100	CHIP INDUCTOR	1	TH-37PV70F/P
R2579	J0JCC0000241	CHIP INDUCTOR	1	TH-37PX70B/E
R2601-03	J0JCC0000100	CHIP INDUCTOR	3	
R2624,25	ERJ3GEYJ220	M 22 OHM,J,1/16W	2	
R2628,29	ERJ3GEYJ752	M 7.5KOHM,J,1/16W	2	
R2853	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2854	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2855	D0GB473JA057	M 47KOHM,J,1/16W	1	
R2856	J0JCC0000100	CHIP INDUCTOR	1	
R2857	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2858	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2859	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2860	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2861	D0GB102JA057	M 1KOHM,J,1/16W	1	
R2863,64	D0GB102JA057	M 1KOHM,J,1/16W	2	
R2865	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2866	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2867	ERJ6ENF8202	M 82KOHM, 1/10W	1	
R2868	ERJ6ENF1602	M 16KOHM, 1/10W	1	
R2869	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2890	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3001-06	ERJ6ENF1500	M 150 OHM, 1/10W	6	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R3008-11	ERJ6ENF1500	M 150 OHM, 1/10W	4	
R3013-15	ERJ6RED750	M 75 OHM, 1/10W	3	
R3018	ERJ6GEYJ680	M 68 OHM,J,1/10W	1	
R3020,21	D1BD2152A028	M 21.5KOHM, 1/10W	2	PAVCCZ
R3023	ERJ6ENF1302	M 13KOHM, 1/10W	1	
R3027,28	ERJ6ENF1500	M 150 OHM, 1/10W	2	
R3031,32	J0JCC0000100	CHIP INDUCTOR	2	
R3033	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3036	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3044,45	J0JCC0000100	CHIP INDUCTOR	2	
R3059-61	ERJ3GEYJ221	M 220 OHM,J,1/16W	3	
R3064	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3087	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R30888	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	TH-37PX70B/E
R3089	ERJ3GEYJ331	M 330 OHM,J,1/16W	1	
R3090	ERJ3GEYJ220	M 22 OHM,J,1/16W	1	
R3092	ERJ3GEYJ680	M 68 OHM,J,1/16W	1	
R3094,95	ERJ3GEYJ680	M 68 OHM,J,1/16W	2	
R3096-01	ERJ3GEYJ221	M 220 OHM,J,1/16W	6	
R3102	D0GB103JA057	M 10KOHM,J,1/16W	1	
R3103	J0JCC0000100	CHIP INDUCTOR	1	
R3104	D0GB103JA057	M 10KOHM,J,1/16W	1	
R3109-13	J0JCC0000100	CHIP INDUCTOR	5	
R3114	ERJ6GEYJ680	M 68 OHM,J,1/10W	1	
R3121	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R3123	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R3130,31	ERJ3GEYJ221	M 220 OHM,J,1/16W	2	
R3133	J0JCC0000100	CHIP INDUCTOR	1	
R3137	ERJ3EKF1000	M 100 OHM, 1/16W	1	
R3140	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R3143	ERJ6ENF63R4	M63.4 OHM, 1/10W	1	PAVCCZ
R3144	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3145	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3146	ERJ3RBD361	M 360 OHM,J,1/16W	1	
R3149	ERJ3RBD361	M 360 OHM,J,1/16W	1	
R3150	ERJ6ENF63R4	M63.4 OHM, 1/10W	1	PAVCCZ
R3151	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3152	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3153,54	ERJ3RBD361	M 360 OHM,J,1/16W	2	
R3163	ERJ6ENF1302	M 13KOHM, 1/10W	1	
R3173	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3174-76	ERJ3GEYJ680	M 68 OHM,J,1/16W	3	
R3177	D0GB103JA057	M 10KOHM,J,1/16W	1	
R3178	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3179,80	ERJ3GEYJ101	M 100 OHM,J,1/16W	2	
R3187	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3191	ERJ3GEYJ220	M 22 OHM,J,1/16W	1	
R3192-94	ERJ6ENF1500	M 150 OHM, 1/10W	3	
R3202	J0JCC0000100	CHIP INDUCTOR	1	
R3205	J0JCC0000100	CHIP INDUCTOR	1	
R3206	ERJ3GEYJ101	M 100 OHM,J,1/16W	1	
R3213,14	J0JCC0000100	CHIP INDUCTOR	2	
R3222	J0JCC0000100	CHIP INDUCTOR	1	
R3227-29	J0JCC0000100	CHIP INDUCTOR	3	
R3236-38	J0JCC0000100	CHIP INDUCTOR	3	
R3239	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3240	ERJ3EKF5600	M 560 OHM, 1/16W	1	
R3243	ERJ6GEYJ271	M 270 OHM,J,1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R3244	J0JCC0000100	CHIP INDUCTOR	1	
R3246	J0JCC0000100	CHIP INDUCTOR	1	
R3247	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3271	J0JCC0000100	CHIP INDUCTOR	1	
R3273,74	J0JCC0000100	CHIP INDUCTOR	2	
R3275	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3302	ERJ6GEYJ101V	M 100 OHM,J,1/10W	1	
R3305	ERJ6GEYJ101V	M 100 OHM,J,1/10W	1	
R3306,07	ERJ6GEYF472	M 4.7KOHM,J,1/10W	2	
R3308,09	ERJ6GEY0R00V	M 0 OHM, 1/10W	2	
R3310	ERJ6RED750	M 75 OHM, 1/10W	1	
R3312	D0GB473JA057	M 47KOHM,J,1/16W	1	
R3313	ERJ6RED750	M 75 OHM, 1/10W	1	
R3318	ERJ6RED750	M 75 OHM, 1/10W	1	
R3348,49	ERJ3GEYJ680	M 68 OHM,J,1/16W	2	
R3350	ERJ3GEYJ101	M 100 OHM,J,1/16W	1	
R3751	ERJ6ENF1432	M14.3KOHM, 1/10W	1	
R3753	ERJ6ENF1741	M1.74KOHM, 1/10W	1	
R3754	ERJ6ENF1621	M1.62KOHM, 1/10W	1	
R3755	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R3758	ERJ6ENF6651	M6.65KOHM, 1/10W	1	
R3765	ERJ6ENF2321	M2.32KOHM, 1/10W	1	
R3767	ERJ6ENF3161	M3.16KOHM, 1/10W	1	
R3768	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R4001	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4026	J0JCC0000100	CHIP INDUCTOR	1	
R4200-02	ERJ2RKD330	M 33 OHM, J,0.063W	3	
R4242	J0JCC0000100	CHIP INDUCTOR	1	
R4284	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4286-88	ERJ2GEJ473	M 47KOHM,J,0.063W	3	
R4317-20	ERJ2GEJ473	M 47KOHM,J,0.063W	4	
R4322-30	ERJ2GEJ473	M 47KOHM,J,0.063W	9	
R4500,01	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R4502,03	ERJ2RKD330	M 33 OHM, J,0.063W	2	
R4506,07	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R4508-23	ERJ2GEJ2R2X	M 2.2OHM, J,0.063W	16	
R4524,25	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R4526,27	ERJ2GEJ102X	M 1KOHM, J,0.063W	2	
R4528	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4529	ERJ2GEJ472	M 4.7KOHM, J,0.063W	1	
R4530	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4531	ERJ2GEJ472	M 4.7KOHM, J,0.063W	1	
R4532,33	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R4535,36	ERJ2GEJ472	M 4.7KOHM, J,0.063W	2	
R4538	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R4539	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R4540	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R4541-43	ERJ2GEJ680	M 68 OHM, J,0.063W	3	
R4544-47	ERJ2GEJ103	M 10KOHM, J,0.063W	4	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R4552	ERJ2GEJ220	M 22 OHM, J,0.063W	1	
R4561	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R4562,63	ERJ2GEJ472	M 4.7KOHM, J,0.063W	2	
R4564,65	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R4578,79	ERJ2GEJ151	M 150 OHM, J,0.063W	2	
R4585	ERJ2GEJ101	M 100 OHM, J,0.063W	1	
R4587	ERJ3GEYF821	M 820 OHM, 1/16W	1	
R4593	ERJ3EKF1101	M 1.1KOHM, 1/16W	1	
R4596-98	ERJ6GEYG102	M 1KOHM,J,1/10W	3	
R4601	ERJ6GEYG102	M 1KOHM,J,1/10W	1	
R4604	ERJ3EKF7501	M 7.5KOHM, 1/16W	1	
R4605	ERJ3EKF1201	M 1.2KOHM, 1/16W	1	
R4606	ERJ3EKF4701	M 4.7KOHM, 1/16W	1	
R4608	ERJ6GEYG102	M 1KOHM,J,1/10W	1	
R4609	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4610	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R4611	ERJ3EKF1371	M1.37KOHM, 1/16W	1	
R4612	ERJ3EKF1501	M 1.5KOHM, 1/16W	1	
R4613,14	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R4615	ERJ3EKF1600	M 160 OHM, 1/16W	1	
R4616-19	D0YAR0000007	M 0.0 OHM, J,0.063W	4	
R4622	ERJ2GEJ101	M 100 OHM, J,0.063W	1	
R4624	ERJ3EKF1691	M1.69KOHM, 1/16W	1	
R4626	ERJ2GEJ105	M 1MOHM, J,0.063W	1	
R4627	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R4628,29	ERJ2GEJ101	M 100 OHM, J,0.063W	2	
R4631	ERJ3EKF4990	M 499 OHM, 1/16W	1	
R4635	EXB28V680JX	RESISTOR ARRAY	1	
R4636-38	ERJ2GEJ680	M 68 OHM, J,0.063W	3	
R4639,40	EXB28V680JX	RESISTOR ARRAY	2	
R4641	ERJ2GEJ220	M 22 OHM, J,0.063W	1	
R4642	EXB28V680JX	RESISTOR ARRAY	1	
R4643,44	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R4645-47	ERJ2GEJ680	M 68 OHM, J,0.063W	3	
R4648	EXB28V330J	RESISTOR ARRAY	1	
R4649	EXB28V680JX	RESISTOR ARRAY	1	
R4650,51	ERJ2GEJ680	M 68 OHM, J,0.063W	2	
R4652	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R4653	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4654	ERJ3EKF4701	M 4.7KOHM, 1/16W	1	
R4655	ERJ2GEJ101	M 100 OHM, J,0.063W	1	
R4656	ERJ2GEJ222	M 2.2KOHM, J,0.063W	1	
R4657,58	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R4661	ERJ2GEJ101	M 100 OHM, J,0.063W	1	
R4664	ERJ3EKF6980	M 698 OHM, 1/16W	1	
R4665,66	ERJ2GEJ473	M 47KOHM,J,0.063W	2	
R4667	ERJ2GEJ151	M 150 OHM, J,0.063W	1	
R4670	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R4682	ERJ3EKF1002	M 10KOHM, 1/16W	1	
R4683	ERJ2GEJ103	M 10KOHM, J,0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R4691,92	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R4698,99	D0YAR0000007	M 0.0 OHM, J,0.063W	2	
R4702,03	D0YAR0000007	M 0.0 OHM, J,0.063W	2	
R4706	ERJ2GEJ102X	M 1KOHM, J,0.063W	1	
R4707	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R4708	ERJ2GEJ102X	M 1KOHM, J,0.063W	1	
R4801	J0JCC0000100	CHIP INDUCTOR	1	
R4819,20	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R4838	ERJ2GEJ101	M 100 OHM, J,0.063W	1	
R4856-65	D0YAR0000007	M 0.0 OHM, J,0.063W	10	
R4872	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R5481	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R5506,07	ERJ6GEYG103	M 10KOHM, J,1/10W	2	
R5508	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R5509	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R5531	ERJ6GEYG222	M 2.2KOHM, J,1/10W	1	
R5532	ERJ6GEYF472	M 4.7KOHM, J,1/10W	1	
R5533	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R5534	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R5535	ERJ6GEYG222	M 2.2KOHM, J,1/10W	1	
R5536	ERJ6GEYF472	M 4.7KOHM, J,1/10W	1	
R5537	ERJ6GEYG681	M 680 OHM, J,1/10W	1	
R5538	ERJ6GEYG222	M 2.2KOHM, J,1/10W	1	
R5540	ERJ6GEYJ471	M 470 OHM, J,1/10W	1	
R5542	ERJ6GEYJ471	M 470 OHM, J,1/10W	1	
R5544	ERJ6GEYG221	M 220 OHM, J,1/10W	1	
R5546,47	ERJ6GEYG103	M 10KOHM, J,1/10W	2	
R5548,49	ERJ6GEYF472	M 4.7KOHM, J,1/10W	2	
R5554	ERJ6ENF2611	M2.61KOHM, 1/10W	1	
R5555	ERJ6ENF1271	M1.27KOHM, 1/10W	1	
R5570	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R5571	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R5572	ERJ6GEYG222	M 2.2KOHM, J,1/10W	1	
R5573	ERJ6GEYF472	M 4.7KOHM, J,1/10W	1	
R5600	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R5604	ERJ3GEYF473	M 47KOHM, 1/16W	1	
R5605	ERJ3EKF1272	M12.7KOHM, 1/16W	1	
R5606-09	D0YAR0000007	M 0.0 OHM, J,0.063W	4	
R5610	ERJ2GEJ104	M 100KOHM, J,0.063W	1	
R5611	ERJ3EKF3602	M 36KOHM, 1/16W	1	
R5612	ERJ3EKF2322	M23.2KOHM, 1/16W	1	
R5620	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R5621	ERJ3GEYF473	M 47KOHM, 1/16W	1	
R5622	ERJ2GEJ104	M 100KOHM, J,0.063W	1	
R5623	ERJ3GEYF473	M 47KOHM, 1/16W	1	
R5625-28	D0YAR0000007	M 0.0 OHM, J,0.063W	4	
R5629	ERJ3EKF3012	M30.1KOHM, 1/16W	1	
R5630	ERJ3EKF4752	M47.5KOHM, 1/16W	1	
R5631	ERJ3EKF3602	M 36KOHM, 1/16W	1	
R5632	ERJ3EKF3002	M 30KOHM, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R5633,34	ERJ3EKF1602	M16.0KOHM, 1/16W	2	
R5635	ERJ2GEJ223	M 22KOHM, J,0.063W	1	
R5636	ERJ2GEJ683	M 68KOHM, J,0.063W	1	
R5637	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R5638	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R5641	ERJ2GEJ473	M 47KOHM, J,0.063W	1	
R5644	ERJ2GEJ222	M 2.2KOHM, J,0.063W	1	
R5646	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R5647	ERJ2GEJ473	M 47KOHM, J,0.063W	1	
R5660	ERJ2GEJ562	M 5.6KOHM, J,0.063W	1	
R5661	ERJ2GEJ473	M 47KOHM, J,0.063W	1	
R5662	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R5670	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R5671	ERJ2GEJ183	M 18KOHM, J,0.063W	1	
R5672	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R5674	ERJ2GEJ473	M 47KOHM, J,0.063W	1	
R5690,91	D0GB103JA057	M 10KOHM, J,1/16W	2	
R5692,93	D0GB473JA057	M 47KOHM, J,1/16W	2	
R5694,95	D0GB102JA057	M 1KOHM, J,1/16W	2	
R5696,97	D0GB103JA057	M 10KOHM, J,1/16W	2	
R5730,31	ERJ2GEJ473	M 47KOHM, J,0.063W	2	
R6001	D0GF7R5JA047	M 7.5 OHM, J,0.33W	1	
R6003	D0GF7R5JA047	M 7.5 OHM, J,0.33W	1	
R6005	D0GF7R5JA047	M 7.5 OHM, J,0.33W	1	
R6020	ERF5TJ330	W 33 OHM, 5W	1	
R6021	D0GF7R5JA047	M 7.5 OHM, J,0.33W	1	
R6024	D0GF7R5JA047	M 7.5 OHM, J,0.33W	1	
R6026	D0GF7R5JA047	M 7.5 OHM, J,0.33W	1	
R6031,32	ERJ6ENF8202	M 82KOHM, 1/10W	2	
R6033	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6034	ERJ6ENF2702	M 27KOHM, 1/10W	1	
R6041	D0GF5R6JA047	M 5.6 OHM, J,0.33W	1	
R6043	D0GF5R6JA047	M 5.6 OHM, J,0.33W	1	
R6053	D0GF5R6JA047	M 5.6 OHM, J,0.33W	1	
R6080	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6082	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6084	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6086	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6088-91	ERJ6GEY0R00V	M 0 OHM, 1/10W	4	
R6102	D0GD221JA059	M 220 OHM, J,1/10W	1	
R6108	D0GD221JA059	M 220 OHM, J,1/10W	1	
R6109	D0GD100JA059	M 10 OHM, J,0.25W	1	
R6110	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R6111	D0GD470JA059	M 47 OHM, J,0.25W	1	
R6113	ERJ14YJ224	M 220KOHM, J,1/4W	1	
R6114	D0GD470JA059	M 47 OHM, J,0.25W	1	
R6116	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R6131,32	ERJ6GEYJ101V	M 100 OHM, J,1/10W	2	
R6134	D0GD750JA059	M 75 OHM, J,0.25W	1	
R6135,36	D0GD100JA059	M 10 OHM, J,0.25W	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6141, 42	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6145	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	1	
R6146, 47	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6151, 52	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6154	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6157-60	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	4	
R6171	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6172, 73	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6181	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6182, 83	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6191, 92	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6193	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6194	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	1	
R6210	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R6213	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6214	D0GD151JA059	M 150 OHM, J, 0.25W	1	
R6220	ERJ6GEYG470V	M 47 OHM, J, 1/10W	1	
R6221	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6222	ERG1FJS103D	M 10KOHM, J, 1W	1	
R6223	ERG2FJS123D	M 12KOHM, J, 2W	1	
R6225	D0GD203JA059	M 20KOHM, J, 1/10W	1	
R6226, 27	ERJ6GEYJ163V	M 16KOHM, J, 1/10W	2	
R6228	ERJ6GEYG562	M 5.6KOHM, J, 1/10W	1	
R6229	ERJ6GEYJ163V	M 16KOHM, J, 1/10W	1	
R6230	ERJ6GEYG470V	M 47 OHM, J, 1/10W	1	
R6231	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6232	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R6241	EXB38V470J	RESISTOR ARRAY	1	
R6242	EXB38V472JV	RESISTOR ARRAY	1	
R6246	ERJ6GEYJ273	M 27KOHM, J, 1/10W	1	
R6247	D0GF154JA047	M 150 KOHM, J, 0.33W	1	
R6248	ERJ6GEYJ273	M 27KOHM, J, 1/10W	1	
R6249	D0GF154JA047	M 150 KOHM, J, 0.33W	1	
R6252, 53	ERJ6ENF3902	M 39KOHM, 1/10W	2	
R6254	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R6255	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R6256	ERJ6ENF1501	M 1.5KOHM, 1/10W	1	
R6257	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6258	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R6261	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R6269	ERJ6GEYJ273	M 27KOHM, J, 1/10W	1	
R6270	D0GF154JA047	M 150 KOHM, J, 0.33W	1	
R6272	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R6273	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6274	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6276	ERJ6GEYG823	M 82KOHM, J, 1/10W	1	
R6278	ERJ6GEYJ273	M 27KOHM, J, 1/10W	1	
R6279	D0GF154JA047	M 150 KOHM, J, 0.33W	1	
R6284	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R6292	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6401-03	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	3	
R6421-23	D0GF5R6JA047	M 5.6 OHM, J, 0.33W	3	
R6441, 42	D0GF5R6JA047	M 5.6 OHM, J, 0.33W	2	
R6451	D0GF5R6JA047	M 5.6 OHM, J, 0.33W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6465	ERJ6ENF2702	M 27KOHM, 1/10W	1	
R6466	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6467, 68	ERJ6ENF8202	M 82KOHM, 1/10W	2	
R6471	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6472	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R6473	ERJ6GEYF561	M 560 OHM, J, 1/10W	1	
R6474	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R6475, 76	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	2	
R6477	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6501, 02	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6503	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6504	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6506	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6507-10	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	4	
R6511, 12	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6516, 17	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6521, 22	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6523	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6531	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6532, 33	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6551	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6552, 53	ERJ6GEYF473	M 47KOHM, J, 1/10W	2	
R6561-64	EXB38V470J	RESISTOR ARRAY	4	
R6565-68	EXB38V472JV	RESISTOR ARRAY	4	
R6580	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R6582, 83	ERJ6ENF3902	M 39KOHM, 1/10W	2	
R6584	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R6585	ERJ6ENF1801	M 1.8KOHM, 1/10W	1	
R6586	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R6587	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R6588	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6590	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6591	EXB38V472JV	RESISTOR ARRAY	1	
R6592	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6605	ERJ6GEYG182	M 1.8KOHM, J, 1/10W	1	
R6607	D1BD6811A027	M 6.81KOHM, 1/10W	1	
R6608, 09	D0GF102JA047	M 1.0 KOHM, J, 0.33W	2	
R6610	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R6612	D0GD470JA059	M 47 OHM, J, 0.25W	1	
R6621, 22	ERJ6GEYG221	M 220 OHM, J, 1/10W	2	
R6623	ERG2FJS333D	M 33KOHM, J, 2W	1	
R6638, 39	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	2	
R6642-44	D0GD330JA059	M 33 OHM, J, 1/10W	3	
R6646-48	D0GD330JA059	M 33 OHM, J, 1/10W	3	
R6658	D0D1101JA009	M 100 OHM, J, 1W	1	
R6659, 60	ERJ6GEYJ224	M 220KOHM, J, 1/10W	2	
R6661	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R6662	ERJ6ENF2201	M 2.2KOHM, 1/10W	1	
R6663	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6664	D0GF222JA047	M 2.2 KOHM, J, 0.33W	1	
R6665	D0GD470JA059	M 47 OHM, J, 0.25W	1	
R6666	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R6667, 68	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	2	
R6671	D0GD470JA059	M 47 OHM, J, 0.25W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6672	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6673, 74	D0GD470JA059	M 47 OHM, J, 0.25W	2	
R6680, 81	D0GD100JA059	M 10 OHM, J, 0.25W	2	
R6692	D0GZ472JA020	M 4.7KOHM, J, 0.5W	1	
R6693	ERJ6GEYG823	M 82KOHM, J, 1/10W	1	
R6694	ERJ6GEYJ273	M 27KOHM, J, 1/10W	1	
R6695	ERJ8GEYJ124	M 120KOHM, J, 1/8W	1	
R6696	ERF5TK2R2	W 2.2 OHM, K, 5W	1	
R6700-04	ERJ6GEYJ471	M 470 OHM, J, 1/10W	5	
R6705, 06	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6707, 08	ERJ6GEYJ471	M 470 OHM, J, 1/10W	2	
R6709	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6710-14	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	5	
R6717, 18	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	2	
R6721, 22	EXB38V220JV	RESISTOR ARRAY	2	
R6723	ERJ6GEYG182	M 1.8KOHM, J, 1/10W	1	
R6724	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6742	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6745	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6746, 47	D0GD103JA059	M 10KOHM, J, 0.25W	2	
R6748	ERJ6GEYG332	M 3.3KOHM, J, 1/10W	1	
R6761	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6762	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6765	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	1	
R6766	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6768	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	1	
R6769	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6775, 76	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6777	D0GD151JA059	M 150 OHM, J, 0.25W	1	
R6781	D0GD470JA059	M 47 OHM, J, 0.25W	1	
R6782	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6788	ERJ6GEYJ474	M 470KOHM, J, 1/10W	1	
R6789	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6791	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R6792	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6793	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6795, 96	ERJ6GEYG104	M 100KOHM, J, 1/10W	2	
R6797	ERJ6ENF1692	M16.9KOHM, 1/10W	1	
R6801	ERG2FNJS8R2E	M 8.2 OHM, J, 2W	1	
R6802	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6806, 07	ERX12SJ1R5	M 1.5 OHM, J, 1/2W	2	
R6808	D0GF272JA047	M 2.7 KOHM, J, 0.33W	1	
R6809	ERG1SJ273	M 27KOHM, J, 1W	1	
R6810	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R6811	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6812	ERJ6ENF2403	M 240KOHM, 1/10W	1	
R6813	ERJ6ENF1002	M 10KOHM, 1/10W	1	
R6814	ERJ6ENF5601	M 5.6KOHM, 1/10W	1	
R6815	ERJ6ENF2700	M 270 OHM, 1/10W	1	
R6816	D1BD1152A028	M11.5KOHM, 1/10W	1	
R6817	ERJ6ENF2491	M2.49KOHM, 1/10W	1	
R6818	ERJ6GEYJ474	M 470KOHM, J, 1/10W	1	
R6821	ERF5TJ221	W 220 OHM, J, 5W	1	
R6822	ERJ12YJ104U	M 100KOHM, 1/2W	1	
R6823	ERG1FJS104D	M 100KOHM, J, 1W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6824	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6825-27	ERJ6ENF2003	M 200KOHM, 1/10W	3	
R6828	ERJ6ENF4701	M 4.7KOHM, 1/10W	1	
R6829, 30	ERJ6GEYG104	M 100KOHM, J, 1/10W	2	
R6831	ERJ6GEYG153	M 15KOHM, J, 1/10W	1	
R6832	D0GF4R7JA047	M 4.7 OHM, J, 0.33W	1	
R6833-36	ERJ6ENF7502	M 75KOHM, 1/10W	4	
R6837	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6839	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6840	ERX12SJ1R5	M 1.5 OHM, J, 1/2W	1	
R6841	ERJ12YJ153U	M 15KOHM, 1/2W	1	
R6842	ERJ12YJ433U	M 43KOHM, 1/2W	1	
R6843	ERJ6GEYJ623	M 62KOHM, J, 1/10W	1	
R6844	D0D2101JA021	M 100 OHM, J, 2W	1	
R6845-47	ERJ6GEYJ623	M 62KOHM, J, 1/10W	3	
R6848	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6849, 50	ERJ6ENF6802	M 68KOHM, 1/10W	2	
R6851	ERJ6ENF1802	M 18KOHM, 1/10W	1	
R6852	ERJ6ENF2701	M 2.7KOHM, 1/10W	1	
R6853	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6855	ERJ12YJ103	M 10KOHM, J, 1/2W	1	
R6856	ERQ12AJW560E	F 56 OHM, J, 1/2W	1	
R6857	ERJ12YJ124U	M 120KOHM, 1/2W	1	
R6860	D0D28R2JA021	M 8.2 OHM, J, 2W	1	
R6861, 62	ERJ6ENF5102	M 51KOHM, 1/10W	2	
R6863	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6864	ERJ6ENF6801	M 6.8KOHM, 1/10W	1	
R6865	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R6866	ERJ6ENF6200	M 620 OHM, 1/10W	1	
R6867	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6868	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R6869	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6871-73	ERJ6ENF3902	M 39KOHM, 1/10W	3	
R6874	ERJ6ENF6801	M 6.8KOHM, 1/10W	1	
R6875	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R6876	ERJ6RBD561	M 560 OHM, 1/10W	1	
R6877	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6878	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R6879	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6886-88	ERJ6GEYJ224	M 220KOHM, J, 1/10W	3	
R6891	ERJ6GEYG183	M 18KOHM, J, 1/10W	1	
R6901	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6902-04	ERJ3GEYJ220	M 22 OHM, J, 1/16W	3	
R6908, 09	ERJ6GEYG221	M 220 OHM, J, 1/10W	2	
R6916, 17	ERJ6GEYG221	M 220 OHM, J, 1/10W	2	
R6924	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6925, 26	J0JCC0000100	CHIP INDUCTOR	2	
R6931-34	ERJ6GEYG103	M 10KOHM, J, 1/10W	4	
R6935, 36	ERJ8GEYJ224	M 220KOHM, J, 1/8W	2	
R6938	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6951	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6952-54	ERJ3GEYJ220	M 22 OHM, J, 1/16W	3	
R6958, 59	ERJ6GEYG221	M 220 OHM, J, 1/10W	2	
R6966, 67	ERJ6GEYG221	M 220 OHM, J, 1/10W	2	
R6974	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6975, 76	J0JCC0000100	CHIP INDUCTOR	2	
R6981-84	ERJ6GEYG103	M 10KOHM, J, 1/10W	4	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6985,86	ERJ8GEYJ224	M 220KOHM, J, 1/8W	2	
R6989	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R7112	D0GF472JA047	M 4.7KOHM, J, 0.33W	1	
R7119	EXB38V220JV	RESISTOR ARRAY	1	
R7122-25	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7126	ERJ6GEYJ224	M 220KOHM, J, 1/10W	1	
R7130-36	EXB38V471J	RESISTOR ARRAY	7	
R7142-45	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7151-54	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7155	EXB38V102J	RESISTOR ARRAY	1	
R7159	EXB38V470J	RESISTOR ARRAY	1	
R7162	EXB38V471J	RESISTOR ARRAY	1	
R7171-74	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7177	EXB38V102J	RESISTOR ARRAY	1	
R7180	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R7184	EXB38V220JV	RESISTOR ARRAY	1	
R7185	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R7186	J0JCC0000100	CHIP INDUCTOR	1	
R7212-15	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7219	ERJ6GEYJ224	M 220KOHM, J, 1/10W	1	
R7223-26	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7229	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R7232-35	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7238	EXB38V471J	RESISTOR ARRAY	1	
R7245	EXB38V102J	RESISTOR ARRAY	1	
R7249	EXB38V220JV	RESISTOR ARRAY	1	
R7250	EXB38V470J	RESISTOR ARRAY	1	
R7257	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R7258	EXB38V102J	RESISTOR ARRAY	1	
R7262-65	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7269	D0GF472JA047	M 4.7KOHM, J, 0.33W	1	
R7273-79	EXB38V471J	RESISTOR ARRAY	7	
R7280	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R7281	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R7285	EXB38V220JV	RESISTOR ARRAY	1	
R7286	J0JCC0000100	CHIP INDUCTOR	1	
R7288,89	EXB38V222J	RESISTOR ARRAY	2	
R7290,91	EXB38V470J	RESISTOR ARRAY	2	
R8001	ERJ2GEJ181	M 180 OHM, J, 0.063W	1	
R8002	ERJ2GEJ820	M 82 OHM, J, 0.063W	1	
R8003	J0JCC0000100	CHIP INDUCTOR	1	
R8004	ERJ3EKF2402	M 24KOHM, 1/16W	1	
R8005	ERJ3EKF1002	M 10KOHM, 1/16W	1	
R8006	ERJ3EKF6801	M 6.8KOHM, 1/16W	1	
R8023-29	D0YAR0000007	M 0.0 OHM, J, 0.063W	7	
R8030	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8031,32	ERJ3EKF2700	M 270 OHM, 1/16W	2	
R8035	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8039	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8056-73	ERJ2GEJ470	M 47 OHM, J, 0.063W	18	
R8074	ERJ2GEJ221	M 220 OHM, J, 0.063W	1	
R8075-78	ERJ2GEJ470	M 47 OHM, J, 0.063W	4	
R8079,80	D0YAR0000007	M 0.0 OHM, J, 0.063W	2	
R8081	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8082	D1BA75R0A026	M0.75KOHM, 1/10W	1	
R8083	ERJ2GEJ301	M 300 OHM, J, 0.063W	1	
R8084	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8086	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R8087	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8090	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8091	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8093	ERJ2GEJ470	M 47 OHM, J, 0.063W	1	
R8095	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8097	ERJ2GEJ221	M 220 OHM, J, 0.063W	1	
R8098,99	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R8100	ERJ2GEJ470	M 47 OHM, J, 0.063W	1	
R8101	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8106	ERJ2GEJ202	M 2KOHM, J, 0.063W	1	
R8107	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8111	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8301	EXB2HV680J	RESISTOR ARRAY	1	TH-37PX70B/E
R8303,04	ERJ2GEJ101	M 100 OHM, J, 0.063W	2	TH-37PX70B/E
R8305	ERJ2GEJ223	M 22KOHM, J, 0.063W	1	TH-37PX70B/E
R8306,07	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	2	TH-37PX70B/E
R8308	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-37PX70B/E
R8309-12	ERJ2GEJ101	M 100 OHM, J, 0.063W	4	TH-37PX70B/E
R8314,15	ERJ2GEJ101	M 100 OHM, J, 0.063W	2	TH-37PX70B/E
R8318	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	1	TH-37PX70B/E
R8321	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-37PX70B/E
R8322	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	TH-37PX70B/E
R8323,24	ERJ2GEJ473	M 47KOHM, J, 0.063W	2	TH-37PX70B/E
R8325-27	ERJ2GEJ680	M 68 OHM, J, 0.063W	3	TH-37PX70B/E
R8328	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-37PV70F/P
R8329	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	TH-37PX70B/E
R8401	ERJ8GEY0R00	M 0 OHM, 1/8W	1	TH-37PX70B/E
R8402	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	TH-37PX70B/E
R8404,05	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	TH-37PX70B/E
R8406	ERJ8RSJR10	M 1 OHM, 1/8W	1	TH-37PX70B/E
R8407	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	TH-37PX70B/E
R8410,11	ERJ2GEJ223	M 22KOHM, J, 0.063W	2	TH-37PX70B/E
R8412	EXB2HV473JV	RESISTOR ARRAY	1	TH-37PX70B/E
R8414	EXB2HV101J	RESISTOR ARRAY	1	TH-37PX70B/E
R8416	ERJ2GEJ223	M 22KOHM, J, 0.063W	1	TH-37PX70B/E
R8417	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	TH-37PX70B/E
R8418	ERJ2GEJ681	M 680 OHM, J, 0.063W	1	TH-37PX70B/E
R8419	EXB2HV101J	RESISTOR ARRAY	1	TH-37PX70B/E
R8421-25	ERJ2GEJ680	M 68 OHM, J, 0.063W	5	TH-37PX70B/E
R8426	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	TH-37PX70B/E

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8427,28	EXB2HV680J	RESISTOR ARRAY	2	TH-37PX70B/E
R8430	ERJ2GEJ101	M 100 OHM, J,0.063W	1	TH-37PX70B/E
R8431,32	ERJ2GEJ151	M 150 OHM, J,0.063W	2	TH-37PX70B/E
R8433	ERJ2GEJ223	M 22KOHM, J,0.063W	1	TH-37PX70B/E
R8434	ERJ2GEJ473	M 47KOHM, J,0.063W	1	TH-37PX70B/E
R8435,36	ERJ2GEJ103	M 10KOHM, J,0.063W	2	TH-37PX70B/E
R8437	EXB2HV104JV	RESISTOR ARRAY	1	TH-37PX70B/E
R8438	ERJ2GEJ104	M 100KOHM, J,0.063W	1	TH-37PX70B/E
R8440	ERJ2GEJ104	M 100KOHM, J,0.063W	1	TH-37PX70B/E
R8441	EXB2HV680J	RESISTOR ARRAY	1	TH-37PX70B/E
R8443	EXB2HV680J	RESISTOR ARRAY	1	TH-37PX70B/E
R8445	ERJ2GEJ104	M 100KOHM, J,0.063W	1	TH-37PX70B/E
R8446	ERJ2GEJ680	M 68 OHM, J,0.063W	1	TH-37PX70B/E
R8449	ERJ2GEJ680	M 68 OHM, J,0.063W	1	TH-37PX70B/E
R8450	ERJ2GEJ103	M 10KOHM, J,0.063W	1	TH-37PX70B/E
R8451	EXB28V680JX	RESISTOR ARRAY	1	TH-37PX70B/E
R8452,53	ERJ2GEJ680	M 68 OHM, J,0.063W	2	TH-37PX70B/E
R8454	EXB28V151JX	RESISTOR ARRAY	1	PAVCCZ TH-37PX70B/E
R8456-61	ERJ2GEJ680	M 68 OHM, J,0.063W	6	TH-37PX70B/E
R8463	EXB28V151JX	RESISTOR ARRAY	1	PAVCCZ TH-37PX70B/E
R8465,66	ERJ2GEJ103	M 10KOHM, J,0.063W	2	TH-37PX70B/E
R8468	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PX70B/E
R8469	ERJ2GEJ101	M 100 OHM, J,0.063W	1	TH-37PX70B/E
R8470,71	ERJ2GEJ103	M 10KOHM, J,0.063W	2	TH-37PX70B/E
R8472	D1HG1038A002	NETWORK RESISTER	1	TH-37PV70F/P
R8474,75	EXB28V103JX	RESISTOR ARRAY	2	TH-37PV70F/P
R8477	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PX70B/E
R8484	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-37PX70B/E
R8502-04	ERJ2GEJ331	M 330 OHM, J,0.063W	3	
R8506	ERJ2GEJ331	M 330 OHM, J,0.063W	1	
R8507-10	ERJ3EKF91R0	M 91 OHM, 1/16W	4	
R8512	ERJ3EKF1800	M 180 OHM, 1/16W	1	
R8513	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R8517-19	D0YAR0000007	M 0.0 OHM, J,0.063W	3	
R8551	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8555-61	ERJ2GEJ680	M 68 OHM, J,0.063W	7	
R8564	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8601,02	ERJ2GEJ220	M 22 OHM, J,0.063W	2	
R8603	ERJ2GEJ473	M 47KOHM, J,0.063W	1	
R8604	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R8605	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R8621-36	ERJ2GEJ680	M 68 OHM, J,0.063W	16	
R8653	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8655	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8702	D0YAR0000007	M 0.0 OHM, J,0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8703	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R8709	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R8710	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R8711,12	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R8732	ERJ2GEJ101	M 100 OHM, J,0.063W	1	
R8735-39	ERJ2GEJ680	M 68 OHM, J,0.063W	5	
R8742	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8745,46	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R8749	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8802-09	ERJ2GEJ103	M 10KOHM, J,0.063W	8	
R8812	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R8813	EXB28V680JX	RESISTOR ARRAY	1	
R8814-17	ERJ2GEJ680	M 68 OHM, J,0.063W	4	
R8818	ERJ2GEJ472	M 4.7KOHM, J,0.063W	1	
R8823	ERJ2GEJ472	M 4.7KOHM, J,0.063W	1	
R8825	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R8826	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R8828	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8832	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8833	J0JCC0000100	CHIP INDUCTOR	1	
R8851-54	D0YAR0000007	M 0.0 OHM, J,0.063W	4	
R8855-60	ERJ2GEJ680	M 68 OHM, J,0.063W	6	
R8862-64	ERJ2GEJ680	M 68 OHM, J,0.063W	3	
R8865-67	EXB2HV680J	RESISTOR ARRAY	3	
R8868	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R8869	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8870	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R8871	ERJ2GEJ103	M 10KOHM, J,0.063W	1	
R8874-76	ERJ2GEJ103	M 10KOHM, J,0.063W	3	
R8877-89	ERJ2GEJ680	M 68 OHM, J,0.063W	13	
R8891,92	ERJ2GEJ680	M 68 OHM, J,0.063W	2	
R8893	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
R8894	ERJ2GEJ680	M 68 OHM, J,0.063W	1	
R8895-97	D0YAR0000007	M 0.0 OHM, J,0.063W	3	
R8898,99	ERJ2GEJ103	M 10KOHM, J,0.063W	2	
R8900,01	ERJ2GEJ680	M 68 OHM, J,0.063W	2	
R8904-10	ERJ2GEJ103	M 10KOHM, J,0.063W	7	
R8911-18	ERJ2GEJ680	M 68 OHM, J,0.063W	8	
R8919-22	ERJ2GEJ472	M 4.7KOHM, J,0.063W	4	
R8923,24	ERJ2GEJ222	M 2.2KOHM, J,0.063W	2	
R8925,26	ERJ2GEJ472	M 4.7KOHM, J,0.063W	2	
R8927	D0YAR0000007	M 0.0 OHM, J,0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8929	EXB2HVR000	RESISTOR ARRAY	1	
R8935	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8947	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8948	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8952	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8963	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R9062-67	ERJ3GEYJ101	M 100 OHM, J, 1/16W	6	
R9070	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R9099	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9101,02	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9104,05	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9107	ERJ3GEYJ332	M 3.3KOHM, J, 1/16W	1	
R9108,09	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9110	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9112	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9113	ERJ3GEYJ100	M 10 OHM, J, 1/16W	1	
R9115,16	ERJ3GEYJ101	M 100 OHM, J, 1/16W	2	
R9119	EXB38V470J	RESISTOR ARRAY	1	
R9120	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9121	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9122,23	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9126	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9127	ERJ3GEYJ683	M 68KOHM, J, 1/16W	1	
R9129	ERJ3GEYJ683	M 68KOHM, J, 1/16W	1	
R9131-33	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	3	
R9134	ERJ3GEYJ333	M 33KOHM, J, 1/16W	1	
R9135	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9141-45	ERJ3GEYJ101	M 100 OHM, J, 1/16W	5	
R9149	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9150,51	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9154,55	ERJ3GEYJ562	M 5.6KOHM, J, 1/16W	2	
R9156	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9158,59	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9160,61	J0JCC0000100	CHIP INDUCTOR	2	
R9164,65	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	
R9166	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9167	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9170-72	D0GB393JA041	M 39KOHM, J, 1/16W	3	
R9173,74	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9177	ERJ3GEYJ223	M 22KOHM, J, 1/16W	1	
R9181-84	D0GB102JA057	M 1KOHM, J, 1/16W	4	
R9185,86	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9187,88	ERJ3GEYJ562	M 5.6KOHM, J, 1/16W	2	
R9189,90	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9193	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9194	J0JCC0000100	CHIP INDUCTOR	1	
R9196	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9199	ERJ3GEYJ272	M 2.7KOHM, J, 1/16W	1	
R9200,01	ERJ3GEYJ100	M 10 OHM, J, 1/16W	2	
R9203	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R9205	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9206,07	D0GB102JA057	M 1KOHM, J, 1/16W	2	
R9215	D0GB123JA057	M 12KOHM, J, 1/16W	1	
R9217-22	D0GB103JA057	M 10KOHM, J, 1/16W	6	
R9223	ERJ3GEYJ272	M 2.7KOHM, J, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R9225	ERJ3GEYJ272	M 2.7KOHM, J, 1/16W	1	
R9237	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9240	J0JCC0000100	CHIP INDUCTOR	1	
R9317	ERJ3GEYJ391	M 390 OHM, J, 1/16W	1	
R9347,48	EXB2HV220JV	RESISTOR ARRAY	2	
R9349	EXB2HV470JV	RESISTOR ARRAY	1	
R9350,51	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9352	EXB2HV220JV	RESISTOR ARRAY	1	
R9354-56	EXB2HV220JV	RESISTOR ARRAY	3	
R9361,62	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9363	EXB2HV470JV	RESISTOR ARRAY	1	
R9369	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9370	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9371	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9379	J0JCC0000100	CHIP INDUCTOR	1	
R9380	ERJ3GEYJ560	M 56 OHM, J, 1/16W	1	
R9383	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R9384,85	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	2	
R9391	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9392,93	J0JCC0000100	CHIP INDUCTOR	2	
R9396-99	ERJ3GEYJ220	M 22 OHM, J, 1/16W	4	
R9402	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R9403	EXB2HV470JV	RESISTOR ARRAY	1	
R9500	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9502	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9503	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R9506	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R9507	J0JCC0000100	CHIP INDUCTOR	1	
R9511-13	ERJ3GEYJ470	M 47 OHM, J, 1/16W	3	
R9516	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9518	J0JCC0000100	CHIP INDUCTOR	1	
R9523	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9525	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9526	J0JCC0000100	CHIP INDUCTOR	1	
R9530	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9531-33	ERJ3GEYJ470	M 47 OHM, J, 1/16W	3	
R9534	EXB38V470J	RESISTOR ARRAY	1	
R9535,36	ERJ3GEYJ470	M 47 OHM, J, 1/16W	2	
R9537	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9539	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9541	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9543,44	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9545	ERJ3GEYJ304	M 300KOHM, J, 1/16W	1	
R9548-50	D0GB103JA057	M 10KOHM, J, 1/16W	3	
R9552	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9553,54	J0JCC0000100	CHIP INDUCTOR	2	
R9557,58	J0JCC0000100	CHIP INDUCTOR	2	
R9561	EXB38V222J	RESISTOR ARRAY	1	
R9562	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R9563-66	EXB2HV470JV	RESISTOR ARRAY	4	
R9567	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9569	J0JCC0000100	CHIP INDUCTOR	1	
R9824-27	ERJ3GEYJ101	M 100 OHM, J, 1/16W	4	
R9828	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9839	EXB38V101JV	RESISTOR ARRAY	1	
R9840	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R9845	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9846,47	EXB2HV222JV	RESISTOR ARRAY	2	
R9848,49	EXB2HV470JV	RESISTOR ARRAY	2	
R9850	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R9854	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9859	EXB38V101JV	RESISTOR ARRAY	1	
R9861-63	D0GB103JA057	M 10KOHM, J, 1/16W	3	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R9868	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R9869-71	D0GB103JA057	M 10KOHM,J,1/16W	3	
R9872	J0JCC0000100	CHIP INDUCTOR	1	
R9874	J0JCC0000100	CHIP INDUCTOR	1	
R9878	ERJ3EKF1102	M 11KOHM, 1/16W	1	
R9879	ERJ3EKF1302	M 13KOHM, 1/16W	1	
R9886,87	ERJ3EKF5602	M 56KOHM, 1/16W	2	
R9888	ERJ3EKF1102	M 11KOHM, 1/16W	1	
R9889	ERJ3EKF1742	M17.2KOHM, 1/16W	1	
R9890	ERJ3EKF4752	M47.5KOHM, 1/16W	1	
R9891	ERJ3EKF1272	M12.7KOHM, 1/16W	1	
R9892	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R9893	ERJ3EKF5602	M 56KOHM, 1/16W	1	
R9894	ERJ3EKF1102	M 11KOHM, 1/16W	1	
R9895	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R9896	ERJ3EKF1822	M18.2KOHM, 1/16W	1	
R9897	ERJ3EKF4752	M47.5KOHM, 1/16W	1	
R9901,02	J0JCC0000100	CHIP INDUCTOR	2	
R9903	EXB2HV470JV	RESISTOR ARRAY	1	
R9904	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R9905	ERJ3GEYJ330	M 33 OHM,J,1/16W	1	
R9906	EXB38V470J	RESISTOR ARRAY	1	
R9907	D0GB151JA057	M 150 OHM,J,1/16W	1	
R9908-11	J0JCC0000100	CHIP INDUCTOR	4	
R9912	D0GB103JA057	M 10KOHM,J,1/16W	1	
R9915-18	J0JCC0000100	CHIP INDUCTOR	4	
R9919	D0GB102JA057	M 1KOHM,J,1/16W	1	
R9922	J0JCC0000100	CHIP INDUCTOR	1	
R9928,29	J0JCC0000100	CHIP INDUCTOR	2	
R9936-39	ERJ3EKF1001	M 1KOHM, 1/16W	4	
R9940	ERJ3GEYJ330	M 33 OHM,J,1/16W	1	
R9941,42	ERJ3GEYJ470	M 47 OHM,J,1/16W	2	
R9943-51	EXB38V470J	RESISTOR ARRAY	9	
R9952-55	ERJ3GEYJ470	M 47 OHM,J,1/16W	4	
R9956	D0GB103JA057	M 10KOHM,J,1/16W	1	
R9960	J0JCC0000100	CHIP INDUCTOR	1	
R9961	D0GB103JA057	M 10KOHM,J,1/16W	1	
RM2501	PNA4701M05TV	REMOCON RECEIVER	1	
S1	K1KA03BA0061	3P CONNECTOR	1	
SC2	K1KA02A00626	2P CONNECTOR	1	
SC20	K1KY30AA0369	30P CONNECTOR	1	
SC30	K1KA10AA0191	10P CONNECTOR	1	
SC41,42	K1ML80B00001	80P CONNECTOR	2	
SC45,46	K1KA09AA00239	9P CONNECTOR	2	
SCMM1,M2	TMME260	CLAMPER	2	
SD1-D3	K1MNC0B00002	CONNECTOR	3	
SD46	K1KB09AA0213	9P CONNECTOR	1	
SS11	K1KA02A00626	2P CONNECTOR	1	
SS12	K1KA10AA0194	10P CONNECTOR	1	
SS23	K1KA12AA0194	12P CONNECTOR	1	
SS34	K1KA03AA0193	3P CONNECTOR	1	
SS53-56	K1MN13BA0258	13P CONNECTOR	4	
SU1-U3	K1MNC0B00002	CONNECTOR	3	
SU45	K1KB09AA0213	9P CONNECTOR	1	
SW2500	K0F162B00002	SWITCH	1	△
SW3753-57	EVQPC105K	SWITCH	5	
T6602	ETS25AZ169AD	SWITCHING TRANS	1	
TU3200	ENG77701GF	TUNER	1	PAVCCZ △
TU8301	ENV77M05D8F	TUNER	1	PAVCCZ TH-37PX70B/E △

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
VR6000	EVMEASA00B14	CONTROL 10KOHMB 0.3W	1	
VR6600	EVMEASA00B13	CONTROL 1KOHMB 0.3W	1	
VR6602	EVMEASA00B53	CONTROL 5KOHMB 0.3W	1	
X1100	H0J100500035	CRYSTAL	1	
X2010	H0J245500082	CRYSTAL	1	
X4500	H0J270500113	CRYSTAL	1	
X8001	H0J270500061	CRYSTAL	1	
X8301	H0J204500006	CRYSTAL	1	PAVCCZ TH-37PX70B/E
X9000	H2D100500004	CRYSTAL	1	
X9200	H0J200500038	CRYSTAL	1	
ZA0001	K4AZ01D00004	TERMINAL	1	PAVCCZ
ZA0002	K4CD08000002	AV TERMINAL	1	
ZA0004,05	K4AZ01D00004	TERMINAL	2	PAVCCZ
ZA0006,07	K4CD08000002	AV TERMINAL	2	
ZA3001-08	K4CD08000002	AV TERMINAL	8	
ZA5501-03	K4CZ01000027	COMPATIBLE WITH JALCO K9	3	
ZA6001,02	K4CD01000011	AV TERMINAL	2	
ZA6005	K4CD01000011	AV TERMINAL	1	
ZA6401-03	K4CD01000011	AV TERMINAL	3	
ZA7101-04	K4AD01Z00001	TERMINAL	4	
ZA7201-04	K4AD01Z00001	TERMINAL	4	
ZA9001	K4CD01000011	AV TERMINAL	1	
C404	F0CZZ335A097	E 0.033UF, 200V	1	
C406	F1E2J4730001	C 0.047PF, , 600V	1	
C407	F2B2W220A032	C 22UF, 450V	1	△
C408	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C410	F1J1E105A080	E 1 UF 25V	1	
C413	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C420	F1J1E105A080	E 1 UF 25V	1	
C421	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C423	ECJ1VB1H472K	C 4700PF, K, 50V	1	
C425	F1J1E105A080	E 1 UF 25V	1	
C426	ECJ1VC1H471J	C 470PF, J, 50V	1	
C427	F1H1C105A071	C 1UF, K, 16V	1	
C428	ECJ1XC1H221J	C 220PF, J, 50V	1	
C429	F1E2J4730001	C 0.047PF, , 600V	1	
C431	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C432,33	F1H1C105A071	C 1UF, K, 16V	2	
C435	ECJ1XC1H101J	C 100PF, J, 50V	1	
C436	F1H1C105A071	C 1UF, K, 16V	1	
C437	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C443,44	ECKD3A102KBP	C 1000PF, K, 1KV	2	
C445	F1H1C105A071	C 1UF, K, 16V	1	
C446	F2B2W3910010	C 390UF, 450V	1	△
C450	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C451	ECKD3A101KBP	C 100PF, K, 1KV	1	
C457	ECWH12333RHV	P 0.013UF,J,1.2KV	1	
C462	F1J1E105A080	E 1 UF 25V	1	
C463	F1H1H2200008	E 22UF, 50V	1	
C467	F1BAF221A107	C 220UF, 250V	1	△
C468	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C469	F1BAF221A107	C 220UF, 250V	1	△
C470	F0CAF335A080	C 0.033UF, 250V	1	△
C472	F1BAF221A107	C 220UF, 250V	1	△
C474,75	F1BAF221A107	C 220UF, 250V	2	△
C478	F1BAF221A107	C 220UF, 250V	1	△
C492	ECA1HM100	E 10UF, 50V	1	
C493	ECA1HM470	E 47UF, 50V	1	
C493	F2A1H4700057	E 47UF, 50V	1	
C497	F2A1H4700057	E 47UF, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C501,02	ECJ1VB1H103K	C 0.001UF, K, 50V	2	
C504	F1H1C105A071	C 1UF, K, 16V	1	
C505	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C506	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C507	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C509	ECA1EHG101	E 100UF, 25V	1	
C511	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C515	F2A1A1220015	E 1200UF, 10V	1	
C516	ECJ1VB1C474K	C 0.47UF, K, 16V	1	
C517	F2A1E221A096	E 220UF, 25V	1	
C518,19	F1H1C105A071	C 1UF, K, 16V	2	
C520	FOC2E683A160	E 0.068UF, 250V	1	
C521	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C522	F1E2E1030002	C 0.010PF, , 600V	1	
C523	F1J1E105A080	E 1 UF 25V	1	
C526	ECJ1VB1H223K	C 0.22UF, K, 50V	1	
C528	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C529	ECJ2FB1C475K	C 47UF, K, 16V	1	
C530	ECJ1VB1E333K	C 0.033UF, K, 25V	1	
C531	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C534	F1H1H471A792	E 470UF, 50V	1	
C546,47	ECJ1VB1H102K	C 1000PF, K, 50V	2	
C552	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C554	F1H1C105A071	C 1UF, K, 16V	1	
C555	F2A2C101A120	E 100UF, 160V	1	△
C556	F2A1E3320039	E 3300PF, 25V	1	
C558	F2A1E4710065	E 470UF, 25V	1	
C559	F2A1A1020084	E 1000UF, 10V	1	
C562	F1H1H223A219	E 0.022UF, 50V	1	
C571	ECJ1VC1H330J	C 33PF, J, 50V	1	
C574	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C577	F2A2A330A022	E 33UF, 100V	1	△
C581	ECJ2VB1H223K	C 0.022UF, K, 50V	1	
C583	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C584	ECJ2VB1H223K	C 0.022UF, K, 50V	1	
C585	F1H1H223A219	E 0.022UF, 50V	1	
C587	ECJ1VB1H332K	C 3300PF, K, 50V	1	
C590	ECJ1XB1H104K	C 10PF, J, 50V	1	
C601	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C603	F1J1E105A080	E 1 UF 25V	1	
C604,05	F2A2D101A203	E 100UF, 200V	2	△
C607	F1H1C105A071	C 1UF, K, 16V	1	
C610	F1J1E105A080	E 1 UF 25V	1	
C611	F2B2T1420003	E 142UF, 220V	1	△
C612	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C616	ECKD3A102KBP	C 1000PF, K, 1KV	1	
C619	F1H1C105A071	C 1UF, K, 16V	1	
C620	F1J1E105A080	E 1 UF 25V	1	
C623	ECA1HM100	E 10UF, 50V	1	
C624	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C625	F2A1H1000083	E 10UF, 50V	1	
C626	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C627	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C630,31	ECJ1VB1H103K	C 0.001UF, K, 50V	2	
C632	ECJ2XC1H330J	C 33PF, J, 50V	1	
C639	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C640	ECJ1VC1H330J	C 33PF, J, 50V	1	
C641	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C650,51	ECJ1VB1E104K	C 0.10UF, K, 25V	2	
C653	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C657	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C658	F1J1E105A080	E 1 UF 25V	1	
C660	ECJ2FB1C225K	C 22UF, K, 16V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C661	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C662	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C665	ECJ1XC1H101J	C 100PF, J, 50V	1	
C666	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C667,68	ECJ1VB1H102K	C 1000PF, K, 50V	2	
C670	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C671	ECJ2VB1E104K	C 0.1UF, K, 25V	1	
C672	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C673	F1E2J4730001	C 0.047PF, , 600V	1	
D401	B0FBAT000006	DIODE	1	△
D404	B0EBKT000007	DIODE	1	△
D407,08	B0ACDJ000010	DIODE	2	
D411	B0BB17000009	DIODE	1	
D415	B0JAME000099	DIODE	1	
D416	B0HAMP000067	DIODE	1	
D418	B0BC8R100013	ZENER DIODE	1	
D419,20	B0EAMR000009	DIODE	2	
D423	MA188	DIODE	1	
D425	MA188	DIODE	1	
D429	B0EAKT000048	DIODE	1	
D431	B0JCDD000002	DIODE	1	
D433	B0BC01400033	ZENER DIODE	1	
D435	B0EAKT000048	DIODE	1	
D436	B0AACK000004	DIODE	1	
D436	MA165TA5	DIODE	1	
D438	B0BC02000014	ZENER DIODE	1	
D439	B0EAKT000048	DIODE	1	
D441	B0HAMM000122	DIODE	1	
D444	B0HAMM000122	DIODE	1	
D445	MTZJ10B	ZENER DIODE	1	
D501	B0EAMR000010	DIODE	1	
D503	B0AACK000004	DIODE	1	
D503	MA165TA5	DIODE	1	
D504	B0AACK000004	DIODE	1	
D504	MA165TA5	DIODE	1	
D506	B0ACDJ000010	DIODE	1	
D507,08	B0BC7R400023	ZENER DIODE	2	
D509	B0JANG000018	DIODE	1	
D511	B0JAML000011	DIODE	1	
D512	B0ACDJ000010	DIODE	1	
D516-18	B0BA03300004	ZENER DIODE	3	
D520	B0ACDJ000010	DIODE	1	
D521	B0JAME000099	DIODE	1	
D522,23	B0JCDD000002	DIODE	2	
D524	B0AACK000004	DIODE	1	
D524	MA165TA5	DIODE	1	
D531	B0HBSN000013	DIODE	1	
D535	MA188	DIODE	1	
D536	B0JBSG000026	DIODE	1	
D538	B0BC5R100039	ZENER DIODE	1	
D539,40	B0HARR000019	DIODE	2	
D543	B0BC01400033	ZENER DIODE	1	
D544,45	B0BA02100001	ZENER DIODE	2	
D546	B0BA02800001	ZENER DIODE	1	
D549	B0BC02500008	ZENER DIODE	1	
D569,70	B0BA05100010	ZENER DIODE	2	
D579	B0AACK000004	DIODE	1	
D582	MAZ705600F	ZENER DIODE	1	
D584	MAZ706200F	ZENER DIODE	1	
D586	B0HAMP000067	DIODE	1	
D598	B0BC5R100039	ZENER DIODE	1	
D599	B0JCND000009	DIODE	1	
D600	B0BC7R400023	ZENER DIODE	1	
D601	B0BC5R100039	ZENER DIODE	1	
D602	B0BC8R100013	ZENER DIODE	1	
D603	B0BA01900005	ZENER DIODE	1	
D701,02	B0BC5R100039	ZENER DIODE	2	
D703	B0EAKT000048	DIODE	1	
F403	K5G631B00007	FUSE	1	△

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
IC401	CNC1S171R	IC	1	△
IC403	CNC1S171R	IC	1	△
IC406	C0DBZZZ00082	IC	1	
IC408	B3PBA0000459	IC	1	△
IC409	MIP3E30MPSCF	IC	1	△
IC411	C0DAEMZ00001	IC	1	
IC412	CNC1S171R	IC	1	△
IC501	C2ABDB000114	IC	1	
IC502	C0EBH0000210	IC	1	
IC504	C0DAEMZ00001	IC	1	
IC505	B3PBA0000459	IC	1	△
IC506	C0DAEMZ00001	IC	1	
IC507	B3PBA0000459	IC	1	△
IC508	C0DAEMZ00001	IC	1	
IC509	C0BBAA000039	IC	1	
IC510	C0DBAZG00034	IC	1	
IC511-13	C0DAEMZ00001	IC	3	
IC520	C9ZB00000561	IC	1	
L403	EXCELSA35	BEAD CHOKE	1	
L404,05	G0B123K00004	CHOKE COIL	2	△
L406	J0JCC0000004	CHIP INDUCTOR	1	
L410	G0B353D00002	CHOKE COIL	1	△
L511	G0A470ZA0035	CHOKE COIL	1	
L512	G0C4R7JA0021	PEAKING COIL	1	
L514	G0A100GA0013	CHOKE COIL	1	
L515	J0JKB0000037	FLAT CORE	1	
L518	J0JCC0000004	CHIP INDUCTOR	1	
P2	K1KA02A00626	2P CONNECTOR	1	
P5	K1KB23A00004	23P CONNECTOR	1	
P9	K1KA03A00537	3P CONNECTOR	1	
P11	K1KA02A00626	2P CONNECTOR	1	
P12	K1KA08A00514	8P CONNECTOR	1	
P25	K1KA13AA0194	13P CONNECTOR	1	
PMM1	TMME047	CLAMPER	1	
PMM2,M3	TMM7464-2	CLAMPER	2	
PMM5	TMM7464-2	CLAMPER	1	
PMM6,M7	TMME260	CLAMPER	2	
PR401	K5Y502BA0001	FUSE	1	△
PR402	ERBSE0R50U	FUSE	1	△
PR501	ERBSE0R50U	FUSE	1	△
PR505	ERBSE5R00U	FUSE	1	△
PR509	ERBSE0R50U	FUSE	1	△
PR601	K5G312B00012	FUSE	1	△
Q401	B1CHND000004	TRANSISTOR	1	
Q402	B1CBGD000001	FET	1	
Q404	B1BCCF000022	TRANSISTOR	1	
Q406	B1DEHQ000014	TRANSISTOR	1	△
Q407	B1HFCFA00021	TRANSISTOR	1	
Q408,09	B1DHCD000034	TRANSISTOR	2	
Q410	2SD1819ARL	TRANSISTOR	1	
Q411	B1HFCFA00021	TRANSISTOR	1	
Q412,13	B1DAGQ000013	TRANSISTOR	2	△
Q420	2SD1819ARL	TRANSISTOR	1	
Q422	B1CBGD000001	FET	1	
Q501,02	2SD1820A0L	TRANSISTOR	2	
Q507	B1DEFQ000008	TRANSISTOR	1	
Q508	B1HBCFA00033	TRANSISTOR	1	
Q509	B1HDCEA00001	TRANSISTOR	1	
Q510	B1DFDD000019	TRANSISTOR	1	
Q517	B1HBCFA00033	TRANSISTOR	1	
Q520	B1HBCFA00033	TRANSISTOR	1	
Q521	B1CBGD000001	FET	1	
Q524	B1CFGF000008	TRANSISTOR	1	
Q525	B1CBGD000001	FET	1	
Q527	B1CERM000012	FET	1	
Q530	B1ADCF000111	TRANSISTOR	1	
Q535	2SD1819ARL	TRANSISTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
Q537	B1DFDD000019	TRANSISTOR	1	
Q538	B1CBGD000001	FET	1	
Q540	B1DFDD000019	TRANSISTOR	1	
Q541	B1CBGD000001	FET	1	
Q553	2SD1819ARL	TRANSISTOR	1	
Q554	B1CHND000004	TRANSISTOR	1	
Q555,56	B1CFRD000018	FET	2	
Q563	2SD1819ARL	TRANSISTOR	1	
Q564,65	B1ADCF000111	TRANSISTOR	2	
Q566	2SD1819ARL	TRANSISTOR	1	
Q569	B1CBGD000001	FET	1	
R401	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R402	ERJ6GEYG821	M 820 OHM, J, 1/10W	1	
R403	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R404	ERJ6GEYG153	M 15KOHM, J, 1/10W	1	
R405	D0B1825JA033	M1.22MOHM, J, 0.05 W	1	△
R406	ERX12SJ4R7	M 4.7 OHM, J, 1/2W	1	
R407	D1AB2203A023	CHIP RESISTOR	1	
R408	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R409	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R410	D1AB2203A023	CHIP RESISTOR	1	
R411	ERF5TJ100	W 10 OHM, J, 5W	1	△
R414	ERJ8GEYJ153	M 15KOHM, J, 1/8W	1	
R415	D1AB2203A023	CHIP RESISTOR	1	
R417	D1AB4303A023	CHIP RESISTOR	1	
R418	ERJ6GEYJ6R8V	M 6.8 OHM, J, 1/10W	1	
R419	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R421	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R422	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R423	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R424	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R425	ERJ6ENF9101	M 18KOHM, 1/10W	1	
R426	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R428	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R429	ERJ6GEYJ4R7	M 4.7 OHM, J, 1/10W	1	
R430	D1AB4303A023	CHIP RESISTOR	1	
R431	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R432	D1AB4303A023	CHIP RESISTOR	1	
R433	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R436	ERJ8GEYJ153	M 15KOHM, J, 1/8W	1	
R437	ERJ6GEYG183	M 18KOHM, J, 1/10W	1	
R438	ERJ6GEYG331	M 330 OHM, G, 1/10W	1	
R439	ERG12SJ120	M 12 OHM, J, 1/2W	1	
R440	ERJ8GEYJ474	M 470KOHM, J, 1/8W	1	
R441,42	D1AB6803A023	CHIP RESISTOR	2	
R443	EVMAASA00B23	CONTROL 2KOHMB	1	
R444	ERJ6GEYF123	M 12KOHM, J, 1/10W	1	
R445	D1AB6803A023	CHIP RESISTOR	1	
R448,49	D0XGR12J0001	M 0.12OHM, J, 5W	2	
R450	ERJ6GEYJ4R7	M 4.7 OHM, J, 1/10W	1	
R451	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R452	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R454	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R455	ERJ6GEYF123	M 12KOHM, J, 1/10W	1	
R456	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R458	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R459	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R460	ERDS2TC0	C 0 OHM, 1/4W	1	
R461	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R463	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R464	ERJ6ENF3302	M 33KOHM, 1/10W	1	
R467	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R468,69	ERX12SJ1R0	M 0.1 OHM, J,1/2W	2	
R471	ERJ8GEYJ332	M 3.3KOHM, J,1/8W	1	
R472-74	D1AB5603A023	CHIP RESISTOR	3	
R476,77	ERJ14YJ181	M 181 OHM, J,1/4W	2	
R478	ERJ8GEYJ220	M 22 OHM, J,1/8W	1	
R482	ERJ8GEYJ220	M 22 OHM, J,1/8W	1	
R483	DOB334JA030	CHIP RESISTOR	1	△
R484	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R485	ERJ6GEYF472	M 4.7KOHM, F,1/10W	1	
R488	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R490	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R491	ERJ6GEYG821	M 820 OHM, J,1/10W	1	
R493	ERG12SJ120	M 12 OHM, J,1/2W	1	
R498	ERG3SJ101	M 100 OHM, J, 3W	1	
R500	ERJ6GEYJ224	M 220KOHM, J,1/10W	1	
R501	ERJ6GEYG154	M 150KOHM, J,1/10W	1	
R502,03	ERJ6GEYJ224	M 220KOHM, J,1/10W	2	
R505	ERJ8GEYJ330	M 33 OHM, J,1/8W	1	
R507	ERJ6GEYG221	M 220 OHM, J,1/10W	1	
R508	ERJ6GEYG182	M 1.8KOHM, J,1/10W	1	
R510	ERJ8GEY0R00	M 0 OHM, 1/8W	1	
R512	ERJ6GEYG823	M 82KOHM, J,1/10W	1	
R513	ERJ6GEYG332	M 3.3KOHM, J,1/10W	1	
R514	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R518	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R519	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R520	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R523	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R524	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R526,27	ERJ6ENF1803	M 180KOHM, 1/10W	2	
R528	ERJ6GEYJ4R7	M 4.7 OHM, J,1/10W	1	
R529	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R530,31	ERJ6RBD333	M 33KOHM, J,1/10W	2	
R532	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R533	ERJ6ENF1803	M 180KOHM, 1/10W	1	
R534	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R537	ERJ6ENF1003	M 100KOHM, 1/10W	1	
R538	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R539	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R540,41	ERJ6GEYG105	M 1MOHM, J,1/10W	2	
R542	ER0S2CKF2202	M 22KOHM, F,1/4W	1	
R543	ERJ6ENF3902	M 39KOHM, 1/10W	1	
R545	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R546	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R547	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R550	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R551	ERJ6GEYF151	M 150 OHM, F,1/10W	1	
R553	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R555	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R556	ERJ6GEYG105	M 1MOHM, J,1/10W	1	
R557,58	ERJ6GEYJ101V	M 100 OHM, J,1/10W	2	
R559	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R560	ERJ6ENF9101	M 9.1KOHM, 1/10W	1	
R561	ERJ6ENF5101	M 5.1KOHM, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R562	ERJ6ENF4701	M 4.7KOHM, 1/10W	1	
R563	ERJ6GEYJ2R2	M 2.2 OHM, J,1/10W	1	
R564	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R565,66	ERJ6GEYG105	M 1MOHM, J,1/10W	2	
R567,68	ERJ8GEYJ105	M 1MOHM, J,1/8W	2	
R569	ERJ6ENF3302	M 33KOHM, 1/10W	1	
R570	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R571	ERJ6GEYG105	M 1MOHM, J,1/10W	1	
R572,73	ERJ6GEYG102	M 1KOHM, J,1/10W	2	
R574	ERJ6GEYG331	M 330 OHM, G,1/10W	1	
R576	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R579	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R581	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R582	ERJ6ENF1002	M 10KOHM, 1/10W	1	
R584	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R585	ERJ6GEYF333	M 33KOHM, J,1/10W	1	
R586	ERJ6GEYJ223	M 22KOHM, J,1/10W	1	
R587	ERJ8RSJR16V	M 16 OHM, 1/8W	1	
R592	ERJ6GEYJ223	M 22KOHM, J,1/10W	1	
R593	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R594	ERJ6GEYF151	M 150 OHM, F,1/10W	1	
R595	ERJ6GEYG221	M 220 OHM, J,1/10W	1	
R596	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R597,98	ERJ6ENF3302	M 33KOHM, 1/10W	2	
R599,00	ERJ8ENF3900	M 390 OHM, 1/8W	2	
R601	ERJ6GEYJ471	M 470 OHM, J,1/10W	1	
R603	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R604	ERJ6RBD303	M 30KOHM, J,1/10W	1	
R605	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R606	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R607	ERJ6ENF2202	M 2.2KOHM, 1/10W	1	
R608	ERJ8GEYJ332	M 3.3KOHM, J,1/8W	1	
R609	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R610	ERJ6GEYG222	M 2.2KOHM, J,1/10W	1	
R611	ERDS2FJ101	C 100 OHM, J,1/4W	1	
R612	ERJ6GEYG222	M 2.2KOHM, J,1/10W	1	
R613	ERJ6ENF2402	M 24KOHM, 1/10W	1	
R614	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R616,17	ERJ6GEYJ223	M 22KOHM, J,1/10W	2	
R618	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R619	ERJ8RQFR39V	M 0.39OHM, J,1/8W	1	
R620	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R622	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R624	ERX2SJR22P	M0.22 OHM, J, 2W	1	
R625	ERJ6GEYF472	M 4.7KOHM, F,1/10W	1	
R626	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R627	ERJ6GEYJ752	M 7.5KOHM, J,1/10W	1	
R628	EVMAASA00B33	CONTROL 3KOHMB	1	
R629	ERJ6GEYG105	M 1MOHM, J,1/10W	1	
R630	ERJ6GEYF472	M 4.7KOHM, F,1/10W	1	
R631	ERJ8GEYJ333	M 33KOHM, J,1/8W	1	
R632	ERJ6GEYG221	M 220 OHM, J,1/10W	1	
R633	ERJ6GEYG105	M 1MOHM, J,1/10W	1	
R634	ERJ8RQFR39	M 0.39OHM, J,1/8W	1	
R635	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R636	ERJ6ENF1603	M 160KOHM, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R637	ERJ8RQFR39	M 0.390HM, J,1/8W	1	
R641	ERJ6GEYF473	M 47KOHM, J,1/10W	1	
R642-44	ERJ8RQFR39	M 0.390HM, J,1/8W	3	
R645	ERJ6GEYJ101V	M 100 OHM, J,1/10W	1	
R646,47	ERJ14YJ330	M 33 OHM, J,1/4W	2	
R648	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R649	ERJ6GEYJ223	M 22KOHM, J,1/10W	1	
R650	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R651	ERJ6ENF1002	M 10KOHM, 1/10W	1	
R652	ERJ6GEYF123	M 12KOHM, J,1/10W	1	
R653	ERJ6ENF3302	M 33KOHM, 1/10W	1	
R654	ERJ6GEYJ223	M 22KOHM, J,1/10W	1	
R655	ERJ8RSJR16V	M 16 OHM, 1/8W	1	
R656	ERJ6ENF1803	M 180KOHM, 1/10W	1	
R657	ERJ6GEYF561	M 560 OHM, F,1/10W	1	
R658	ERJ6GEYG105	M 1MOHM, J,1/10W	1	
R659	ERJ6RBD303	M 30KOHM, J,1/10W	1	
R660	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R661	EVMAASA00B53	CONTROL 5KOHMB	1	
R662	ERJ6ENF1503	M 150KOHM, 1/10W	1	
R664	ERJ6ENF9101	M 9.1KOHM, 1/10W	1	
R665	EVMAASA00B23	CONTROL 2KOHMB	1	
R669	ERJ6ENF1503	M 150KOHM, 1/10W	1	
R670	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R671	ERJ6RBD911	M 910 OHM, J,1/10W	1	
R672,73	ERJ6GEYG102	M 1KOHM, J,1/10W	2	
R674	ERJ8GEYJ333	M 33KOHM, J,1/8W	1	
R675	ERJ6ENF2202	M 2.2KOHM, 1/10W	1	
R676	ERJ8GEYJ333	M 33KOHM, J,1/8W	1	
R677	ERJ6GEYJ474	M 470KOHM, J,1/10W	1	
R678-80	ERJ8RSJR16V	M 16 OHM, 1/8W	3	
R682	ERJ6ENF2002	M 20KOHM, 1/10W	1	
R683	ERJ14YJ330	M 33 OHM, J,1/4W	1	
R684,85	ERJ6GEYG102	M 1KOHM, J,1/10W	2	
R686	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R687	ERJ6GEYG104	M 100KOHM, J,1/10W	1	
R688	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R689	ERJ8GEYJ472	M 4.7KOHM, J,1/8W	1	
R690	ERJ6GEYJ4R7	M 4.7 OHM, J,1/10W	1	
R691	ERJ6GEYG105	M 1MOHM, J,1/10W	1	
R693	ERJ6GEYJ100V	M 10 OHM, J,1/10W	1	
R695	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R696	ERJ6GEYJ100V	M 10 OHM, J,1/10W	1	
R697	ERJ6GEYJ4R7	M 4.7 OHM, J,1/10W	1	
R698	ERJ8RSJR16V	M 16 OHM, 1/8W	1	
R699	ERJ8GEYJ105	M 1MOHM, J,1/8W	1	
R700,01	ERJ6ENF1503	M 150KOHM, 1/10W	2	
R702	ERJ6ENF1102	M 11KOHM, 1/10W	1	
R707,08	ERJ6GEYG102	M 1KOHM, J,1/10W	2	
R709,10	ERJ6GEYJ101V	M 100 OHM, J,1/10W	2	
R711,12	ERJ6GEYG222	M 2.2KOHM, J,1/10W	2	
R713	ERJ6GEYG152	M 1.5KOHM, J,1/10W	1	
R714	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R715	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R716	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R717	ERJ6GEYG122	M 1.2KOHM, J,1/10W	1	
R718	ERJ6GEYG103	M 10KOHM, J,1/10W	1	
R719	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
R720	ERJ6GEYG152	M 1.5KOHM, J,1/10W	1	
R721	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R722-24	ERJ6GEYG102	M 1KOHM, J,1/10W	3	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R726,27	ERJ6GEYG222	M 2.2KOHM, J,1/10W	2	
R729	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R730-38	ERJ8GEYJ105	M 1MOHM, J,1/8W	9	
R739	ERJ6ENF1003	M 100KOHM, 1/10W	1	
R740	ERJ6GEYJ243	M 24KOHM, J,1/10W	1	
R741	ERJ8GEYJ205	M 2MOHM, J,1/8W	1	
R742	ERJ6GEYG102	M 1KOHM, J,1/10W	1	
RL401-03	K6B1CGA00055	REALY	3	△
S401,02	J0LT00000009	SWITCH	2	△
T401	G4D4A0000122	SWITCHING TRANS	1	
T402	G4D1A0000128	SWITCHING TRANS	1	△
T404	ETS42LB11GAD	SWITCHING TRANS	1	△
T410	G4D2A0000283	SWITCHING TRANS	1	△
T601	G4D2A0000284	SWITCHING TRANS	1	
W13	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
W46	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
X501	H2B400400021	CRYSTAL	1	
Z1-Z3	K4ZZ01000206	TERMINAL	3	
ZN401,02	D4EAD6210001	VARISTOR	2	△
ZN403	ERZVGAD681T2	VARISTOR	1	△
ZN404.405	ERZVA7D511	VARISTOR	2	△

16.11. Electrical Replacement Parts List (42inch)

Note:

All parts except parts mentioned [PAVCCZ] in the Remarks column are supplied by PAVC-CSG.

Parts mentioned [PAVCCZ] are supplied by PAVCCZ.

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
F401.402	K5D802BNA005	TIME LAG FUSE HIGH	2	△
C10	K1MN20BA0231	20P CONNECTOR	1	
C11	K1MN55BA0076	55P CONNECTOR	1	
C20	K1MN20BA0231	20P CONNECTOR	1	
C21	K1MN55BA0076	55P CONNECTOR	1	
C23	K1KA12BA0107	12P CONNECTOR	1	
C1102	FIJ1A106A043	C 0.010UF, K, 16V	1	
C1103,04	FI61C104A081	C 0.10UF, K, 16V	2	
C1106	FIH1H2700008	E 27UF, 50V	1	
C1107	FIH1H2200008	E 22UF, 50V	1	
C1108	FI61C104A081	C 0.10UF, K, 16V	1	
C1109	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C1111	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C1112	FI61C104A081	C 0.10UF, K, 16V	1	
C1114	FI61C104A081	C 0.10UF, K, 16V	1	
C1117	FI61C104A081	C 0.10UF, K, 16V	1	
C1122	FI61E1030005	C 0.01UF, Z, 25V	1	
C1123	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C2005-08	FIH1H5610007	E 560UF, 50V	4	PAVCCZ
C2010-15	FIH1H5610007	E 560UF, 50V	6	PAVCCZ
C2021,22	FIH1H5610007	E 560UF, 50V	2	PAVCCZ
C2023	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2048-50	ECJ1XB1H104K	C 10PF, J, 50V	3	
C2052,53	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2054	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2055	ECJ1VC1H120J	C 12PF, J, 50V	1	
C2056	ECJ1VC1H080C	C 8PF, C, 50V	1	TH-42PX70B/E
C20156	ECJ1VC1H120J	C 12PF, J, 50V	1	TH-42PV70F/P
C2057,58	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2059	F2G0J470A019	E 47UF 6.3V	1	
C2060	F2G0J470A019	E 47UF 6.3V	1	TH-42PX70B/E
C2061	ECJ1XB1H104K	C 10PF, J, 50V	1	TH-42PX70B/E
C2062-64	FIJ0J106A021	C 0.010UF, K, 16V	3	PAVCCZ TH-42PX70B/E
C2065	ECJ1XB1H104K	C 10PF, J, 50V	1	TH-42PX70B/E
C2068,69	ECJ1VB1H102K	C 1000UF, Z, 50V	2	TH-42PX70B/E
C2088	ECJ2FB1A475K	C 4.7UF, K, 10V	1	
C2089	FIH1H5610007	E 560UF, 50V	1	PAVCCZ
C2091	ECJ1VC1H100C	C 10PF, C, 50V	1	
C2092	FIH1H2200008	E 22UF, 50V	1	
C2096,97	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2100	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2101	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2102	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2103,04	FIJ1A106A043	C 0.010UF, K, 16V	2	
C2105,06	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2107,08	F2G0J470A019	E 47UF 6.3V	2	
C2109,10	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2111	FIH0J2250008	C 2.2UF, K, 16V	1	
C2112,13	F2G0J470A019	E 47UF 6.3V	2	
C2114,15	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2116	FIH1H471A792	E 470UF, 50V	1	
C2117	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2118	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C2119	EEH1A221P	C 220PF, J, 10V	1	
C2120,21	FIH1H5600007	E 56UF, 50V	2	PAVCCZ
C2122,23	FIJ1A106A043	C 0.010UF, K, 16V	2	
C2124	ECJ1XB1H104K	C 10PF, J, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C2126	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2127	ECJ1VB1C105K	C 0.01UF, K, 16V	1	TH-42PX70B/E
C2129	ECJ1VB1C105K	C 0.01UF, K, 16V	1	TH-42PX70B/E
C2130	FIJ0J106A021	C 0.010UF, K, 16V	1	PAVCCZ
C2131	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2133	EEH1B1H4R7R	C 4.7PF, J, 50V	1	
C2134	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2135,36	ECJ1VB1C105K	C 0.01UF, K, 16V	2	
C2137	F2G0J470A019	E 47UF 6.3V	1	
C2138	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2139-42	FIJ1A106A043	C 0.010UF, K, 16V	4	
C2143	FIH1H181A792	E 180UF, 50V	1	
C2146	FIH1H181A792	E 180UF, 50V	1	
C2147	EEH1B1C220R	C 22PF, J, 16V	1	
C2151	F2G0J470A019	E 47UF 6.3V	1	
C2153	ECJ1VC1H330J	C 33PF, J, 50V	1	
C2154	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2159,60	ECJ1VB1C105K	C 0.01UF, K, 16V	2	
C2161	EEH1B1C101UP	C 100PF, J, 16V	1	
C2162-65	ECJ1VB1C105K	C 0.01UF, K, 16V	4	
C2170	ECJ1VC1H330J	C 33PF, J, 50V	1	
C2171	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2173	ECJ2FF1C475Z	C 0.047UF, Z, 16V	1	
C2183	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2185	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2186	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2187	FIH0J2250008	C 2.2UF, K, 16V	1	
C2188	FIH1H471A792	E 470UF, 50V	1	
C2189	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C2190,91	FIJ1A106A043	C 0.010UF, K, 16V	2	
C2192	F2G0J470A019	E 47UF 6.3V	1	
C2213	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2216	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2244	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2245	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2246	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2251	FIJ1A106A043	C 0.010UF, K, 16V	1	
C2261-64	FIJ1A106A043	C 0.010UF, K, 16V	4	
C2265-68	ECJ1XC1H101J	C 100PF, J, 50V	4	
C2272	ECJ2FF1C475Z	C 0.047UF, Z, 16V	1	
C2274	ECJ1XB1H104K	C 10PF, J, 50V	1	TH-42PX70B/E
C2280	ECJ2FB1A475K	C 4.7UF, K, 10V	1	
C2281	FIH1H5610007	E 560UF, 50V	1	PAVCCZ
C2288,89	FIJ1A106A043	C 0.010UF, K, 16V	2	
C2301,02	ECJ1XB1C104K	C 0.1UF, Z, 16V	2	
C2303	FIJ1E105A171	E 1 UF 25V	1	
C2305	FIJ1E105A171	E 1 UF 25V	1	
C2307	FIJ1E105A171	E 1 UF 25V	1	
C2309	FIJ1E105A171	E 1 UF 25V	1	
C2311	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2313	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2315	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2317	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2319	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2321	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2323	ECJ1VB1C333K	C 0.033UF, K, 16V	1	
C2325	FIJ1H474A757	C 0.47UF, 50V	1	
C2327	ECJ1XB1H104K	C 10PF, J, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C2329	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2331	F1J1H474A757	C 0.47UF, 50V	1	
C2333	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2335	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2337	F1H1H223A219	E 0.022UF, 50V	1	
C2339	F1H1H223A219	E 0.022UF, 50V	1	
C2341	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2343	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2345	F1H1H223A219	E 0.022UF, 50V	1	
C2347	F1H1H223A219	E 0.022UF, 50V	1	
C2349	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2352	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C2353	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2355	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2357	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2359	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2361	EEEFGE1E471P	E 470UF, 25V	1	
C2363	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2365	EEEBB1C221UP	C 220PF, J, 16V	1	
C2375	F1H1H223A219	E 0.022UF, 50V	1	
C2377	F1H1H223A219	E 0.022UF, 50V	1	
C2379	F1H1H223A219	E 0.022UF, 50V	1	
C2381	F1H1H223A219	E 0.022UF, 50V	1	
C2383	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2385	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2387	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2389	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2502,03	ECJ2XB1H102K	C 1000PF, K, 50V	2	
C2512	F1K0J1060020	C 10UF, K, 6.3V	1	
C2515	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2517	ECJ1VB1H103K	C 0.001UF, K, 50V	1	TH-42PX70B/E
C2521	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C2522-27	ECJ1VB1H102K	C 1000UF, Z, 50V	6	
C2601,02	ECJ1XB1H104K	C 10PF, J, 50V	2	
C2801	ECJ3XB1C106M	C 1.0UF, K, 16V	1	
C2802,03	F1J1H474A757	C 0.47UF, 50V	2	
C2813	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2814	ECJ1VB1H472K	C 4700PF, K, 50V	1	
C2815	ECJ1XB1H104K	C 10PF, J, 50V	1	
C2816	EEEBB1V220P	E 22UF, 35V	1	
C2817	ECJ1VB1H102K	C 1000UF, Z, 50V	1	
C2819	EEEBB1E470P	C 47PF, J, 25V	1	
C3001,02	ECJ1VB1H102K	C 1000UF, Z, 50V	2	
C3021	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C3024,25	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C3026	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3040	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3043	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C3047	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C3049-56	ECJ1VB1A105K	C 0.01UF, Z, 50V	8	
C3066	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	TH-42PX70B/E
C3068	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3070	EEEBB1C471UP	C 470PF, J, 16V	1	
C3071	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3072	EEEBB1C471UP	C 470PF, J, 16V	1	
C3075,76	EEEBB1C221UP	C 220PF, J, 16V	2	
C3081	F2H0J1010009	C 100UF, 6.3V	1	PAVCCZ
C3100-02	ECJ1VB1A105K	C 0.01UF, Z, 50V	3	
C3103	EEEBB1C100R	C 10PF, J, 16V	1	
C3115-17	ECJ1XB1H104K	C 10PF, J, 50V	3	
C3118	EEEBB1C470P	C 47PF, J, 16V	1	
C3119	EEEBB1C100R	C 10PF, J, 16V	1	
C3120	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3201	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3214	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3216	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3226-28	ECJ1XB1H104K	C 10PF, J, 50V	3	
C3230	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3263	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3265-68	ECJ1XB1H104K	C 10PF, J, 50V	4	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C3270	EEEBB0J102UP	C 1100PF, J, 6.3V	1	PAVCCZ
C3271	EEEBB1C100R	C 10PF, J, 16V	1	
C3272	ECJ1XB1H104K	C 10PF, J, 50V	1	
C3273	F2G1H100A031	E 10UF, 50V	1	PAVCCZ
C3274-76	ECJ1XB1C104K	C 0.1UF, Z, 16V	3	
C3279	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C3280	ECJ1XC1H101J	C 100PF, J, 50V	1	
C3281	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C3750	F1J1H102A721	E 1000UF, 50V	1	PAVCCZ
C4500-03	F1G1C104A081	C 0.10UF, K, 16V	4	
C4506,07	F1G1C104A081	C 0.10UF, K, 16V	2	
C4508,09	EEEBB0J330R	C 33PF, J, 6.3V	2	
C4510,11	F1G1C104A081	C 0.10UF, K, 16V	2	
C4515	F1G1C104A081	C 0.10UF, K, 16V	1	
C4527	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4528	F1G1C104A081	C 0.10UF, K, 16V	1	
C4531	F1G1C104A081	C 0.10UF, K, 16V	1	
C4533	F1G1H680A565	E 68UF, 50V	1	
C4534,35	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4537	ECJ1XB1H104K	C 10PF, J, 50V	1	
C4538	F2G0J470A019	E 47UF 6.3V	1	
C4539	F1J1A106A043	C 0.010UF, K, 16V	1	
C4541	F1H1H471A219	E 470UF, 50V	1	
C4543-45	F1G1C104A081	C 0.10UF, K, 16V	3	
C4546	F1H0J2250008	C 2.2UF, K, 16V	1	
C4547	F1G1C104A081	C 0.10UF, K, 16V	1	
C4548,49	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4550	F1G1C104A081	C 0.10UF, K, 16V	1	
C4551,52	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4553	F1G1H1020008	E 1000UF, 50V	1	
C4555,56	F1J1A106A043	C 0.010UF, K, 16V	2	
C4557	F1G1C104A081	C 0.10UF, K, 16V	1	
C4559,60	F1G1C104A081	C 0.10UF, K, 16V	2	
C4562	F1H1H822A219	E 8200UF, 50V	1	
C4563	ECJ1VB1C823K	C 0.082UF, K, 16V	1	
C4564,65	F1G1E1030005	C 0.01UF, Z, 25V	2	
C4566	ECJ1XB1C393K	C 0.039UF, K, 16V	1	
C4567	ECJ1XB1H104K	C 10PF, J, 50V	1	
C4568	F1G1C104A081	C 0.10UF, K, 16V	1	
C4569	F1J1C684A097	C 0.68UF, Z, 16V	1	
C4570	F2G0J470A019	E 47UF 6.3V	1	
C4572,73	F1G1C104A081	C 0.10UF, K, 16V	2	
C4574	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4575	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4576	F2G0J470A019	E 47UF 6.3V	1	
C4577,78	F1G1C104A081	C 0.10UF, K, 16V	2	
C4580	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4581	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4582,83	F1G1C104A081	C 0.10UF, K, 16V	2	
C4584,85	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C4586	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4587	F1G1C104A081	C 0.10UF, K, 16V	1	
C4588	ECJ1VB1C823K	C 0.082UF, K, 16V	1	
C4589	F1G1H150A565	E 15UF, 50V	1	
C4590	ECJ0EC1H180J	C 180PF, K, 50V	1	
C4591,92	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C4593	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4595	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4596	F1G1C104A081	C 0.10UF, K, 16V	1	
C4598	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4600,01	F1G1E1030005	C 0.01UF, Z, 25V	2	
C4602	F1G1C104A081	C 0.10UF, K, 16V	1	
C4604	F1H0J2250008	C 2.2UF, K, 16V	1	
C4605	F1G1C104A081	C 0.10UF, K, 16V	1	
C4607	F2G0J470A019	E 47UF 6.3V	1	
C4609	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4611	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C4612	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4613	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4614	F1G1C104A081	C 0.10UF, K, 16V	1	
C4615	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4616,17	F1G1C104A081	C 0.10UF, K, 16V	2	
C4618	F1G1E1030005	C 0.01UF, Z, 25V	1	
C4619	F1G1C104A081	C 0.10UF, K, 16V	1	
C4620	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C4623	F1G1C104A081	C 0.10UF, K, 16V	1	
C4624,25	ECJ1XB1H104K	C 10PF, J, 50V	2	
C4628	F1G1C104A081	C 0.10UF, K, 16V	1	
C4629	F1J1A106A043	C 0.010UF, K, 16V	1	
C4807	F1G1C104A081	C 0.10UF, K, 16V	1	
C5501	F2A1C471A537	E 470UF, 16V	1	PAVCCZ
C5502	ECJ2VB1C104K	C 0.1UF, K, 16V	1	
C5503	F2A1C471A537	E 470UF, 16V	1	PAVCCZ
C5504	ECJ2VB1C104K	C 0.1UF, K, 16V	1	
C5521,22	ECJ2VB1C104K	C 0.1UF, K, 16V	2	
C5551	F2A1H331A257	E 330UF, 50V	1	
C5552	ECJ2VB1E104K	C 0.1UF, K, 25V	1	
C5595	ECA1HM220	E 22UF, 50V	1	
C5600	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C5601	F1G1C104A081	C 0.10UF, K, 16V	1	
C5602	ECGRLOG680ER	C 68PF, J, 4V	1	
C5603,04	F1G1E1030005	C 0.01UF, Z, 25V	2	
C5605	F1J1A475A039	C 4.7UF, K, 10V	1	
C5606	F1H1H471A219	E 470UF, 50V	1	
C5607	F1G1H221A459	E 220UF, 50V	1	PAVCCZ
C5608	F1G1C104A081	C 0.10UF, K, 16V	1	
C5609,10	EEHBL1C470P	C 47PF, J, 16V	2	
C5615	F1J1A106A043	C 0.010UF, K, 16V	1	
C5616	ECJ0EB1A473K	C 0.047UF, K, 10V	1	
C5617	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C5618,19	F1J1A106A043	C 0.010UF, K, 16V	2	
C5620	ECJ1XB1H104K	C 10PF, J, 50V	1	
C5621	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5622	F1J1A475A039	C 4.7UF, K, 10V	1	
C5623	ECJ0EB1H471K	C 470PF, K, 50V	1	
C5624	F1G1H221A459	E 220UF, 50V	1	PAVCCZ
C5625	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5626,27	F1G1C104A081	C 0.10UF, K, 16V	2	
C5628,29	ECGRLOG680ER	C 68PF, J, 4V	2	
C5630,31	EEHBL1C470P	C 47PF, J, 16V	2	
C5632	ECJ1VB1C105K	C 0.01UF, K, 16V	1	
C5636-41	F1G1C104A081	C 0.10UF, K, 16V	6	
C5643	ECJ1XB1H104K	C 10PF, J, 50V	1	
C5644	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5645	F1H1A225A051	E 22UF, 50V	1	
C5661	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5662	ECJ0EB1A473K	C 0.047UF, K, 10V	1	
C5663	F1G1E1030005	C 0.01UF, Z, 25V	1	
C5670	ECJ1VB1A105K	C 0.01UF, Z, 50V	1	
C5673,74	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	
C5676	F1G1C104A081	C 0.10UF, K, 16V	1	
C5690,91	F2G0J470A019	E 47UF 6.3V	2	
C5692,93	ECJ1XB1H104K	C 10PF, J, 50V	2	
C5694,95	F2G0J470A019	E 47UF 6.3V	2	
C5710-16	ECJ2VF1C104Z	C 0.1UF, Z, 16V	7	
C6001	F1L2J332A022	C 3300UF, K, 6.3V	1	
C6002	F1L2J222A022	C 2200UF, K, 6.3V	1	
C6011-15	F2A2T201A002	E 200UF,	5	
C6021,22	F1L2J272A022	C 2700UF, K, 6.3V	2	
C6031	FOC2E225A218	E 0.022UF, 250V	1	
C6037	F1L1E4750004	C 4.7UF, 25V	1	
C6091	F1L2J1020001	C 1000UF, K, 6.3V	1	
C6111,12	F2A2D221A022	E 220UF, 200V	2	
C6132	F1L1E4750004	C 4.7UF, 25V	1	
C6134,35	F1L1E4750004	C 4.7UF, 25V	2	
C6151	ECJ3YB1E105K	C 1UF, K, 25V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C6152-54	F1L1E4750004	C 4.7UF, 25V	3	
C6193-95	F1L1E4750004	C 4.7UF, 25V	3	
C6197	F1L1E4750004	C 4.7UF, 25V	1	
C6201,02	FOC2E405A176	E 0.040UF, 250V	2	
C6209	F1L1E4750004	C 4.7UF, 25V	1	
C6211,12	F1L1E4750004	C 4.7UF, 25V	2	
C6213	F2A1E102A220	E 1000UF, 25V	1	
C6220	F1L2J1020001	C 1000UF, K, 6.3V	1	
C6221	ECJ2XB1H104K	C 0.1UF, K, 50V	1	
C6241	F2A1A101A439	E 100UF, 10V	1	
C6242	F1H1C105A072	C 1UF, K, 16V	1	
C6243	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6251	F1H1C105A072	C 1UF, K, 16V	1	
C6252	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6261,62	F2A2A221A073	E 220UF, 100V	2	
C6272,73	F2A1E221A487	E 220UF, 25V	2	
C6276	F1L1E4750004	C 4.7UF, 25V	1	
C6286-89	ECJ2XB1H104K	C 0.1UF, K, 50V	4	
C6401	F1L2J332A022	C 3300UF, K, 6.3V	1	
C6402	F1L2J222A022	C 2200UF, K, 6.3V	1	
C6411-15	F2A2T201A002	E 200UF,	5	
C6421,22	F1L2J272A022	C 2700UF, K, 6.3V	2	
C6431	FOC2E405A176	E 0.040UF, 250V	1	
C6480	ECJ2XB1H104K	C 0.1UF, K, 50V	1	
C6502	F1L1E4750004	C 4.7UF, 25V	1	
C6504,05	F1L1E4750004	C 4.7UF, 25V	2	
C6521	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6522	F1L1E4750004	C 4.7UF, 25V	1	
C6524,25	F1L1E4750004	C 4.7UF, 25V	2	
C6527	F1L1E4750004	C 4.7UF, 25V	1	
C6531,32	FOC2E405A176	E 0.040UF, 250V	2	
C6561	F2A1A101A439	E 100UF, 10V	1	
C6562	F1H1C105A072	C 1UF, K, 16V	1	
C6563	F2A1A101A439	E 100UF, 10V	1	
C6564	F1H1C105A072	C 1UF, K, 16V	1	
C6565,66	ECJ2VB1H103K	C 0.01UF, K, 50V	2	
C6581	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6582	F1H1C105A072	C 1UF, K, 16V	1	
C6592	F2A1E221A487	E 220UF, 25V	1	
C6593	ECJ2XC1H102J	C 1000PF, J, 50V	1	
C6603,04	F1K2J102A014	C 1000UF, K, 6.3V	2	
C6605,06	F1L2J472A022	C 4700UF, K, 6.3V	2	
C6620,21	F1E2J222A002	C 2200PF, 600V	2	
C6641	ECQE2224KF3	P 2.2UF, K, 250V	1	PAVCCZ
C6661,62	F1K2J102A014	C 1000UF, K, 6.3V	2	
C6671	F1L1E4750004	C 4.7UF, 25V	1	
C6691	ECA2CM101	E 100UF, 160V	1	
C6694	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6695	ECJ2XC1H102J	C 1000PF, J, 50V	1	
C6702-06	ECJ2XB1H104K	C 0.1UF, K, 50V	5	
C6708	ECJ2XB1H104K	C 0.1UF, K, 50V	1	
C6721	ECA1HM101	E 100UF, 50V	1	
C6722	ECJ2XC1H101J	C 100PF, J, 50V	1	
C6723-25	F1L1E4750004	C 4.7UF, 25V	3	
C6726,27	F1H1C105A072	C 1UF, K, 16V	2	
C6740	ECJ2XC1H101J	C 100PF, J, 50V	1	
C6752	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6753	F1L1E4750004	C 4.7UF, 25V	1	
C6755,56	F1L1E4750004	C 4.7UF, 25V	2	
C6771	F1H1C105A072	C 1UF, K, 16V	1	
C6772,73	F1L1E4750004	C 4.7UF, 25V	2	
C6775	F1L1E4750004	C 4.7UF, 25V	1	
C6776,77	ECJ2XB1H104K	C 0.1UF, K, 50V	2	
C6791	F2A1E221A487	E 220UF, 25V	1	
C6795,96	F2A1E221A487	E 220UF, 25V	2	
C6801	F2A2E470A022	E 47UF, 250V	1	
C6803	ECKD3D221KBP	C 220PF, K, 2KV	1	
C6804	F2A2E100A022	E 10UF, 250V	1	
C6805	ECJ2XC1H331J	C 330PF, J, 50V	1	
C6806	ECA2CM101	E 100UF, 160V	1	
C6811	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6812	F1L1E4750004	C 4.7UF, 25V	1	
C6813	ECA2CM101	E 100UF, 160V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C6814	F2A1E221A487	E 220UF, 25V	1	
C6815	ECJ2XC1H102J	C 1000PF, J, 50V	1	
C6822	F2A2G470A018	E 470UF, 400V	1	
C6823	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6832	ECJ2XB1H392K	C 3900PF, K, 50V	1	
C6841	F2A2E470A022	E 47UF, 250V	1	
C6842	ECA2CM101	E 100UF, 160V	1	
C6845	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6861	F1H1C105A072	C 1UF, K, 16V	1	
C6862	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6863	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6871	F1H1C105A072	C 1UF, K, 16V	1	
C6872	ECJ3YB1E105K	C 1UF, K, 25V	1	
C6873	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C6901	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6902	TCUY1C105ZFN	C 1UF, 16V	1	
C6904	TCUY1C105ZFN	C 1UF, 16V	1	
C6906	TCUY1C105ZFN	C 1UF, 16V	1	
C6908	TCUY1C105ZFN	C 1UF, 16V	1	
C6910	TCUY1C105ZFN	C 1UF, 16V	1	
C6912	TCUY1C105ZFN	C 1UF, 16V	1	
C6921	F1L2E1040002	E 1000UF, 25V	1	
C6923,24	F1L2E1040002	E 1000UF, 25V	2	
C6926,27	F1L2E1040002	E 1000UF, 25V	2	
C6929	F1L2E1040002	E 1000UF, 25V	1	
C6931	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6936	ECJ2XB1H681K	C 680PF, K, 50V	1	
C6937	ECJ2VB1H221K	C 220PF, K, 50V	1	
C6951	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6952	TCUY1C105ZFN	C 1UF, 16V	1	
C6955	TCUY1C105ZFN	C 1UF, 16V	1	
C6957,58	TCUY1C105ZFN	C 1UF, 16V	2	
C6961	TCUY1C105ZFN	C 1UF, 16V	1	
C6963	TCUY1C105ZFN	C 1UF, 16V	1	
C6971	F1L2E1040002	E 1000UF, 25V	1	
C6973,74	F1L2E1040002	E 1000UF, 25V	2	
C6976,77	F1L2E1040002	E 1000UF, 25V	2	
C6979	F1L2E1040002	E 1000UF, 25V	1	
C6981	ECJ2XB1H102K	C 1000PF, K, 50V	1	
C6986	ECJ2XB1H681K	C 680PF, K, 50V	1	
C6987	ECJ2VB1H221K	C 220PF, K, 50V	1	
C7110	F1H1C105A072	C 1UF, K, 16V	1	
C7114	F1H1C105A072	C 1UF, K, 16V	1	
C7116	F1H1C105A072	C 1UF, K, 16V	1	
C7117	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7118	F1K2A474A006	C 0.47UF, 6.3V	1	
C7121	F1H1C105A072	C 1UF, K, 16V	1	
C7123	F1H1C105A072	C 1UF, K, 16V	1	
C7124	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7125	F1K2A474A006	C 0.47UF, 6.3V	1	
C7126	F1H1C105A072	C 1UF, K, 16V	1	
C7127	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7128	F1K2A474A006	C 0.47UF, 6.3V	1	
C7130	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C7140	F1H1C105A072	C 1UF, K, 16V	1	
C7141	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7142	F1K2A474A006	C 0.47UF, 6.3V	1	
C7145	F1H1C105A072	C 1UF, K, 16V	1	
C7148	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	
C7150-53	F1K2A474A006	C 0.47UF, 6.3V	4	
C7203	F1H1C105A072	C 1UF, K, 16V	1	
C7207	F1H1C105A072	C 1UF, K, 16V	1	
C7209	F1H1C105A072	C 1UF, K, 16V	1	
C7210	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7211	F1K2A474A006	C 0.47UF, 6.3V	1	
C7214	F1H1C105A072	C 1UF, K, 16V	1	
C7216	F1H1C105A072	C 1UF, K, 16V	1	
C7217	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7218	F1K2A474A006	C 0.47UF, 6.3V	1	
C7219	F1H1C105A072	C 1UF, K, 16V	1	
C7220	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7221	F1K2A474A006	C 0.47UF, 6.3V	1	
C7229	ECJ1XB1C104K	C 0.1UF, Z, 16V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C7230-33	F1K2A474A006	C 0.47UF, 6.3V	4	
C7235	F1H1C105A072	C 1UF, K, 16V	1	
C7236	ECJ1XC1H101J	C 100PF, J, 50V	1	
C7237	F1K2A474A006	C 0.47UF, 6.3V	1	
C7240	F1H1C105A072	C 1UF, K, 16V	1	
C7242	F1K2A474A006	C 0.47UF, 6.3V	1	
C7244,45	ECJ1XB1C104K	C 0.1UF, Z, 16V	2	
C8001	F1G1C104A081	C 0.10UF, K, 16V	1	
C8002-05	F1H0J1050012	C 1UF, K, 16V	4	
C8006-08	F1G1C104A081	C 0.10UF, K, 16V	3	
C8009,10	F1J1A106A043	C 0.010UF, K, 16V	2	
C8011-14	F1G1C104A081	C 0.10UF, K, 16V	4	
C8015,16	F1H0J1050012	C 1UF, K, 16V	2	
C8017	F1J1A106A043	C 0.010UF, K, 16V	1	
C8018-21	F1G1C104A081	C 0.10UF, K, 16V	4	
C8022	F1H0J1050012	C 1UF, K, 16V	1	
C8023,24	F1J1A106A043	C 0.010UF, K, 16V	2	
C8025-29	F1G1C104A081	C 0.10UF, K, 16V	5	
C8030,31	F1H0J1050012	C 1UF, K, 16V	2	
C8032	F1J1A106A043	C 0.010UF, K, 16V	1	
C8033,34	F1G1C104A081	C 0.10UF, K, 16V	2	
C8035,36	F1J1A106A043	C 0.010UF, K, 16V	2	
C8037-41	F1G1C104A081	C 0.10UF, K, 16V	5	
C8042	ECGRLOG680ER	C 68PF, J, 4V	1	
C8043-51	F1G1C104A081	C 0.10UF, K, 16V	9	
C8052	F1H0J1050012	C 1UF, K, 16V	1	
C8053	F1G1E1030005	C 0.01UF, Z, 25V	1	
C8056,57	F1G1C104A081	C 0.10UF, K, 16V	2	
C8058	F1J1A106A043	C 0.010UF, K, 16V	1	
C8067	F1G1E1030005	C 0.01UF, Z, 25V	1	
C8068	F1G1C104A081	C 0.10UF, K, 16V	1	
C8069	F1G1H820A565	E 82UF, 50V	1	
C8070-74	F1G1C104A081	C 0.10UF, K, 16V	5	
C8075	F1J0G2260001	C 0.001UF, 6.3V	1	PAVCCZ
C8076-80	F1G1C104A081	C 0.10UF, K, 16V	5	
C8301	F1G1E1030005	C 0.01UF, Z, 25V	1	TH-42PX70B/E
C8304	F1G1C104A081	C 0.10UF, K, 16V	1	TH-42PX70B/E
C8306	F1G1H1020008	E 1000UF, 50V	1	TH-42PX70B/E
C8307	F1G1C104A081	C 0.10UF, K, 16V	1	TH-42PX70B/E
C8309	F1G1C104A081	C 0.10UF, K, 16V	1	TH-42PX70B/E
C8310	EEHBOG101R	C 100PF, J, 4V	1	TH-42PX70B/E
C8311,12	F1G1H100A565	C 100PF, K, 50V	2	TH-42PX70B/E
C8313,14	F1G1E1030005	C 0.01UF, Z, 25V	2	TH-42PX70B/E
C8316	F2G0J470A019	E 47UF 6.3V	1	TH-42PX70B/E
C8319-21	F1G1E1030005	C 0.01UF, Z, 25V	3	TH-42PX70B/E
C8322	F1G1C104A081	C 0.10UF, K, 16V	1	TH-42PX70B/E
C8323,24	F1G1H220A565	E 22UF, 50V	2	TH-42PX70B/E
C8325	F1G1E1030005	C 0.01UF, Z, 25V	1	TH-42PX70B/E
C8327,28	ECJ1VB1A105K	C 0.01UF, Z, 50V	2	TH-42PX70B/E
C8329-36	F1G1E1030005	C 0.01UF, Z, 25V	8	TH-42PX70B/E
C8338,39	F1G1H220A565	E 22UF, 50V	2	TH-42PX70B/E
C8340	F1G1E1030005	C 0.01UF, Z, 25V	1	TH-42PX70B/E
C8402-10	F1G1C104A081	C 0.10UF, K, 16V	9	TH-42PX70B/E
C8411	F2G1A101A019	E 100UF, 10V	1	TH-42PX70B/E
C8412-14	F1G1C104A081	C 0.10UF, K, 16V	3	TH-42PX70B/E
C8416,17	F1G1E1030005	C 0.01UF, Z, 25V	2	TH-42PX70B/E
C8551,52	F1G1C104A081	C 0.10UF, K, 16V	2	
C8555	F1G1C104A081	C 0.10UF, K, 16V	1	
C8601	F1G1C104A081	C 0.10UF, K, 16V	1	
C8621,22	F1G1C104A081	C 0.10UF, K, 16V	2	
C8731	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9028,29	F1J1A106A043	C 0.010UF, K, 16V	2	
C9033,34	F1G1C104A083	C 0.10UF, K, 16V	2	
C9035,36	F1J1A106A043	C 0.010UF, K, 16V	2	
C9037	F1G1E1030005	C 0.01UF, Z, 25V	1	
C9039	F1J1A106A043	C 0.010UF, K, 16V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C9040	FI1G1C104A083	C 0.10UF, K, 16V	1	
C9044	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9045-53	FI1G1C104A083	C 0.10UF, K, 16V	9	
C9055-57	FI1G1C104A083	C 0.10UF, K, 16V	3	
C9058	FI1J1A106A043	C 0.010UF, K, 16V	1	
C9061	FI1G1C104A077	C 0.10UF, K, 16V	1	
C9062	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9063	FI1G1C104A083	C 0.10UF, K, 16V	1	
C9468	FI1G1E1030005	C 0.01UF, Z, 25V	1	
C9469	FI1G1C104A083	C 0.10UF, K, 16V	1	
C9500	FI1G1C104A077	C 0.10UF, K, 16V	1	
C9505	FI1G1C104A077	C 0.10UF, K, 16V	1	
C9508	FI1G1C104A077	C 0.10UF, K, 16V	1	
C9509,10	FI1G1H120A565	E 12UF, 50V	2	
C9511	FI1J1A106A043	C 0.010UF, K, 16V	1	
C9516-25	FI1G1C104A077	C 0.10UF, K, 16V	10	
C9526	FI1J1A106A043	C 0.010UF, K, 16V	1	
C9527,28	FI1G1C104A077	C 0.10UF, K, 16V	2	
C9531	FI1J1A106A043	C 0.010UF, K, 16V	1	
C9559-64	FI1G1C104A077	C 0.10UF, K, 16V	6	
C9823	ECJ3YB1E106M	C 10 UF, K, 25V	1	
C9825	FI1G1H101A565	C 100PF, K, 50V	1	
C9832	FI1J1A106A043	C 0.010UF, K, 16V	1	
C9837	FI1J1A106A043	C 0.010UF, K, 16V	1	
C9838	FI1G1C104A083	C 0.10UF, K, 16V	1	
C9840	FI1G1E1030005	C 0.01UF, Z, 25V	1	
C9841-43	FI1G1C104A083	C 0.10UF, K, 16V	3	
C9844	FI1G1E1030005	C 0.01UF, Z, 25V	1	
C9845,46	FI1G1C104A083	C 0.10UF, K, 16V	2	
C9858	ECJ3YB1E106M	C 10 UF, K, 25V	1	
C9859	FI1G1E1030005	C 0.01UF, Z, 25V	1	
C9860	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9861,62	ECJ1VB1E104K	C 0.10UF, K, 25V	2	
C9863	ECJ2YB0J475K	C 3.3UF, Z, 4.7V	1	
C9864	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C9865,66	ECGR10G680ER	C 68PF, J, 4V	2	
C9867-72	ECJ3YB1E106M	C 10 UF, K, 25V	6	
C9873	ECGR10G680ER	C 68PF, J, 4V	1	
C9874	FI1G1H680A565	E 68UF, 50V	1	
C9877	FI1G1H680A565	E 68UF, 50V	1	
C9878	FI1G1E1030005	C 0.01UF, Z, 25V	1	
C9879,80	FI1G1E822A086	C 8200UF, Z, 25V	2	
C9881	FI1G1E1030005	C 0.01UF, Z, 25V	1	
C9882	FI1G1E822A086	C 8200UF, Z, 25V	1	
C9883	FI1G1H101A565	C 100PF, K, 50V	1	
C9884,85	FI1G1H1020008	E 1000UF, 50V	2	
C9886,87	ECJ1VB1E104K	C 0.10UF, K, 25V	2	
C9888	FI1G1H361A565	E 360UF, 50V	1	
C9900-25	FI1G1C104A077	C 0.10UF, K, 16V	26	
C9927-51	FI1G1C104A077	C 0.10UF, K, 16V	25	
C9955-59	FI1G1C104A077	C 0.10UF, K, 16V	5	
C9960-64	FI1J1A106A043	C 0.010UF, K, 16V	5	
C9966,67	FI1G1C104A077	C 0.10UF, K, 16V	2	
CB1-B8	K1MN68BA0052	68P CONNECTOR	8	
D5	K1KB31BA0064	31P CONNECTOR	1	
D6	K1KA21A00011	21P CONNECTOR	1	
D9	K1KA07A00292	7P CONNECTOR	1	
D20	K1KY30BA0090	30P CONNECTOR	1	
D25	K1KA13B00069	13P CONNECTOR	1	
D31,32	K1MN55BA0257	55P CONNECTOR	2	
D1100	MA704A	DIODE	1	
D1102	MA704A	DIODE	1	
D1107	MA704A	DIODE	1	
D2026	MA2J11100L	DIODE	1	
D2028,29	MA2J11100L	DIODE	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D2031-34	MA2J11100L	DIODE	4	
D2119	B0BC01100001	ZENER DIODE	1	
D2301,02	MA2J11100L	DIODE	2	
D2303	MA3056H	ZENER DIODE	1	
D2304	MA2J11100L	DIODE	1	
D2512	MA8043LTX	ZENER DIODE	1	
D2520	LNJ107W5PRW	LED	1	
D2524	MAZ80560ML	ZENER DIODE	1	
D2525B	LN1471YTR	LED	1	TH-42PX70B/E
D2526	MAZ80560ML	ZENER DIODE	1	TH-42PX70B/E
D2632,33	MA2J11100L	DIODE	2	
D2634	MA3X78900L	ZENER DIODE	1	
D2635	MA2J11100L	DIODE	1	
D2636	MA3047H	ZENER DIODE	1	
D2637	MA2J11100L	DIODE	1	
D2638	B0BC03900015	ZENER DIODE	1	
D3003-06	MA8140M	ZENER DIODE	4	
D3008-12	MA8140M	ZENER DIODE	5	
D3013,14	MAZ80560ML	ZENER DIODE	2	
D3025	MA8140M	ZENER DIODE	1	
D3027,28	MA8140M	ZENER DIODE	2	
D3030-32	MA8140M	ZENER DIODE	3	
D3038,39	MA8140M	ZENER DIODE	2	
D3044	B0BC01100001	ZENER DIODE	1	
D3100	MA8140M	ZENER DIODE	1	
D3102	MA2J11100L	DIODE	1	
D3334-38	MA2J11100L	DIODE	5	
D4500-12	EZAEG2A50AX	DIODE	13	
D4513	MA3056MTX	ZENER DIODE	1	
D4514	EZAEG2A50AX	DIODE	1	
D4515	MA3056MTX	ZENER DIODE	1	
D4516-23	EZAEG2A50AX	DIODE	8	
D4524-27	BOHCMM000014	DIODE	4	
D4528	EZAEG2A50AX	DIODE	1	
D4532	BOHCMM000014	DIODE	1	
D5517	MTZJ10B	ZENER DIODE	1	
D5518	MTZJT-7712B	ZENER DIODE	1	PAVCCZ
D5519	MTZJT-776.8B	ZENER DIODE	1	PAVCCZ
D5521	MA2J11100L	DIODE	1	
D5522	MA3X152A0L	DIODE	1	
D5526	MA3X152A0L	DIODE	1	
D5528	MA8120M	ZENER DIODE	1	
D5529	MAZ80680LL	ZENER DIODE	1	
D5530	MA2J11100L	DIODE	1	
D5601,02	MA22D3900L	DIODE	2	
D5603,04	B0JCDD000002	DIODE	2	
D5605	MA22D3900L	DIODE	1	
D5606	B0JCDD000002	DIODE	1	
D5607,08	MA8024LTX	ZENER DIODE	2	
D5609	MA8056LTX	ZENER DIODE	1	
D5670	MA2J11100L	DIODE	1	
D5671	BOHCMM000014	DIODE	1	
D5673	BOHCMM000014	DIODE	1	
D5690,91	B0BC6R600005	ZENER DIODE	2	
D6001	BOHBSN000008	DIODE	1	
D6021	MA3DF30000LZ	ZENER DIODE	1	
D6024,25	BOEHP000003	DIODE	2	
D6032	MA2J11100L	DIODE	1	
D6061,62	MA3DF30000LZ	ZENER DIODE	2	
D6071,72	BOHBSN000008	DIODE	2	
D6082	MA3DF30000LZ	ZENER DIODE	1	
D6091	BOHBSN000008	DIODE	1	
D6092	BOEHP000003	DIODE	1	
D6101	B0JCME000037	DIODE	1	
D6104	B0JCME000037	DIODE	1	
D6131,32	BOEHP000003	DIODE	2	
D6151-53	BOEHP000003	DIODE	3	
D6191	BOEHP000003	DIODE	1	
D6193	BOEHP000003	DIODE	1	
D6211	B0JCME000037	DIODE	1	
D6221	BOEHP000003	DIODE	1	
D6222,23	MA2J11100L	DIODE	2	
D6253	LNJ301MPUJA	LED	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D6254	MAZ80510LL	ZENER DIODE	1	
D6255	MA2J11100L	DIODE	1	
D6273	MA2J11100L	DIODE	1	
D6275	MA8068M	ZENER DIODE	1	
D6276	MA3X152A0L	DIODE	1	
D6278	MA3X152A0L	DIODE	1	
D6280	MAZ80510LL	ZENER DIODE	1	
D6281	B0JCME000037	DIODE	1	
D6401,02	B0HBSN000008	DIODE	2	
D6422	MA3DF40000LZ	ZENER DIODE	1	
D6441	B0ECHP000003	DIODE	1	
D6451	B0ECHP000003	DIODE	1	
D6461,62	MA3DF30000LZ	ZENER DIODE	2	
D6466	MA2J11100L	DIODE	1	
D6471	B0HBSN000008	DIODE	1	
D6472	B0ECHP000003	DIODE	1	
D6477	MA2J11100L	DIODE	1	
D6478	B0HCKS000002	DIODE	1	
D6480	MA2J11100L	DIODE	1	
D6481	MA3DF30000LZ	ZENER DIODE	1	
D6491	MA3DF40000LZ	ZENER DIODE	1	
D6497	B0ECHP000003	DIODE	1	
D6501	B0ECHP000003	DIODE	1	
D6503	B0ECHP000003	DIODE	1	
D6521-23	B0ECHP000003	DIODE	3	
D6583	LNJ301MPUJA	LED	1	
D6584	MAZ80510LL	ZENER DIODE	1	
D6585	MA2J11100L	DIODE	1	
D6604	MA2J11100L	DIODE	1	
D6605	MAZ80510LL	ZENER DIODE	1	
D6606	B0HCMM000014	DIODE	1	
D6607	MA2J11100L	DIODE	1	
D6619	B0HCKS000002	DIODE	1	
D6621	B0HDSM000005	DIODE	1	
D6623,24	B0HDSM000005	DIODE	2	
D6631,32	MA8240MTX	ZENER DIODE	2	
D6641,42	B0HCKS000002	DIODE	2	
D6643	B0JCME000037	DIODE	1	
D6644	B0HCKS000002	DIODE	1	
D6661	MA2J11100L	DIODE	1	
D6662-64	MA8330M	ZENER DIODE	3	
D6665	MAZ80510LL	ZENER DIODE	1	
D6666,67	MA2J11100L	DIODE	2	
D6670,71	B0JCME000037	DIODE	2	
D6690	MA2J11100L	DIODE	1	
D6691,92	MA8200M	ZENER DIODE	2	
D6701	MA8056H	ZENER DIODE	1	
D6702,03	MA2J11100L	DIODE	2	
D6721	B0HCKS000002	DIODE	1	
D6722	MA2J11100L	DIODE	1	
D6725	B0ECHP000003	DIODE	1	
D6726-33	MA8056H	ZENER DIODE	8	
D6761	B0JCME000037	DIODE	1	
D6763	B0ECHP000003	DIODE	1	
D6764	B0HCKS000002	DIODE	1	
D6765,66	B0ECHP000003	DIODE	2	
D6773	B0HCKS000002	DIODE	1	
D6791	MA8200M	ZENER DIODE	1	
D6802	B0BC01000044	ZENER DIODE	1	
D6804	B0ECHP000003	DIODE	1	
D6805	MA8240MTX	ZENER DIODE	1	
D6806	B0HCKS000002	DIODE	1	
D6809	B0HCMM000014	DIODE	1	
D6820-23	MA2J11100L	DIODE	4	
D6824,25	MA8330M	ZENER DIODE	2	
D6826	MA2J11100L	DIODE	1	
D6827,28	MA8330M	ZENER DIODE	2	
D6830	MA8056H	ZENER DIODE	1	
D6836	MAZ81500ML	ZENER DIODE	1	
D6837	MA2J11100L	DIODE	1	
D6838	B0BC027A0234	ZENER DIODE	1	
D6839	B0ECHP000003	DIODE	1	
D6841	B0HCKS000002	DIODE	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D6842,43	MA2J11100L	DIODE	2	
D6859	B0ECHP000003	DIODE	1	
D6860	B0HCKS000002	DIODE	1	
D6861	MAZ80510LL	ZENER DIODE	1	
D6862	MA2J11100L	DIODE	1	
D6871	MAZ80510LL	ZENER DIODE	1	
D6872	MA2J11100L	DIODE	1	
D6901,02	MA8056H	ZENER DIODE	2	
D6903-05	B0HCMM000013	DIODE	3	
D6951,52	MA8056H	ZENER DIODE	2	
D6953-55	B0HCMM000013	DIODE	3	
D7103-10	B0HCMM000014	DIODE	8	
D7201-08	B0HCMM000014	DIODE	8	
D9017-19	MA3033	ZENER DIODE	3	
D9020	B0JCCE000008	DIODE	1	
D9110	B0JCGD000002	DIODE	1	
D9802	B0JCCE000008	DIODE	1	
D9804	B0JCCE000008	DIODE	1	
D9807,08	B0JCCE000008	DIODE	2	
D9811	B0JCCE000008	DIODE	1	
D9812	MA22D3900L	DIODE	1	
D9813-15	B0JCGD000002	DIODE	3	
D9816,17	MA22D3900L	DIODE	2	
DG1	K1KA12B00151	12P CONNECTOR	1	PAVCCZ
DG2	K1KB23A00003	23P CONNECTOR	1	
DG5	K1KB31AA0140	31P CONNECTOR	1	
DG6	K1KB80AA0218	80P CONNECTOR	1	PAVCCZ
DG32	K1KA07AA0266	7P CONNECTOR	1	
DG33	K1KA11AA0153	11P CONNECTOR	1	
DG34	K1KA30AA0009	30P CONNECTOR	1	
FL2001,02	J0HABB000004	LC FILTER	2	
FL3001,02	J0HABB000003	LC FILTER	2	
FL3003-05	J0HABB000004	LC FILTER	3	
FL4800-02	J0JAD0000028	CHIP INDUCTOR	3	
FL5730	J0HABH000013	LC FILTER	1	
FL5732-34	J0HABH000013	LC FILTER	3	
FL7101	J0HABH000013	LC FILTER	1	
FL7201	J0HABH000013	LC FILTER	1	
FL9300,01	F1J1E104A148	C 0.10UF, Z, 25V	2	
FL9504	F1J1E104A148	C 0.10UF, Z, 25V	1	
FL9803	F1J1E104A148	C 0.10UF, Z, 25V	1	
FL9805,06	F1J1E104A148	C 0.10UF, Z, 25V	2	
FL9900-04	F1J1E104A148	C 0.10UF, Z, 25V	5	
GK1,K2	K1KY12B00001	12P CONNECTOR	2	
H2	K1KA23A00003	23P CONNECTOR	1	
H3,H4	K1KA23A00005	23P CONNECTOR	2	
H6	K1KB80AA0218	80P CONNECTOR	1	PAVCCZ
H12	K1KA04AA0190	4P CONNECTOR	1	
H15	K1KA04AA0150	4P CONNECTOR	1	
IC1100	MNZSFD7GP42	IC	1	
IC1101	TVRP464	IC	1	PAVCCZ
IC2002	C0FBBY000027	IC	1	TH-42PX70B/E
IC2006	C0JBAZ002261	IC	1	TH-42PX70B/E
IC2008	C0CBCBE00001	IC	1	
IC2010	C0CBCBC00190	IC	1	
IC2011	C0ABBB000230	IC	1	
IC2106	C1AB00002746	IC	1	PAVCCZ
IC2107	C0DBFFD00003	IC	1	
IC2301	C1AB00002730	IC	1	
IC2303	C0DBGYY00202	IC	1	
IC2601	C0JBAU000034	IC	1	
IC2610	C0DBAJB00004	IC	1	
IC3001	AN15876A-VT	IC	1	
IC3101	AN15862A-VT	IC	1	
IC4500	TVRP317	IC	1	PAVCCZ
IC4501	TVRP316	IC	1	PAVCCZ
IC4504	C3EBEY000009	IC	1	
IC4506	C0DBGGF00001	IC	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
IC4507	C0CBCBC00190	IC	1	
IC4508,09	C0CBCAD00082	IC	2	
IC4510	C1AB00002753	IC	1	
IC4515	NJM2903V	IC	1	
IC4800	C1ZBZ0003577	IC	1	
IC5550	EHMDD9851	LINEAR IC	1	
IC5600	C0DBAYY00273	IC	1	
IC5601	C0DBAYY00274	IC	1	
IC5660	C0EBM0000026	IC	1	
IC5670	C0CBCBC00190	IC	1	
IC5671	C0EBF0000376	IC	1	
IC6131	C0ZBZ0000895	IC	1	
IC6151	C0ZBZ0001324	IC	1	
IC6191	C0ZBZ0000895	IC	1	
IC6211	C0ZBZ0001325	IC	1	
IC6221	C0DBEMC00043	IC	1	
IC6241	C0JBAZ000005	IC	1	
IC6251	NJM2903M	INTEGRATED CIRCUIT	1	
IC6471	C0DBEKA00003	IC	1	
IC6472	C0JBAA000377	IC	1	
IC6501	C0ZBZ0000895	IC	1	
IC6521	C0ZBZ0001324	IC	1	
IC6561,62	C0JBAZ000005	IC	2	
IC6581	NJM2903M	INTEGRATED CIRCUIT	1	
IC6671	C0ZBZ0001325	IC	1	
IC6721,22	C0JBAZ000994	IC	2	
IC6724,25	C0CBADC00072	IC	2	
IC6752	C0ZBZ0001324	IC	1	
IC6771	C0CBADC00072	IC	1	
IC6772	C0ZBZ0001325	IC	1	
IC6773,74	C0JBAA000377	IC	2	
IC6791	NOBF1FB00001	IC	1	
IC6801,02	C0DBEMC00043	IC	2	
IC6803	C5HABZZ00165	IC	1	
IC6821	C0DBEMC00043	IC	1	
IC6841	C0DBEMC00043	IC	1	
IC6861	NJM2903M	INTEGRATED CIRCUIT	1	
IC6871	NJM2903M	INTEGRATED CIRCUIT	1	
IC6901-06	AN16077A-VT	IC	6	PAVCCZ
IC6951-56	AN16077A-VT	IC	6	PAVCCZ
IC7101,02	C0JBAZ001120	IC	2	
IC7201,02	C0JBAZ001120	IC	2	
IC7204	C0JBAZ001120	IC	1	
IC8001	MN2WS0039A	IC	1	PAVCCZ
IC8002,03	C3ABRG000080	IC	2	
IC8004	C0ZBZ0001030	IC	1	
IC8301	C1AB00002710	IC	1	PAVCCZ TH-42PX70B/E
IC8302	C0CBCAD00082	IC	1	TH-42PX70B/E
IC8401	C0JBAZ002800	IC	1	TH-42PX70B/E
IC8402	C0JBAZ001120	IC	1	TH-42PX70B/E
IC8403	C0ZBZ0001333	IC	1	TH-42PX70B/E
IC8404-07	C0JBAZ001120	IC	4	TH-42PX70B/E
IC8408,09	C0JBAU000025	IC	2	PAVCCZ TH-42PX70B/E
IC8554	TVRP280	IC	1	PAVCCZ
IC8601	TVRP301	IC	1	PAVCCZ TH-42PX70E
IC8601	TVRP299	IC	1	PAVCCZ TH-42PX70B
IC8601	TVRP300	IC	1	PAVCCZ TH-42PV70F
IC8601	TVRP473	IC	1	PAVCCZ TH-42PV70P
IC8621,22	C0JBAZ002845	IC	2	PAVCCZ
IC9001	TVRP207-1	IC	1	PAVCCZ
IC9002	C1ZBZ0003577	IC	1	
IC9003	MNZSFC9GPH2	IC	1	PAVCCZ
IC9007	TVRP210-1	IC	1	PAVCCZ
IC9011	C0EBF0000431	IC	1	
IC9013	C0JBAZ002060	IC	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
IC9200	C1ZBZ0003600	IC	1	
IC9303	TVRP215-1	IC	1	PAVCCZ
IC9500	C1ZBZ0003575	IC	1	
IC9802,03	C0JBAZ001120	IC	2	
IC9805	C0DBAYY00274	IC	1	
IC9806	C0DBAYY00273	IC	1	
IC9900	MN84524	IC	1	
IC9901	C3ABQJ000055	IC	1	
JA2	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
JA4-A8	ERJ6GEY0R00V	M 0 OHM, 1/10W	5	
JK2002	K2HA204A0041	JACK	1	
JK3001	K1FB315A0006	CONNECTOR	1	
JK3002,03	K1FB121A0010	CONNECTOR	2	PAVCCZ
JK3005	K2HA511A0002	JACK	1	PAVCCZ
JK4500,01	K1FY119D0002	CONNECTOR	2	
JK8401	K1NA68B00044	68P CONNECTOR	1	PAVCCZ TH-42PX70B/E
JK8801	K1NA09D00004	9P CONNECTOR	1	
JS1100	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-42PV70F/P TH-42PX70E
JS1101	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-42PX70B
JS1106	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-42PX70E
JS1115	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-42PV70P
JS1116	D0YAR0000007	M 0.0 OHM, J,0.063W	1	TH-42PV70F
JS1106	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
JS2031-33	J0JCC0000100	CHIP INDUCTOR	3	
JS2046	J0JCC0000100	CHIP INDUCTOR	1	
JS2048,49	J0JCC0000100	CHIP INDUCTOR	2	
JS2051	J0JCC0000100	CHIP INDUCTOR	1	
JS2059-62	J0JCC0000100	CHIP INDUCTOR	4	
JS2064	J0JCC0000100	CHIP INDUCTOR	1	
JS2096	J0JCC0000100	CHIP INDUCTOR	1	
JS2515	J0JCC0000100	CHIP INDUCTOR	1	TH-42PV70F/P
JS2516	J0JCC0000100	CHIP INDUCTOR	1	TH-42PX70B/E
JS3002	J0JCC0000100	CHIP INDUCTOR	1	TH-42PX70B/E
JS3005	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
JS3007-16	ERJ6GEY0R00V	M 0 OHM, 1/10W	10	
JS3018-20	ERJ6GEY0R00V	M 0 OHM, 1/10W	3	
JS3023	J0JCC0000100	CHIP INDUCTOR	1	
JS3032	J0JCC0000100	CHIP INDUCTOR	1	
JS3040-43	ERJ6GEY0R00V	M 0 OHM, 1/10W	4	
JS3053	J0JCC0000100	CHIP INDUCTOR	1	TH-42PV70F/P
JS3206	J0JCC0000100	CHIP INDUCTOR	1	
JS3208	J0JCC0000100	CHIP INDUCTOR	1	
JS3213	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
JS4501	D0YAR0000007	M 0.0 OHM, J,0.063W	1	
K1	K1KY12B00001	12P CONNECTOR	1	
L1100	J0JHC0000078	CHIP INDUCTOR	1	
L2001,02	J0JCC0000364	CHIP INDUCTOR	2	
L2003-10	J0JCC0000100	BEAD CHOKE	8	
L2015,16	J0JCC0000100	BEAD CHOKE	2	
L2021	J0JHC0000078	CHIP INDUCTOR	1	
L2022	J0JHC0000078	CHIP INDUCTOR	1	TH-42PX70B/E
L2022	J0JCC0000100	CHIP INDUCTOR	1	TH-42PV70F/P
L2026	G1C6R8MA0061	INDUCTOR COIL	1	
L2027	J0JHC0000045	CHIP INDUCTOR	1	
L2029	J0JCC0000077	CHIP INDUCTOR	1	
L2039,40	J0JHC0000045	CHIP INDUCTOR	2	
L2300	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2302	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2304	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2306	G1C100MA0291	INDUCTION COIL	1	PAVCCZ
L2308	J0JJC0000011	CHIP INDUCTOR	1	
L2310	J0JJC0000011	CHIP INDUCTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
L2647	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
L2648	G1C470MA0077	INDUCTION COIL	1	
L2649	G1C100MA0072	INDUCTION COIL	1	
L2650	G1C3R3ZA0083	INDUCTION COIL	1	
L3001,02	J0JCC0000100	BEAD CHOKE	2	
L3004	G1C101M00018	INDUCTION COIL	1	
L3206-08	J0JCC0000241	CHIP INDUCTOR	3	
L3209	J0JGC0000021	CHIP INDUCTOR COIL	1	
L3210	J0JCC0000241	CHIP INDUCTOR	1	
L3211	J0JGC0000021	CHIP INDUCTOR COIL	1	
L4500-07	J0JHC0000078	CHIP INDUCTOR	8	
L4511	J0JHC0000078	CHIP INDUCTOR	1	
L4512	J0JCC0000077	CHIP INDUCTOR	1	
L4516-18	J0JHC0000078	CHIP INDUCTOR	3	
L4520,21	J0JHC0000078	CHIP INDUCTOR	2	
L4524	J0JHC0000078	CHIP INDUCTOR	1	
L5550	TALL08N2R7MA	INDUCTION COIL	1	
L5551,52	G0C150MA0056	PEAKING COIL	2	
L5564	TALL08N2R7MA	INDUCTION COIL	1	
L5565	G0A220GA0002	CHOKE COIL	1	
L5566	TALL08N2R7MA	INDUCTION COIL	1	
L5600,01	G1C2R2ZA0083	INDUCTION COIL	2	
L5602	G1C3R3ZA0083	INDUCTION COIL	1	
L5604	G1C100MA0077	INDUCTION COIL	1	
L5605	J0JCC0000241	CHIP INDUCTOR	1	
L5606	G1C100MA0077	INDUCTION COIL	1	
L5610,11	J0JHC0000035	CHIP INDUCTOR	2	
L5670	J0JHC0000078	CHIP INDUCTOR	1	
L5690,91	J0JHC0000078	CHIP INDUCTOR	2	
L5692	J0JCC0000241	CHIP INDUCTOR	1	
L5735	J0JHC0000078	CHIP INDUCTOR	1	
L6000	J0JJC0000015	CHIP INDUCTOR	1	
L6001-03	ELC13P1R9	CHOKE COIL	3	
L6010	J0JJC0000015	CHIP INDUCTOR	1	
L6011-13	ELC13P1R9	CHOKE COIL	3	
L6045-48	G0ZZ00002183	PEAKING COIL	4	
L6057,58	G0ZZ00002183	PEAKING COIL	2	
L6061-64	G0ZZ00002183	PEAKING COIL	4	
L6083,84	G0ZZ00002183	PEAKING COIL	2	
L6101	J0JJC0000015	CHIP INDUCTOR	1	
L6103	G0ZZ00002183	PEAKING COIL	1	
L6106	J0JJC0000015	CHIP INDUCTOR	1	
L6212	J0JJC0000015	CHIP INDUCTOR	1	
L6221	G0ZZ00002183	PEAKING COIL	1	
L6241	G0ZZ00002183	PEAKING COIL	1	
L6262	G0ZZ00002183	PEAKING COIL	1	
L6271	G0ZZ00002183	PEAKING COIL	1	
L6401-03	ELC13P1R9	CHOKE COIL	3	
L6411-13	ELC13P1R9	CHOKE COIL	3	
L6461-68	G0ZZ00002183	PEAKING COIL	8	
L6472	G0ZZ00002183	PEAKING COIL	1	
L6474	G0ZZ00002183	PEAKING COIL	1	
L6481,82	G0ZZ00002183	PEAKING COIL	2	
L6485,86	G0ZZ00002183	PEAKING COIL	2	
L6591,92	G0ZZ00002183	PEAKING COIL	2	
L6601,02	G0ZZ00002183	PEAKING COIL	2	
L6690	G0ZZ00002183	PEAKING COIL	1	
L8001-05	J0JHC0000045	CHIP INDUCTOR	5	
L8006	J0JCC0000100	CHIP INDUCTOR	1	
L8007-10	J0JHC0000045	CHIP INDUCTOR	4	
L8301,02	J0JHC0000045	CHIP INDUCTOR	2	TH-42PX70B/E
L8304	J0JHC0000045	CHIP INDUCTOR	1	TH-42PX70B/E
L8551	J0JCC0000241	CHIP INDUCTOR	1	
L8621	J0JCC0000241	CHIP INDUCTOR	1	
L9500	G1C150KA0038	INDUCTION COIL	1	
L9501,02	J0JHC0000078	CHIP INDUCTOR	2	
L9504,05	J0JHC0000078	CHIP INDUCTOR	2	
L9800	G1C2R2Z00007	INDUCTION COIL	1	
L9801	G1C1R5Z00006	INDUCTION COIL	1	
L9802	G1C2R2Z00007	INDUCTION COIL	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
NP	TNPA4177AD	CIRCUIT BOARD H	1	PAVCCZ TH-42PX70B/E △
NP	TNPA4177AH	CIRCUIT BOARD H	1	PAVCCZ TH-42PV70F/P △
NP	TZTNP01HNTD	CIRCUIT BOARD DG	1	PAVCCZ TH-42PX70E △
NP	TXNDG1HNTB	CIRCUIT BOARD DG		PAVCCZ TH-42PX70B △
NP	TXNDG1KYTE	CIRCUIT BOARD DG	1	PAVCCZ TH-42PV70F △
NP	TZTNP01MFTE	CIRCUIT BOARD DG		PAVCCZ TH-42PV70P △
NP	TNPA4178AB	CIRCUIT BOARD PA	1	PAVCCZ △
NP	TNPA4165AB	CIRCUIT BOARD C1	1	PAVCCZ △
NP	TNPA4166AB	CIRCUIT BOARD C2	1	PAVCCZ △
NP	TZTNP01HNTB	CIRCUIT BOARD D	1	PAVCCZ △
NP	TNPA4221AE	CIRCUIT BOARD P	1	PAVCCZ △
NP	TNPA4182AB	CIRCUIT BOARD SC	1	PAVCCZ △
NP	TNPA4185AB	CIRCUIT BOARD SD	1	PAVCCZ △
NP	TNPA4183AB	CIRCUIT BOARD SS	1	PAVCCZ △
NP	TNPA4184AB	CIRCUIT BOARD SU	1	PAVCCZ △
NP	TNPA4283AB	CIRCUIT BOARD GK	1	PAVCCZ △
NP	TNPA4137AH	CIRCUIT BOARD K	1	PAVCCZ TH-42PX70B/E △
NP	TNPA4137AG	CIRCUIT BOARD K	1	PAVCCZ TH-42PV70F/P △
NP	TNPA4138AC	CIRCUIT BOARD S	1	PAVCCZ △
PA3,A4	K1KB23A00004	23P CONNECTOR	2	
PA5	K1KA23A00005	23P CONNECTOR	1	
PA9800	K5H4022A0023	FUSE	1	
PA9900	K5H5022A0023	FUSE	1	
PAMM3	TMME047	CLAMPER	1	
PAMM7	TMME047	CLAMPER	1	
PAMM11,12	TMME300	CLAMPER	2	
PC6480	B3PBA0000223	IC	1	
PC6701,02	B3PBA0000457	IC	2	
PC6704	B3PBA0000456	IC	1	
PC6705	B3PBA0000397	IC	1	
PC6801	B3PBA0000223	IC	1	
PC6861	B3PBA0000223	IC	1	
PC6871	B3PBA0000223	IC	1	
Q1107,08	2SD0601ARL	TRANSISTOR	2	
Q2000,01	2SD0601ARL	TRANSISTOR	2	
Q2002-07	2SC584500L	TRANSISTOR	6	
Q2015	2SA207700L	TRANSISTOR	1	
Q2016,17	2SC584500L	TRANSISTOR	2	
Q2021	2SA207700L	TRANSISTOR	1	
Q2031	2SA207700L	TRANSISTOR	1	
Q2033	2SA207700L	TRANSISTOR	1	
Q2034,35	2SC584500L	TRANSISTOR	2	
Q2039-41	2SC584500L	TRANSISTOR	3	
Q2101,02	2SC584500L	TRANSISTOR	2	
Q2301	2SA207700L	TRANSISTOR	1	
Q2510,11	2SD0601ARL	TRANSISTOR	2	
Q2513	2SD0601ARL	TRANSISTOR	1	
Q2518	2SD0601ARL	TRANSISTOR	1	TH-42PX70B/E
Q2635	2SC584500L	TRANSISTOR	1	
Q2636,37	2SA207700L	TRANSISTOR	2	
Q2638	2SC584500L	TRANSISTOR	1	
Q2639	2SK3065T100	FET	1	
Q3027,28	2SA207700L	TRANSISTOR	2	
Q3031,32	2SC584500L	TRANSISTOR	2	
Q3200	2SA207700L	TRANSISTOR	1	
Q4500-05	2SD0601ARL	TRANSISTOR	6	
Q4514-17	2SB0709ARL	TRANSISTOR	4	
Q4519	2SB0709ARL	TRANSISTOR	1	
Q5501	2SD0601ARL	TRANSISTOR	1	
Q5521,22	2SA207700L	TRANSISTOR	2	
Q5523,24	2SD0601ARL	TRANSISTOR	2	
Q5561	B1DHDC000028	TRANSISTOR	1	
Q5562	2SD0601ARL	TRANSISTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
Q5600-02	B1MBEDA00015	TRANSISTOR	3	
Q5603,04	2SD0601ARL	TRANSISTOR	2	
Q5690,91	2SD0601ARL	TRANSISTOR	2	
Q5692,93	B1DHDC000028	TRANSISTOR	2	
Q6001-03	B1JADN000001	TRANSISTOR	3	
Q6021-23	B1JADN000001	TRANSISTOR	3	
Q6031	B1ADRD000001	TRANSISTOR	1	
Q6041,42	B1JADN000002	TRANSISTOR	2	
Q6052	B1JADN000002	TRANSISTOR	1	
Q6101	B1DFKM000002	TRANSISTOR	1	
Q6103	B1ABNF000006	TRANSISTOR	1	
Q6104	B1ADNF000006	TRANSISTOR	1	
Q6106	B1DFKM000002	TRANSISTOR	1	
Q6111	B1DFKM000001	TRANSISTOR	1	
Q6114	B1DFKM000001	TRANSISTOR	1	
Q6141	B1ABNF000006	TRANSISTOR	1	
Q6142	B1ADNF000006	TRANSISTOR	1	
Q6146	B1ABNF000006	TRANSISTOR	1	
Q6147	B1ADNF000006	TRANSISTOR	1	
Q6171	B1ABRD000003	TRANSISTOR	1	
Q6172	B1ADRD000001	TRANSISTOR	1	
Q6181	B1ABRD000003	TRANSISTOR	1	
Q6222	2SC1473AEA	TRANSISTOR	1	
Q6251	2SD0601ARL	TRANSISTOR	1	
Q6256	2SD1263A	TRANSISTOR	1	
Q6271	2SD0601ARL	TRANSISTOR	1	
Q6401-03	B1JADN000001	TRANSISTOR	3	
Q6421-23	B1JADP000002	TRANSISTOR	3	
Q6441,42	B1JADN000002	TRANSISTOR	2	
Q6451	B1JADP000002	TRANSISTOR	1	
Q6501	B1ABNF000006	TRANSISTOR	1	
Q6502	B1ADNF000006	TRANSISTOR	1	
Q6521	B1ABNF000006	TRANSISTOR	1	
Q6522	B1ADNF000006	TRANSISTOR	1	
Q6531	B1ABRD000003	TRANSISTOR	1	
Q6532	B1ADRD000001	TRANSISTOR	1	
Q6551	B1ABRD000003	TRANSISTOR	1	
Q6552	B1ADRD000001	TRANSISTOR	1	
Q6581	2SD0601ARL	TRANSISTOR	1	
Q6601	B1DFES000003	TRANSISTOR	1	
Q6602	2SD0601ARL	TRANSISTOR	1	
Q6603	2SB0709ARL	TRANSISTOR	1	
Q6621,22	2SK399500L	FET	2	
Q6642-44	2SK399500L	FET	3	
Q6646-48	2SK399500L	FET	3	
Q6661	B1DEET000002	TRANSISTOR	1	
Q6662	2SD0601ARL	TRANSISTOR	1	
Q6665	B1ABNF000006	TRANSISTOR	1	
Q6671,72	B1DFDR000001	TRANSISTOR	2	
Q6679	B1ABNF000006	TRANSISTOR	1	
Q6680	B1ADNF000006	TRANSISTOR	1	
Q6690	2SA19610Q0HW	TRANSISTOR	1	
Q6742,43	2SD0601ARL	TRANSISTOR	2	
Q6762	B1ADNF000006	TRANSISTOR	1	
Q6781	B1ABNF000006	TRANSISTOR	1	
Q6782	B1ADNF000006	TRANSISTOR	1	
Q6791	2SD0601ARL	TRANSISTOR	1	
Q6805	2SC3063	TRANSISTOR	1	
Q6806	2SC1473AEA	TRANSISTOR	1	
Q6821,22	2SD1263A	TRANSISTOR	2	
Q6824	2SD0601ARL	TRANSISTOR	1	
Q6841	2SD1263A	TRANSISTOR	1	
Q6842	2SC1473AEA	TRANSISTOR	1	
Q8401,02	2SD0601ARL	TRANSISTOR	2	TH-42PX70B/E
Q9010	2SD0601ARL	TRANSISTOR	1	
Q9044	2SD0601ARL	TRANSISTOR	1	
Q9046	2SD0601ARL	TRANSISTOR	1	
Q9050-54	2SD0601ARL	TRANSISTOR	5	
Q9301,02	2SD0601ARL	TRANSISTOR	2	
Q9805,06	2SD0601ARL	TRANSISTOR	2	
Q9807-09	B1MBEDA00015	TRANSISTOR	3	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R1104	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1110	ERJ2GEJ273	M 27KOHM,J,0.063W	1	
R1122	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1124,25	ERJ2GEJ220	M 22 OHM,J,0.063W	2	
R1126	ERJ2GEJ273	M 27KOHM,J,0.063W	1	
R1134	ERJ2GEJ101	M 100 OHM,J,0.063W	1	
R1140	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1144	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1146	ERJ2GEJ102X	M 1KOHM,J,0.063W	1	
R1147	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1153	ERJ2GEJ821	M 820 OHM,J,0.063W	1	
R1162	ERJ2GEJ101	M 100 OHM,J,0.063W	1	
R1163	ERJ2GEJ105	M 1MOHM,J,0.063W	1	
R1164	ERJ2GEJ103	M 10KOHM,J,0.063W	1	
R1165	ERJ2GEJ182	M 1.8KOHM,J,0.063W	1	
R1166	ERJ2GEJ104	M 100KOHM,J,0.063W	1	
R1169	ERJ2GED563X	M 56KOHM,J,0.063W	1	
R1170	ERJ2GEJ273	M 27KOHM,J,0.063W	1	
R1171	ERJ2GED563X	M 56KOHM,J,0.063W	1	
R1172	ERJ2GEJ273	M 27KOHM,J,0.063W	1	
R1174,75	ERJ2GEJ220	M 22 OHM,J,0.063W	2	
R1179	ERJ2GEJ101	M 100 OHM,J,0.063W	1	
R1181	ERJ2GEJ101	M 100 OHM,J,0.063W	1	
R1182	ERJ2GEJ273	M 27KOHM,J,0.063W	1	
R1183,84	ERJ2GEJ220	M 22 OHM,J,0.063W	2	
R1185,86	ERJ2GEJ101	M 100 OHM,J,0.063W	2	
R1194	ERJ2GED563X	M 56KOHM,J,0.063W	1	
R1195	ERJ2GEJ104	M 100KOHM,J,0.063W	1	
R1196	ERJ2GEJ333	M 33KOHM,J,0.063W	1	
R1199	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1200,01	ERJ2GEJ562	M 5.6KOHM,J,0.063W	2	
R1203	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1204	D0YAR0000007	M 0.0 OHM,J,0.063W	1	
R1205,06	ERJ2GEJ220	M 22 OHM,J,0.063W	2	
R1209	ERJ2GEJ473	M 47KOHM,J,0.063W	1	
R1216	ERJ2GEJ333	M 33KOHM,J,0.063W	1	
R1217	ERJ2GED563X	M 56KOHM,J,0.063W	1	
R1218-20	ERJ2GEJ103	M 10KOHM,J,0.063W	3	
R1221	ERJ3EKF7151	M 7.15KOHM,1/16W	1	
R1222-28	ERJ2GEJ473	M 47KOHM,J,0.063W	7	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R1229	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1231-34	ERJ2GEJ473	M 47KOHM, J, 0.063W	4	
R1235	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R1236,37	ERJ2GEJ473	M 47KOHM, J, 0.063W	2	
R1239	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1241	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R1243-47	ERJ2GEJ473	M 47KOHM, J, 0.063W	5	
R1255	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	
R2001	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R2006	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R2007	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2010-15	ERJ2GEJ473	M 47KOHM, J, 0.063W	6	
R2018	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2020	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2023	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2025	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R2027	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R2029-32	ERJ6GEYJ223	M 22KOHM, J, 1/10W	4	
R2035,36	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2037,38	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	
R2039,40	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2041,42	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	
R2047	ERJ3GEYJ331	M 330 OHM, J, 1/16W	1	
R2048	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2049	ERJ3GEYJ331	M 330 OHM, J, 1/16W	1	
R2050	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2051,52	ERJ6GEYJ184	M 180KOHM, J, 1/10W	2	
R2053,54	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2056,57	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R2058	ERJ3GEYJ301	M 300 OHM, J, 1/16W	1	
R2059	D0GB105JA057	M 1MOHM, J, 1/16W	1	
R2066,67	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	TH-42PX70B/E
R2070,71	J0JCC0000100	CHIP INDUCTOR	2	TH-42PX70B/E
R2072	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	TH-42PX70B/E
R2073	ERJ3GEYJ330	M 33 OHM, J, 1/16W	1	TH-42PX70B/E
R2074,75	ERJ3GEYJ223	M 22KOHM, J, 1/16W	2	TH-42PX70B/E
R2084	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R2085	ERJ3GEYJ561	M 560 OHM, J, 1/16W	1	
R2086	ERJ3GEYJ471	M 470 OHM, J, 1/16W	1	
R2088	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R2089	ERJ3GEYJ561	M 560 OHM, J, 1/16W	1	
R2092	ERJ3GEYJ471	M 470 OHM, J, 1/16W	1	
R2093	ERJ3GEYJ332	M 3.3KOHM, J, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R2094	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2096	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2097	ERJ3GEYJ332	M 3.3KOHM, J, 1/16W	1	
R2100	ERJ3EKF2002	M 20KOHM, 1/16W	1	
R2101,02	ERJ3GEYJ331	M 330 OHM, J, 1/16W	2	
R2104	ERJ3EKF2001	M 2KOHM, 1/16W	1	
R2110	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2111	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R2112	D0GB105JA057	M 1MOHM, J, 1/16W	1	
R2113	ERJ3EKF1203	M 120KOHM, 1/16W	1	
R2114	ERJ3EKF7502	M 75KOHM, 1/16W	1	
R2118	D0GB105JA057	M 1MOHM, J, 1/16W	1	
R2119	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2122	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2123	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2124	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2125	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	1	
R2127	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2128	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2129	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2131	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2132	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2133,34	ERJ3GEYJ221	M 220 OHM, J, 1/16W	2	TH-42PX70B/E
R2137,38	ERJ3GEYJ221	M 220 OHM, J, 1/16W	2	
R2144	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2145,46	ERJ3EKF2002	M 20KOHM, 1/16W	2	
R2149	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2150,51	ERJ3EKF2002	M 20KOHM, 1/16W	2	
R2152	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R2154	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R2156,57	ERJ3GEYJ331	M 330 OHM, J, 1/16W	2	
R2159	ERJ3GEYJ331	M 330 OHM, J, 1/16W	1	
R2164	ERJ3GEYJ221	M 220 OHM, J, 1/16W	1	
R2165	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2166	ERJ3EKF1602	M 16.0KOHM, 1/16W	1	
R2167	ERJ3GEYJ221	M 220 OHM, J, 1/16W	1	
R2168	ERJ3EKF1602	M 16.0KOHM, 1/16W	1	
R2169	ERJ3EKF2202	M 22KOHM, 1/16W	1	
R2170-73	ERJ3GEYJ221	M 220 OHM, J, 1/16W	4	
R2178	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R2179	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2180	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R2181	ERJ3EKF2202	M 22KOHM, 1/16W	1	
R2182,83	ERJ3EKF3602	M 36KOHM, 1/16W	2	
R2194	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R2195,96	ERJ3GEYJ104	M 100KOHM, J, 1/16W	2	
R2197	ERJ3EKF6802	M 68KOHM, 1/16W	1	
R2198	ERJ3EKF1583	M 158KOHM, 1/16W	1	PAVCCZ
R2205	ERJ3GEYJ203	M 20KOHM, J, 1/16W	1	
R2206	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2208-10	D0GB103JA057	M 10KOHM, J, 1/16W	3	
R2216	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2217	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2219	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2220	D0GB123JA057	M 12KOHM, J, 1/16W	1	
R2223-25	J0JCC0000100	CHIP INDUCTOR	3	
R2227-31	J0JCC0000100	CHIP INDUCTOR	5	
R2233	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R2234	ERJ3GEYJ330	M 33 OHM, J, 1/16W	1	TH-42PX70B/E
R2235	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2238	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R2244	D0GB102JA057	M 1KOHM, J, 1/16W	1	TH-42PX70B/E
R2252-54	ERJ3GEYJ330	M 33 OHM, J, 1/16W	3	TH-42PX70B/E

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R2257	J0JCC0000100	CHIP INDUCTOR	1	
R2263	J0JCC0000100	CHIP INDUCTOR	1	
R2265	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2266	ERJ3GEYJ561	M 560 OHM,J,1/16W	1	
R2271	EXB28V220J	RESISTOR ARRAY	1	
R2276	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2290,91	J0JCC0000100	CHIP INDUCTOR	2	
R2294-97	J0JCC0000100	CHIP INDUCTOR	4	
R2301,02	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	2	
R2303,04	J0JCC0000100	CHIP INDUCTOR	2	
R2305	ERJ3GEYJ471	M 470 OHM,J,1/16W	1	
R2306	ERJ3GEYJ683	M 68KOHM,J,1/16W	1	
R2308	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2311	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2313	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2315	ERJ8GEYJ3R3V	M 3.3 OHM,J,1/8W	1	
R2317	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2319	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2321	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2323	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2325	ERJ6GEYJ100V	M 10 OHM,J,1/10W	1	
R2330	D0GB102JA057	M 1KOHM,J,1/16W	1	
R2331	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2506,07	J0JHC0000096	CHIP INDUCTOR	2	
R2516	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	
R2517	ERJ6GEYJ470V	M 47 OHM,J,1/10W	1	
R2520	ERJ3GEYJ224	M 220KOHM,J,1/16W	1	
R2524	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	
R2525	ERJ3EKF5760	M 576 OHM, 1/16W	1	
R2530	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	
R2531	ERJ3GEYJ271	M 270 OHM,J,1/16W	1	
R2539	D0GB473JA057	M 47KOHM,J,1/16W	1	TH-42PX70B/E
R2540	ERJ3GEYJ223	M 22KOHM,J,1/16W	1	TH-42PX70B/E
R2542	D0GB473JA057	M 47KOHM,J,1/16W	1	
R2554	ERJ6RED750	M 75 OHM, 1/10W	1	TH-42PX70B/E
R2556,57	ERJ3GEYJ562	M 5.6KOHM,J,1/16W	2	
R2558	ERJ6GEYJ0R00V	M 0 OHM, 1/10W	1	
R2567	ERJ6GEYJ0R00V	M 0 OHM, 1/10W	1	TH-42PX70B/E
R2572	ERJ6GEYJ0R00V	M 0 OHM, 1/10W	1	TH-42PX70B/E
R2576,77	J0JCC0000241	CHIP INDUCTOR	2	
R2578	J0JCC0000100	CHIP INDUCTOR	1	
R2579	J0JCC0000241	CHIP INDUCTOR	1	TH-42PX70B/E
R2579	J0JCC0000100	CHIP INDUCTOR	1	TH-42PV70F/P
R2601-03	J0JCC0000100	CHIP INDUCTOR	3	
R2624,25	ERJ3GEYJ220	M 22 OHM,J,1/16W	2	
R2628,29	ERJ3GEYJ752	M 7.5KOHM,J,1/16W	2	
R2853	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2854	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2855	D0GB473JA057	M 47KOHM,J,1/16W	1	
R2856	J0JCC0000100	CHIP INDUCTOR	1	
R2857	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2858	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	
R2859	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2860	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2861	D0GB102JA057	M 1KOHM,J,1/16W	1	
R2863,64	D0GB102JA057	M 1KOHM,J,1/16W	2	
R2865	D0GB103JA057	M 10KOHM,J,1/16W	1	
R2866	ERJ3GEYJ222	M 2.2KOHM,J,1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R2867	ERJ6ENF8202	M 82KOHM, 1/10W	1	
R2868	ERJ6ENF1602	M 16KOHM, 1/10W	1	
R2869	ERJ3GEYJ472	M 4.7KOHM,J,1/16W	1	
R2890	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3001-06	ERJ6ENF1500	M 150 OHM, 1/10W	6	
R3008-11	ERJ6ENF1500	M 150 OHM, 1/10W	4	
R3013-15	ERJ6RED750	M 75 OHM, 1/10W	3	
R3018	ERJ6GEYG680	M 68 OHM,J,1/10W	1	
R3020,21	D1BD2152A028	M 21.5KOHM, 1/10W	2	PAVCCZ
R3023	ERJ6ENF1302	M 13KOHM, 1/10W	1	
R3027,28	ERJ6ENF1500	M 150 OHM, 1/10W	2	
R3031,32	J0JCC0000100	CHIP INDUCTOR	2	
R3033	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3036	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3044,45	J0JCC0000100	CHIP INDUCTOR	2	
R3059-61	ERJ3GEYJ221	M 220 OHM,J,1/16W	3	
R3064	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3087	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3088	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	TH-42PX70B/E
R3089	ERJ3GEYJ331	M 330 OHM,J,1/16W	1	
R3090	ERJ3GEYJ220	M 22 OHM,J,1/16W	1	
R3092	ERJ3GEYJ680	M 68 OHM,J,1/16W	1	
R3094,95	ERJ3GEYJ680	M 68 OHM,J,1/16W	2	
R3096-01	ERJ3GEYJ221	M 220 OHM,J,1/16W	6	
R3102	D0GB103JA057	M 10KOHM,J,1/16W	1	
R3103	J0JCC0000100	CHIP INDUCTOR	1	
R3104	D0GB103JA057	M 10KOHM,J,1/16W	1	
R3109-13	J0JCC0000100	CHIP INDUCTOR	5	
R3114	ERJ6GEYG680	M 68 OHM,J,1/10W	1	
R3121	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R3123	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R3130,31	ERJ3GEYJ221	M 220 OHM,J,1/16W	2	
R3133	J0JCC0000100	CHIP INDUCTOR	1	
R3137	ERJ3EKF1000	M 100 OHM, 1/16W	1	
R3140	ERJ3GEYJ470	M 47 OHM,J,1/16W	1	
R3143	ERJ6ENF63R4	M63.4 OHM, 1/10W	1	PAVCCZ
R3144	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3145	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3146	ERJ3RBD361	M 360 OHM,J,1/16W	1	
R3149	ERJ3RBD361	M 360 OHM,J,1/16W	1	
R3150	ERJ6ENF63R4	M63.4 OHM, 1/10W	1	PAVCCZ
R3151	ERJ3GEYJ221	M 220 OHM,J,1/16W	1	
R3152	ERJ3GEYJ104	M 100KOHM,J,1/16W	1	
R3153,54	ERJ3RBD361	M 360 OHM,J,1/16W	2	
R3163	ERJ6ENF1302	M 13KOHM, 1/10W	1	
R3173	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3174-76	ERJ3GEYJ680	M 68 OHM,J,1/16W	3	
R3177	D0GB103JA057	M 10KOHM,J,1/16W	1	
R3178	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3179,80	ERJ3GEYJ101	M 100 OHM,J,1/16W	2	
R3187	ERJ6ENF1500	M 150 OHM, 1/10W	1	
R3191	ERJ3GEYJ220	M 22 OHM,J,1/16W	1	
R3192-94	ERJ6ENF1500	M 150 OHM, 1/10W	3	
R3202	J0JCC0000100	CHIP INDUCTOR	1	
R3205	J0JCC0000100	CHIP INDUCTOR	1	
R3206	ERJ3GEYJ101	M 100 OHM,J,1/16W	1	
R3213,14	J0JCC0000100	CHIP INDUCTOR	2	
R3222	J0JCC0000100	CHIP INDUCTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R3227-29	J0JCC0000100	CHIP INDUCTOR	3	
R3236-38	J0JCC0000100	CHIP INDUCTOR	3	
R3239	ERJ3GEYJ221	M 220 OHM, J, 1/16W	1	
R3240	ERJ3EKF5600	M 560 OHM, 1/16W	1	
R3243	ERJ6GEYG271	M 270 OHM, J, 1/10W	1	
R3244	J0JCC0000100	CHIP INDUCTOR	1	
R3246	J0JCC0000100	CHIP INDUCTOR	1	
R3247	ERJ3GEYJ221	M 220 OHM, J, 1/16W	1	
R3271	J0JCC0000100	CHIP INDUCTOR	1	
R3273, 74	J0JCC0000100	CHIP INDUCTOR	2	
R3275	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R3302	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R3305	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R3306, 07	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	2	
R3308, 09	ERJ6GEY0R00V	M 0 OHM, 1/10W	2	
R3310	ERJ6RED750	M 75 OHM, 1/10W	1	
R3312	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R3313	ERJ6RED750	M 75 OHM, 1/10W	1	
R3318	ERJ6RED750	M 75 OHM, 1/10W	1	
R3348, 49	ERJ3GEYJ680	M 68 OHM, J, 1/16W	2	
R3350	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R3751	ERJ6ENF1432	M14.3KOHM, 1/10W	1	
R3753	ERJ6ENF1741	M1.74KOHM, 1/10W	1	
R3754	ERJ6ENF1621	M1.62KOHM, 1/10W	1	
R3755	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R3758	ERJ6ENF6651	M6.65KOHM, 1/10W	1	
R3765	ERJ6ENF2321	M2.32KOHM, 1/10W	1	
R3767	ERJ6ENF3161	M3.16KOHM, 1/10W	1	
R3768	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R4001	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4026	J0JCC0000100	CHIP INDUCTOR	1	
R4200-02	ERJ2RKD330	M 33 OHM, J, 0.063W	3	
R4242	J0JCC0000100	CHIP INDUCTOR	1	
R4284	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4286-88	ERJ2GEJ473	M 47KOHM, J, 0.063W	3	
R4317-20	ERJ2GEJ473	M 47KOHM, J, 0.063W	4	
R4322-30	ERJ2GEJ473	M 47KOHM, J, 0.063W	9	
R4500, 01	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R4502, 03	ERJ2RKD330	M 33 OHM, J, 0.063W	2	
R4506, 07	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R4508-23	ERJ2GEJ2R2X	M 2.2OHM, J, 0.063W	16	
R4524, 25	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R4526, 27	ERJ2GEJ102X	M 1KOHM, J, 0.063W	2	
R4528	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4529	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	1	
R4530	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4531	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	1	
R4532, 33	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R4535, 36	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	2	
R4538	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R4539	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R4540	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R4541-43	ERJ2GEJ680	M 68 OHM, J, 0.063W	3	
R4544-47	ERJ2GEJ103	M 10KOHM, J, 0.063W	4	
R4552	ERJ2GEJ220	M 22 OHM, J, 0.063W	1	
R4561	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R4562, 63	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	2	
R4564, 65	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R4578, 79	ERJ2GEJ151	M 150 OHM, J, 0.063W	2	
R4585	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R4587	ERJ3GEYF821	M 820 OHM, 1/16W	1	
R4593	ERJ3EKF1101	M 1.1KOHM, 1/16W	1	
R4596-98	ERJ6GEYG102	M 1KOHM, J, 1/10W	3	
R4601	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R4604	ERJ3EKF7501	M 7.5KOHM, 1/16W	1	
R4605	ERJ3EKF1201	M 1.2KOHM, 1/16W	1	
R4606	ERJ3EKF4701	M 4.7KOHM, 1/16W	1	
R4608	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R4609	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4610	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R4611	ERJ3EKF1371	M1.37KOHM, 1/16W	1	
R4612	ERJ3EKF1501	M 1.5KOHM, 1/16W	1	
R4613, 14	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R4615	ERJ3EKF1600	M 160 OHM, 1/16W	1	
R4616-19	D0YAR0000007	M 0.0 OHM, J, 0.063W	4	
R4622	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R4624	ERJ3EKF1691	M1.69KOHM, 1/16W	1	
R4626	ERJ2GEJ105	M 1MOHM, J, 0.063W	1	
R4627	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R4628, 29	ERJ2GEJ101	M 100 OHM, J, 0.063W	2	
R4631	ERJ3EKF4990	M 499 OHM, 1/16W	1	
R4635	EXB28V680JX	RESISTOR ARRAY	1	
R4636-38	ERJ2GEJ680	M 68 OHM, J, 0.063W	3	
R4639, 40	EXB28V680JX	RESISTOR ARRAY	2	
R4641	ERJ2GEJ220	M 22 OHM, J, 0.063W	1	
R4642	EXB28V680JX	RESISTOR ARRAY	1	
R4643, 44	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R4645-47	ERJ2GEJ680	M 68 OHM, J, 0.063W	3	
R4648	EXB28V330J	RESISTOR ARRAY	1	
R4649	EXB28V680JX	RESISTOR ARRAY	1	
R4650, 51	ERJ2GEJ680	M 68 OHM, J, 0.063W	2	
R4652	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R4653	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4654	ERJ3EKF4701	M 4.7KOHM, 1/16W	1	
R4655	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R4656	ERJ2GEJ222	M 2.2KOHM, J, 0.063W	1	
R4657, 58	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R4661	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R4664	ERJ3EKF6980	M 698 OHM, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R4665,66	ERJ2GEJ473	M 47KOHM, J, 0.063W	2	
R4667	ERJ2GEJ151	M 150 OHM, J, 0.063W	1	
R4670	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R4682	ERJ3EKF1002	M 10KOHM, 1/16W	1	
R4683	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4691,92	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R4698,99	D0YAR0000007	M 0.0 OHM, J, 0.063W	2	
R4702,03	D0YAR0000007	M 0.0 OHM, J, 0.063W	2	
R4706	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	
R4707	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R4708	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	
R4801	J0JCC0000100	CHIP INDUCTOR	1	
R4819,20	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R4838	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R4856-65	D0YAR0000007	M 0.0 OHM, J, 0.063W	10	
R4872	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R5480	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R5506,07	ERJ6GEYG103	M 10KOHM, J, 1/10W	2	
R5508	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R5509	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R5531	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R5532	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R5533	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R5534	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R5535	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R5536	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R5537	ERJ6GEYG681	M 680 OHM, J, 1/10W	1	
R5538	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R5540	ERJ6GEYJ471	M 470 OHM, J, 1/10W	1	
R5542	ERJ6GEYJ471	M 470 OHM, J, 1/10W	1	
R5544	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R5546,47	ERJ6GEYG103	M 10KOHM, J, 1/10W	2	
R5548,49	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	2	
R5554	ERJ6ENF2611	M2.61KOHM, 1/10W	1	
R5555	ERJ6ENF1271	M1.27KOHM, 1/10W	1	
R5570	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R5571	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R5572	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R5573	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R5600	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R5604	ERJ3GEYF473	M 47KOHM, 1/16W	1	
R5605	ERJ3EKF1272	M12.7KOHM, 1/16W	1	
R5606-09	D0YAR0000007	M 0.0 OHM, J, 0.063W	4	
R5610	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R5611	ERJ3EKF3602	M 36KOHM, 1/16W	1	
R5612	ERJ3EKF2322	M23.2KOHM, 1/16W	1	
R5620	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R5621	ERJ3GEYF473	M 47KOHM, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R5622	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R5623	ERJ3GEYF473	M 47KOHM, 1/16W	1	
R5625-28	D0YAR0000007	M 0.0 OHM, J, 0.063W	4	
R5629	ERJ3EKF3012	M30.1KOHM, 1/16W	1	
R5630	ERJ3EKF4752	M47.5KOHM, 1/16W	1	
R5631	ERJ3EKF3602	M 36KOHM, 1/16W	1	
R5632	ERJ3EKF3002	M 30KOHM, 1/16W	1	
R5633,34	ERJ3EKF1602	M16.0KOHM, 1/16W	2	
R5635	ERJ2GEJ223	M 22KOHM, J, 0.063W	1	
R5636	ERJ2GEJ683	M 68KOHM, J, 0.063W	1	
R5637	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R5638	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R5641	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R5644	ERJ2GEJ222	M 2.2KOHM, J, 0.063W	1	
R5646	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R5647	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R5660	ERJ2GEJ562	M 5.6KOHM, J, 0.063W	1	
R5661	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R5662	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R5670	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R5671	ERJ2GEJ183	M 18KOHM, J, 0.063W	1	
R5672	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R5674	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R5690,91	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R5692,93	D0GB473JA057	M 47KOHM, J, 1/16W	2	
R5694,95	D0GB102JA057	M 1KOHM, J, 1/16W	2	
R5696,97	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R5730,31	ERJ2GEJ473	M 47KOHM, J, 0.063W	2	
R6001	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	1	
R6003	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	1	
R6005	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	1	
R6020	ERF5TJ330	W 33 OHM, 5W	1	
R6021	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	1	
R6024	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	1	
R6026	D0GF7R5JA047	M 7.5 OHM, J, 0.33W	1	
R6031,32	ERJ6ENF8202	M 82KOHM, 1/10W	2	
R6033	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6034	ERJ6ENF2702	M 27KOHM, 1/10W	1	
R6041	D0GF5R6JA047	M 5.6 OHM, J, 0.33W	1	
R6043	D0GF5R6JA047	M 5.6 OHM, J, 0.33W	1	
R6053	D0GF5R6JA047	M 5.6 OHM, J, 0.33W	1	
R6062	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6064	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6066	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6068	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R6070-73	ERJ6GEY0R00V	M 0 OHM, 1/10W	4	
R6102	D0GD221JA059	M 220 OHM, J, 1/10W	1	
R6108	D0GD221JA059	M 220 OHM, J, 1/10W	1	
R6109	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6110	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6111	D0GD470JA059	M 47 OHM,J,0.25W	1	
R6113	ERJ14YJ224	M 220KOHM, J,1/4W	1	
R6114	D0GD470JA059	M 47 OHM,J,0.25W	1	
R6116	ERJ6GEYF473	M 47KOHM,J,1/10W	1	
R6131,32	ERJ6GEYJ101V	M 100 OHM,J,1/10W	2	
R6134	D0GD750JA059	M 75 OHM,J,0.25W	1	
R6135,36	D0GD100JA059	M 10 OHM,J,0.25W	2	
R6141,42	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6145	D0GF1R0JA047	M 1.0 OHM,J, 0.33W	1	
R6146,47	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6151,52	ERJ6GEYJ101V	M 100 OHM,J,1/10W	2	
R6154	D0GD750JA059	M 75 OHM,J,0.25W	1	
R6157-60	D0GF1R0JA047	M 1.0 OHM,J, 0.33W	4	
R6171	D0GD100JA059	M 10 OHM,J,0.25W	1	
R6172,73	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6181	D0GD100JA059	M 10 OHM,J,0.25W	1	
R6182,83	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6191,92	ERJ6GEYJ101V	M 100 OHM,J,1/10W	2	
R6193	D0GD750JA059	M 75 OHM,J,0.25W	1	
R6194	D0GF1R0JA047	M 1.0 OHM,J, 0.33W	1	
R6210	ERJ6GEYG222	M 2.2KOHM,J,1/10W	1	
R6213	ERJ6GEYJ101V	M 100 OHM,J,1/10W	1	
R6214	D0GD151JA059	M 150 OHM,J,0.25W	1	
R6220	ERJ6GEYG470V	M 47 OHM,J,1/10W	1	
R6221	ERJ6GEYF472	M 4.7KOHM,J,1/10W	1	
R6222	ERG1FJS103D	M 10KOHM, J, 1W	1	
R6223	ERG2FJS123D	M 12KOHM, J, 2W	1	
R6225	D0GD203JA059	M 20KOHM,J,1/10W	1	
R6226,27	ERJ6GEYJ163V	M 16KOHM,J,1/10W	2	
R6228	ERJ6GEYG562	M 5.6KOHM,J,1/10W	1	
R6229	ERJ6GEYJ163V	M 16KOHM,J,1/10W	1	
R6230	ERJ6GEYG470V	M 47 OHM,J,1/10W	1	
R6231	ERJ6GEYF472	M 4.7KOHM,J,1/10W	1	
R6232	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R6241	EXB38V470J	RESISTOR ARRAY	1	
R6242	EXB38V472JV	RESISTOR ARRAY	1	
R6246	ERJ6GEYJ273	M 27KOHM,J,1/10W	1	
R6247	D0GF154JA047	M 150 KOHM,J,0.33W	1	
R6248	ERJ6GEYJ273	M 27KOHM,J,1/10W	1	
R6249	D0GF154JA047	M 150 KOHM,J,0.33W	1	
R6252,53	ERJ6ENF3902	M 39KOHM, 1/10W	2	
R6254	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R6255	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R6256	ERJ6ENF1501	M 1.5KOHM, 1/10W	1	
R6257	ERJ6GEYG103	M 10KOHM,J,1/10W	1	
R6258	ERJ6GEYG222	M 2.2KOHM,J,1/10W	1	
R6261	ERJ6GEYG104	M 100KOHM,J,1/10W	1	
R6269	ERJ6GEYJ273	M 27KOHM,J,1/10W	1	
R6270	D0GF154JA047	M 150 KOHM,J,0.33W	1	
R6272	ERJ6GEYG222	M 2.2KOHM,J,1/10W	1	
R6273	ERJ6GEYG103	M 10KOHM,J,1/10W	1	
R6274	ERJ6GEYG221	M 220 OHM,J,1/10W	1	
R6276	ERJ6GEYG823	M 82KOHM,J,1/10W	1	
R6278	ERJ6GEYJ273	M 27KOHM,J,1/10W	1	
R6279	D0GF154JA047	M 150 KOHM,J,0.33W	1	
R6284	ERJ6GEYG102	M 1KOHM,J,1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6292	ERJ6GEYF473	M 47KOHM,J,1/10W	1	
R6401-03	D0GF7R5JA047	M 7.5 OHM,J, 0.33W	3	
R6421-23	D0GF5R6JA047	M 5.6 OHM,J, 0.33W	3	
R6441,42	D0GF5R6JA047	M 5.6 OHM,J, 0.33W	2	
R6451	D0GF5R6JA047	M 5.6 OHM,J, 0.33W	1	
R6465	ERJ6ENF2702	M 27KOHM, 1/10W	1	
R6466	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6467,68	ERJ6ENF8202	M 82KOHM, 1/10W	2	
R6471	ERJ6GEYG392	M 3.9KOHM,J,1/10W	1	
R6472	ERJ6GEYG222	M 2.2KOHM,J,1/10W	1	
R6473	ERJ6GEYF561	M 560 OHM,J,1/10W	1	
R6474	ERJ6GEYG102	M 1KOHM,J,1/10W	1	
R6475,76	ERJ6GEYF472	M 4.7KOHM,J,1/10W	2	
R6477	ERJ6GEYJ101V	M 100 OHM,J,1/10W	1	
R6501,02	ERJ6GEYJ101V	M 100 OHM,J,1/10W	2	
R6503	D0GD100JA059	M 10 OHM,J,0.25W	1	
R6504	D0GD750JA059	M 75 OHM,J,0.25W	1	
R6506	D0GD100JA059	M 10 OHM,J,0.25W	1	
R6507-10	D0GF1R0JA047	M 1.0 OHM,J, 0.33W	4	
R6511,12	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6516,17	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6521,22	ERJ6GEYJ101V	M 100 OHM,J,1/10W	2	
R6523	D0GD750JA059	M 75 OHM,J,0.25W	1	
R6531	D0GD100JA059	M 10 OHM,J,0.25W	1	
R6532,33	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6551	D0GD100JA059	M 10 OHM,J,0.25W	1	
R6552,53	ERJ6GEYF473	M 47KOHM,J,1/10W	2	
R6561-64	EXB38V470J	RESISTOR ARRAY	4	
R6565-68	EXB38V472JV	RESISTOR ARRAY	4	
R6580	ERJ6GEYG222	M 2.2KOHM,J,1/10W	1	
R6582,83	ERJ6ENF3902	M 39KOHM, 1/10W	2	
R6584	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R6585	ERJ6ENF1801	M 1.8KOHM, 1/10W	1	
R6586	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R6587	ERJ6GEYG222	M 2.2KOHM,J,1/10W	1	
R6588	ERJ6GEYG103	M 10KOHM,J,1/10W	1	
R6590	ERJ6GEYG221	M 220 OHM,J,1/10W	1	
R6591	EXB38V472JV	RESISTOR ARRAY	1	
R6592	ERJ6GEYF472	M 4.7KOHM,J,1/10W	1	
R6605	ERJ6GEYG182	M 1.8KOHM,J,1/10W	1	
R6607	D1BD6811A027	M 6.81KOHM, 1/10W	1	
R6608,09	D0GF102JA047	M 1.0 KOHM,J,0.33W	2	
R6610	ERJ6GEYG104	M 100KOHM,J,1/10W	1	
R6612	D0GD470JA059	M 47 OHM,J,0.25W	1	
R6621,22	ERJ6GEYG221	M 220 OHM,J,1/10W	2	
R6623	ERG2FJS333D	M 33KOHM, J, 2W	1	
R6638,39	D0GF1R0JA047	M 1.0 OHM,J, 0.33W	2	
R6642-44	D0GD330JA059	M 33 OHM,J,1/10W	3	
R6646-48	D0GD330JA059	M 33 OHM,J,1/10W	3	
R6658	D0D1101JA009	M 100 OHM,J,1W	1	
R6659,60	ERJ6GEYJ224	M 220KOHM,J,1/10W	2	
R6661	ERJ6GEYG104	M 100KOHM,J,1/10W	1	
R6662	ERJ6ENF2201	M 2.2KOHM, 1/10W	1	
R6663	ERJ6GEYG103	M 10KOHM,J,1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6664	D0GF222JA047	M 2.2 KOHM, J, 0.33W	1	
R6665	D0GD470JA059	M 47 OHM, J, 0.25W	1	
R6666	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R6667, 68	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	2	
R6671	D0GD470JA059	M 47 OHM, J, 0.25W	1	
R6672	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6673, 74	D0GD470JA059	M 47 OHM, J, 0.25W	2	
R6680, 81	D0GD100JA059	M 10 OHM, J, 0.25W	2	
R6692	D0GZ472JA020	M 4.7KOHM, J, 0.5W	1	
R6693	ERJ6GEYG823	M 82KOHM, J, 1/10W	1	
R6694	ERJ6GEYJ273	M 27KOHM, J, 1/10W	1	
R6695	ERJ8GEYJ124	M 120KOHM, J, 1/8W	1	
R6696	ERF5TK2R2	W 2.2 OHM, K, 5W	1	
R6700-04	ERJ6GEYJ471	M 470 OHM, J, 1/10W	5	
R6705, 06	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6707, 08	ERJ6GEYJ471	M 470 OHM, J, 1/10W	2	
R6709	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6710-14	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	5	
R6717, 18	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	2	
R6721, 22	EXB38V220JV	RESISTOR ARRAY	2	
R6723	ERJ6GEYG182	M 1.8KOHM, J, 1/10W	1	
R6724	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6742	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6745	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6746, 47	D0GD103JA059	M 10KOHM, J, 0.25W	2	
R6748	ERJ6GEYG332	M 3.3KOHM, J, 1/10W	1	
R6761	D0GD100JA059	M 10 OHM, J, 0.25W	1	
R6762	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6765	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	1	
R6766	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6768	D0GF1R0JA047	M 1.0 OHM, J, 0.33W	1	
R6769	D0GD750JA059	M 75 OHM, J, 0.25W	1	
R6775, 76	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R6777	D0GD151JA059	M 150 OHM, J, 0.25W	1	
R6781	D0GD470JA059	M 47 OHM, J, 0.25W	1	
R6782	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6788	ERJ6GEYJ474	M 470KOHM, J, 1/10W	1	
R6789	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R6791	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R6792	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6793	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6795, 96	ERJ6GEYG104	M 100KOHM, J, 1/10W	2	
R6797	ERJ6ENF1692	M 16.9KOHM, 1/10W	1	
R6801	ERG2FNJS8R2E	M 8.2 OHM, J, 2W	1	
R6802	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6806, 07	ERX12SJ1R5	M 1.5 OHM, J, 1/2W	2	
R6808	D0GF272JA047	M 2.7 KOHM, J, 0.33W	1	
R6809	ERG1SJ273	M 27KOHM, J, 1W	1	
R6810	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R6811	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6812	ERJ6ENF2403	M 240KOHM, 1/10W	1	
R6813	ERJ6ENF1002	M 10KOHM, 1/10W	1	
R6814	ERJ6ENF5601	M 5.6KOHM, 1/10W	1	
R6815	ERJ6ENF2700	M 270 OHM, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6816	D1BD1152A028	M 11.5KOHM, 1/10W	1	
R6817	ERJ6ENF2491	M 2.49KOHM, 1/10W	1	
R6818	ERJ6GEYJ474	M 470KOHM, J, 1/10W	1	
R6821	ERF5TJ221	W 220 OHM, J, 5W	1	
R6822	ERJ12YJ104U	M 100KOHM, 1/2W	1	
R6823	ERG1FJS104D	M 100KOHM, J, 1W	1	
R6824	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6825-27	ERJ6ENF2003	M 200KOHM, 1/10W	3	
R6828	ERJ6ENF4701	M 4.7KOHM, 1/10W	1	
R6829, 30	ERJ6GEYG104	M 100KOHM, J, 1/10W	2	
R6831	ERJ6GEYG153	M 15KOHM, J, 1/10W	1	
R6832	D0GF4R7JA047	M 4.7 OHM, J, 0.33W	1	
R6833-36	ERJ6ENF7502	M 75KOHM, 1/10W	4	
R6837	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6839	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6840	ERX12SJ1R5	M 1.5 OHM, J, 1/2W	1	
R6841	ERJ12YJ153U	M 15KOHM, 1/2W	1	
R6842	ERJ12YJ433U	M 43KOHM, 1/2W	1	
R6843	ERJ6GEYJ623	M 62KOHM, J, 1/10W	1	
R6844	D0D2101JA021	M 100 OHM, J, 2W	1	
R6845-47	ERJ6GEYJ623	M 62KOHM, J, 1/10W	3	
R6848	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R6849, 50	ERJ6ENF6802	M 68KOHM, 1/10W	2	
R6851	ERJ6ENF1802	M 18KOHM, 1/10W	1	
R6852	ERJ6ENF2701	M 2.7KOHM, 1/10W	1	
R6853	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6855	ERJ12YJ103	M 10KOHM, J, 1/2W	1	
R6856	ERQ12AJW560E	F 56 OHM, J, 1/2W	1	
R6857	ERJ12YJ124U	M 120KOHM, 1/2W	1	
R6860	D0D28R2JA021	M 8.2 OHM, J, 2W	1	
R6861, 62	ERJ6ENF5102	M 51KOHM, 1/10W	2	
R6863	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R6864	ERJ6ENF6801	M 6.8KOHM, 1/10W	1	
R6865	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R6866	ERJ6ENF6200	M 620 OHM, 1/10W	1	
R6867	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6868	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R6869	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6871-73	ERJ6ENF3902	M 39KOHM, 1/10W	3	
R6874	ERJ6ENF6801	M 6.8KOHM, 1/10W	1	
R6875	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R6876	ERJ6RBD561	M 560 OHM, 1/10W	1	
R6877	ERJ6GEYG392	M 3.9KOHM, J, 1/10W	1	
R6878	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R6879	ERJ6GEYF472	M 4.7KOHM, J, 1/10W	1	
R6886-88	ERJ6GEYJ224	M 220KOHM, J, 1/10W	3	
R6891	ERJ6GEYG183	M 18KOHM, J, 1/10W	1	
R6901	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6902-04	ERJ3GEYJ220	M 22 OHM, J, 1/16W	3	
R6905	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6909	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6913	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6917	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6924	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R6925, 26	J0JCC0000100	CHIP INDUCTOR	2	
R6931-34	ERJ6GEYG103	M 10KOHM, J, 1/10W	4	
R6935, 36	ERJ8GEYJ224	M 220KOHM, J, 1/8W	2	
R6938	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R6951	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R6952-54	ERJ3GEYJ220	M 22 OHM, J, 1/16W	3	
R6955	ERJ6GEYJ221	M 220 OHM, J, 1/10W	1	
R6959	ERJ6GEYJ221	M 220 OHM, J, 1/10W	1	
R6963	ERJ6GEYJ221	M 220 OHM, J, 1/10W	1	
R6967	ERJ6GEYJ221	M 220 OHM, J, 1/10W	1	
R6971	ERJ6GEYJ221	M 220 OHM, J, 1/10W	1	
R6975,76	J0JCC0000100	CHIP INDUCTOR	2	
R6981-84	ERJ6GEYJ103	M 10KOHM, J, 1/10W	4	
R6985,86	ERJ8GEYJ224	M 220KOHM, J, 1/8W	2	
R6989	ERJ6GEYJ103	M 10KOHM, J, 1/10W	1	
R7112	D0GF472JA047	M 4.7KOHM, J, 0.33W	1	
R7119	EXB38V220JV	RESISTOR ARRAY	1	
R7122-25	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7126	ERJ6GEYJ224	M 220KOHM, J, 1/10W	1	
R7130-36	EXB38V471J	RESISTOR ARRAY	7	
R7142-45	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7151-54	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7155	EXB38V102J	RESISTOR ARRAY	1	
R7159	EXB38V470J	RESISTOR ARRAY	1	
R7162	EXB38V471J	RESISTOR ARRAY	1	
R7171-74	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7177	EXB38V102J	RESISTOR ARRAY	1	
R7180	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R7184	EXB38V220JV	RESISTOR ARRAY	1	
R7185	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R7186	J0JCC0000100	CHIP INDUCTOR	1	
R7212-15	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7219	ERJ6GEYJ224	M 220KOHM, J, 1/10W	1	
R7223-26	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7229	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R7232-35	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7238	EXB38V471J	RESISTOR ARRAY	1	
R7245	EXB38V102J	RESISTOR ARRAY	1	
R7249	EXB38V220JV	RESISTOR ARRAY	1	
R7250	EXB38V470J	RESISTOR ARRAY	1	
R7257	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R7258	EXB38V102J	RESISTOR ARRAY	1	
R7262-65	D0GZ6R8JA020	M 6.8 OHM, J, 0.5W	4	
R7269	D0GF472JA047	M 4.7KOHM, J, 0.33W	1	
R7273-79	EXB38V471J	RESISTOR ARRAY	7	
R7280	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R7281	ERJ6GEYJ102	M 1KOHM, J, 1/10W	1	
R7285	EXB38V220JV	RESISTOR ARRAY	1	
R7286	J0JCC0000100	CHIP INDUCTOR	1	
R7288,89	EXB38V222J	RESISTOR ARRAY	2	
R7290,91	EXB38V470J	RESISTOR ARRAY	2	
R8001	ERJ2GEJ181	M 180 OHM, J, 0.063W	1	
R8002	ERJ2GEJ820	M 82 OHM, J, 0.063W	1	
R8003	J0JCC0000100	CHIP INDUCTOR	1	
R8004	ERJ3EKF2402	M 24KOHM, 1/16W	1	
R8005	ERJ3EKF1002	M 10KOHM, 1/16W	1	
R8006	ERJ3EKF6801	M 6.8KOHM, 1/16W	1	
R8023-29	D0YAR0000007	M 0.0 OHM, J, 0.063W	7	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8030	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8031,32	ERJ3EKF2700	M 270 OHM, 1/16W	2	
R8035	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8039	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8056-73	ERJ2GEJ470	M 47 OHM, J, 0.063W	18	
R8074	ERJ2GEJ221	M 220 OHM, J, 0.063W	1	
R8075-78	ERJ2GEJ470	M 47 OHM, J, 0.063W	4	
R8079,80	D0YAR0000007	M 0.0 OHM, J, 0.063W	2	
R8081	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8082	D1BA75R0A026	M0.75KOHM, 1/10W	1	
R8083	ERJ2GEJ301	M 300 OHM, J, 0.063W	1	
R8084	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8086	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	
R8087	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8090	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8091	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8093	ERJ2GEJ470	M 47 OHM, J, 0.063W	1	
R8095	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8097	ERJ2GEJ221	M 220 OHM, J, 0.063W	1	
R8098,99	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R8100	ERJ2GEJ470	M 47 OHM, J, 0.063W	1	
R8101	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8106	ERJ2GEJ202	M 2KOHM, J, 0.063W	1	
R8107	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8111	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8301	EXB2HV680J	RESISTOR ARRAY	1	TH-42PX70B/E
R8303,04	ERJ2GEJ101	M 100 OHM, J, 0.063W	2	TH-42PX70B/E
R8305	ERJ2GEJ223	M 22KOHM, J, 0.063W	1	TH-42PX70B/E
R8306,07	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	2	TH-42PX70B/E
R8308	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-42PX70B/E
R8309-12	ERJ2GEJ101	M 100 OHM, J, 0.063W	4	TH-42PX70B/E
R8314,15	ERJ2GEJ101	M 100 OHM, J, 0.063W	2	TH-42PX70B/E
R8318	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	1	TH-42PX70B/E
R8321	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-42PX70B/E
R8322	ERJ2GEJ102X	M 1KOHM, J, 0.063W	1	TH-42PX70B/E
R8323,24	ERJ2GEJ473	M 47KOHM, J, 0.063W	2	TH-42PX70B/E
R8325-27	ERJ2GEJ680	M 68 OHM, J, 0.063W	3	TH-42PX70B/E
R8328	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-42PV70F/P
R8329	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	TH-42PX70B/E
R8401	ERJ8GEY0R00	M 0 OHM, 1/8W	1	TH-42PX70B/E
R8402	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	TH-42PX70B/E
R8404,05	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	TH-42PX70B/E
R8406	ERJ8RSJR10	M 1 OHM, 1/8W	1	TH-42PX70B/E

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8407	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	TH-42PX70B/E
R8410, 11	ERJ2GEJ223	M 22KOHM, J, 0.063W	2	TH-42PX70B/E
R8412	EXB2HV473JV	RESISTOR ARRAY	1	TH-42PX70B/E
R8414	EXB2HV101J	RESISTOR ARRAY	1	TH-42PX70B/E
R8416	ERJ2GEJ223	M 22KOHM, J, 0.063W	1	TH-42PX70B/E
R8417	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	TH-42PX70B/E
R8418	ERJ2GEJ681	M 680 OHM, J, 0.063W	1	TH-42PX70B/E
R8419	EXB2HV101J	RESISTOR ARRAY	1	TH-42PX70B/E
R8421-25	ERJ2GEJ680	M 68 OHM, J, 0.063W	5	TH-42PX70B/E
R8426	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	TH-42PX70B/E
R8427, 28	EXB2HV680J	RESISTOR ARRAY	2	TH-42PX70B/E
R8430	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	TH-42PX70B/E
R8431, 32	ERJ2GEJ151	M 150 OHM, J, 0.063W	2	TH-42PX70B/E
R8433	ERJ2GEJ223	M 22KOHM, J, 0.063W	1	TH-42PX70B/E
R8434	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	TH-42PX70B/E
R8435, 36	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	TH-42PX70B/E
R8437	EXB2HV104JV	RESISTOR ARRAY	1	TH-42PX70B/E
R8438	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	TH-42PX70B/E
R8440	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	TH-42PX70B/E
R8441	EXB2HV680J	RESISTOR ARRAY	1	TH-42PX70B/E
R8443	EXB2HV680J	RESISTOR ARRAY	1	TH-42PX70B/E
R8445	ERJ2GEJ104	M 100KOHM, J, 0.063W	1	TH-42PX70B/E
R8446	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	TH-42PX70B/E
R8449	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	TH-42PX70B/E
R8450	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	TH-42PX70B/E
R8451	EXB28V680JX	RESISTOR ARRAY	1	TH-42PX70B/E
R8452, 53	ERJ2GEJ680	M 68 OHM, J, 0.063W	2	TH-42PX70B/E
R8454	EXB28V151JX	RESISTOR ARRAY	1	PAVCCZ TH-42PX70B/E
R8456-61	ERJ2GEJ680	M 68 OHM, J, 0.063W	6	TH-42PX70B/E
R8463	EXB28V151JX	RESISTOR ARRAY	1	PAVCCZ TH-42PX70B/E
R8465, 66	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	TH-42PX70B/E
R8468	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	TH-42PX70B/E
R8469	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	TH-42PX70B/E
R8470, 71	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	TH-42PX70B/E
R8472	D1HG1038A002	NETWORK RESISTER	1	TH-42PV70F/P
R8474, 75	EXB28V103JX	RESISTOR ARRAY	2	TH-42PV70F/P
R8477	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	TH-42PX70B/E
R8484	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	TH-42PX70B/E
R8502-04	ERJ2GEJ331	M 330 OHM, J, 0.063W	3	
R8506	ERJ2GEJ331	M 330 OHM, J, 0.063W	1	
R8507-10	ERJ3EKF91R0	M 91 OHM, 1/16W	4	
R8512	ERJ3EKF1800	M 180 OHM, 1/16W	1	
R8513	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	
R8517-19	DOYAR0000007	M 0.0 OHM, J, 0.063W	3	
R8551	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8555-61	ERJ2GEJ680	M 68 OHM, J, 0.063W	7	
R8564	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8601, 02	ERJ2GEJ220	M 22 OHM, J, 0.063W	2	
R8603	ERJ2GEJ473	M 47KOHM, J, 0.063W	1	
R8604	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R8605	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8621-36	ERJ2GEJ680	M 68 OHM, J, 0.063W	16	
R8653	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8655	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8702	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	
R8703	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8709	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	
R8710	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8711, 12	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R8732	ERJ2GEJ101	M 100 OHM, J, 0.063W	1	
R8735-39	ERJ2GEJ680	M 68 OHM, J, 0.063W	5	
R8742	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8745, 46	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R8749	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8802-09	ERJ2GEJ103	M 10KOHM, J, 0.063W	8	
R8812	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	
R8813	EXB28V680JX	RESISTOR ARRAY	1	
R8814-17	ERJ2GEJ680	M 68 OHM, J, 0.063W	4	
R8818	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	1	
R8823	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	1	
R8825	ERJ6GEY0R00V	M 0 OHM, 1/10W	1	
R8826	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8828	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8832	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8833	J0JCC0000100	CHIP INDUCTOR	1	
R8851-54	DOYAR0000007	M 0.0 OHM, J, 0.063W	4	
R8855-60	ERJ2GEJ680	M 68 OHM, J, 0.063W	6	
R8862-64	ERJ2GEJ680	M 68 OHM, J, 0.063W	3	
R8865-67	EXB2HV680J	RESISTOR ARRAY	3	
R8868	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8869	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8870	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	
R8871	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8874-76	ERJ2GEJ103	M 10KOHM, J, 0.063W	3	
R8877-89	ERJ2GEJ680	M 68 OHM, J, 0.063W	13	
R8891, 92	ERJ2GEJ680	M 68 OHM, J, 0.063W	2	
R8893	DOYAR0000007	M 0.0 OHM, J, 0.063W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R8894	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8895-97	D0YAR0000007	M 0.0 OHM, J, 0.063W	3	
R8898,99	ERJ2GEJ103	M 10KOHM, J, 0.063W	2	
R8900,01	ERJ2GEJ680	M 68 OHM, J, 0.063W	2	
R8904-10	ERJ2GEJ103	M 10KOHM, J, 0.063W	7	
R8911-18	ERJ2GEJ680	M 68 OHM, J, 0.063W	8	
R8919-22	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	4	
R8923,24	ERJ2GEJ222	M 2.2KOHM, J, 0.063W	2	
R8925,26	ERJ2GEJ472	M 4.7KOHM, J, 0.063W	2	
R8927	D0YAR0000007	M 0.0 OHM, J, 0.063W	1	
R8929	EXB2HVR000	RESISTOR ARRAY	1	
R8935	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8947	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8948	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R8952	ERJ2GEJ680	M 68 OHM, J, 0.063W	1	
R8963	ERJ2GEJ103	M 10KOHM, J, 0.063W	1	
R9062-67	ERJ3GEYJ101	M 100 OHM, J, 1/16W	6	
R9070	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R9099	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9101,02	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9104,05	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9107	ERJ3GEYJ332	M 3.3KOHM, J, 1/16W	1	
R9108,09	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9110	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9112	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9113	ERJ3GEYJ100	M 10 OHM, J, 1/16W	1	
R9115,16	ERJ3GEYJ101	M 100 OHM, J, 1/16W	2	
R9119	EXB38V470J	RESISTOR ARRAY	1	
R9120	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9121	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9122,23	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9126	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9127	ERJ3GEYJ683	M 68KOHM, J, 1/16W	1	
R9129	ERJ3GEYJ683	M 68KOHM, J, 1/16W	1	
R9131-33	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	3	
R9134	ERJ3GEYJ333	M 33KOHM, J, 1/16W	1	
R9135	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9141-45	ERJ3GEYJ101	M 100 OHM, J, 1/16W	5	
R9149	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9150,51	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9154,55	ERJ3GEYJ562	M 5.6KOHM, J, 1/16W	2	
R9156	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9158,59	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9160,61	J0JCC0000100	CHIP INDUCTOR	2	
R9164,65	ERJ3GEYJ222	M 2.2KOHM, J, 1/16W	2	
R9166	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9167	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9170-72	D0GB393JA041	M 39KOHM, J, 1/16W	3	
R9173,74	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9177	ERJ3GEYJ223	M 22KOHM, J, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R9181-84	D0GB102JA057	M 1KOHM, J, 1/16W	4	
R9185,86	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9187,88	ERJ3GEYJ562	M 5.6KOHM, J, 1/16W	2	
R9189,90	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9193	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9194	J0JCC0000100	CHIP INDUCTOR	1	
R9196	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9199	ERJ3GEYJ272	M 2.7KOHM, J, 1/16W	1	
R9200,01	ERJ3GEYJ100	M 10 OHM, J, 1/16W	2	
R9203	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R9205	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9206,07	D0GB102JA057	M 1KOHM, J, 1/16W	2	
R9215	D0GB123JA057	M 12KOHM, J, 1/16W	1	
R9217-22	D0GB103JA057	M 10KOHM, J, 1/16W	6	
R9223	ERJ3GEYJ272	M 2.7KOHM, J, 1/16W	1	
R9225	ERJ3GEYJ272	M 2.7KOHM, J, 1/16W	1	
R9237	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9240	J0JCC0000100	CHIP INDUCTOR	1	
R9317	ERJ3GEYJ391	M 390 OHM, J, 1/16W	1	
R9347,48	EXB2HV220JV	RESISTOR ARRAY	2	
R9349	EXB2HV470JV	RESISTOR ARRAY	1	
R9350,51	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9352	EXB2HV220JV	RESISTOR ARRAY	1	
R9354-56	EXB2HV220JV	RESISTOR ARRAY	3	
R9361,62	ERJ3GEYJ220	M 22 OHM, J, 1/16W	2	
R9363	EXB2HV470JV	RESISTOR ARRAY	1	
R9369	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9370	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9371	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9379	J0JCC0000100	CHIP INDUCTOR	1	
R9380	ERJ3GEYJ560	M 56 OHM, J, 1/16W	1	
R9383	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R9384,85	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	2	
R9391	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9392,93	J0JCC0000100	CHIP INDUCTOR	2	
R9396-99	ERJ3GEYJ220	M 22 OHM, J, 1/16W	4	
R9402	ERJ6GEYR00V	M 0 OHM, 1/10W	1	
R9403	EXB2HV470JV	RESISTOR ARRAY	1	
R9500	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9502	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9503	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R9506	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R9507	J0JCC0000100	CHIP INDUCTOR	1	
R9511-13	ERJ3GEYJ470	M 47 OHM, J, 1/16W	3	
R9516	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9518	J0JCC0000100	CHIP INDUCTOR	1	
R9523	ERJ3GEYJ472	M 4.7KOHM, J, 1/16W	1	
R9525	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9526	J0JCC0000100	CHIP INDUCTOR	1	
R9530	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9531-33	ERJ3GEYJ470	M 47 OHM, J, 1/16W	3	
R9534	EXB38V470J	RESISTOR ARRAY	1	
R9535,36	ERJ3GEYJ470	M 47 OHM, J, 1/16W	2	
R9538,39	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9541	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9543,44	D0GB103JA057	M 10KOHM, J, 1/16W	2	
R9545	ERJ3GEYJ304	M 300KOHM, J, 1/16W	1	
R9548-50	D0GB103JA057	M 10KOHM, J, 1/16W	3	
R9552	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9553,54	J0JCC0000100	CHIP INDUCTOR	2	
R9557,58	J0JCC0000100	CHIP INDUCTOR	2	
R9561	EXB38V222J	RESISTOR ARRAY	1	
R9562	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R9563-66	EXB2HV470JV	RESISTOR ARRAY	4	
R9567	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9569	J0JCC0000100	CHIP INDUCTOR	1	
R9824-27	ERJ3GEYJ101	M 100 OHM, J, 1/16W	4	
R9828	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9839	EXB38V101JV	RESISTOR ARRAY	1	
R9840	ERJ3GEYJ220	M 22 OHM, J, 1/16W	1	
R9845	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9846, 47	EXB2HV222JV	RESISTOR ARRAY	2	
R9848, 49	EXB2HV470JV	RESISTOR ARRAY	2	
R9850	D0GB473JA057	M 47KOHM, J, 1/16W	1	
R9854	ERJ3GEYJ101	M 100 OHM, J, 1/16W	1	
R9859	EXB38V101JV	RESISTOR ARRAY	1	
R9861-63	D0GB103JA057	M 10KOHM, J, 1/16W	3	
R9868	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9869-71	D0GB103JA057	M 10KOHM, J, 1/16W	3	
R9872	J0JCC0000100	CHIP INDUCTOR	1	
R9874	J0JCC0000100	CHIP INDUCTOR	1	
R9878	ERJ3EKF1102	M 11KOHM, 1/16W	1	
R9879	ERJ3EKF1302	M 13KOHM, 1/16W	1	
R9886, 87	ERJ3EKF5602	M 56KOHM, 1/16W	2	
R9888	ERJ3EKF1102	M 11KOHM, 1/16W	1	
R9889	ERJ3EKF1742	M17.2KOHM, 1/16W	1	
R9890	ERJ3EKF4752	M47.5KOHM, 1/16W	1	
R9891	ERJ3EKF1272	M12.7KOHM, 1/16W	1	
R9892	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9893	ERJ3EKF5602	M 56KOHM, 1/16W	1	
R9894	ERJ3EKF1102	M 11KOHM, 1/16W	1	
R9895	ERJ3GEYJ104	M 100KOHM, J, 1/16W	1	
R9896	ERJ3EKF1822	M18.2KOHM, 1/16W	1	
R9897	ERJ3EKF4752	M47.5KOHM, 1/16W	1	
R9901, 02	J0JCC0000100	CHIP INDUCTOR	2	
R9903	EXB2HV470JV	RESISTOR ARRAY	1	
R9904	ERJ3GEYJ470	M 47 OHM, J, 1/16W	1	
R9905	ERJ3GEYJ330	M 33 OHM, J, 1/16W	1	
R9906	EXB38V470J	RESISTOR ARRAY	1	
R9907	D0GB151JA057	M 150 OHM, J, 1/16W	1	
R9908-11	J0JCC0000100	CHIP INDUCTOR	4	
R9912	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9915-18	J0JCC0000100	CHIP INDUCTOR	4	
R9919	D0GB102JA057	M 1KOHM, J, 1/16W	1	
R9922	J0JCC0000100	CHIP INDUCTOR	1	
R9928, 29	J0JCC0000100	CHIP INDUCTOR	2	
R9936-39	ERJ3EKF1001	M 1KOHM, 1/16W	4	
R9940	ERJ3GEYJ330	M 33 OHM, J, 1/16W	1	
R9941, 42	ERJ3GEYJ470	M 47 OHM, J, 1/16W	2	
R9943-51	EXB38V470J	RESISTOR ARRAY	9	
R9952-55	ERJ3GEYJ470	M 47 OHM, J, 1/16W	4	
R9956	D0GB103JA057	M 10KOHM, J, 1/16W	1	
R9960	J0JCC0000100	CHIP INDUCTOR	1	
R9961	D0GB103JA057	M 10KOHM, J, 1/16W	1	
RM2501	PNA4701M05TV	REMOCON RECEIVER	1	
S1	K1KA03BA0061	3P CONNECTOR	1	
SC2	K1KA02A00626	2P CONNECTOR	1	
SC20	K1KY30AA0369	30P CONNECTOR	1	
SC30	K1KA10AA0191	10P CONNECTOR	1	
SC41, 42	K1ML80B00001	80P CONNECTOR	2	
SC45, 46	K1KA09A00239	9P CONNECTOR	2	
SCMM1, M2	TMME260	CLAMPER	2	
SD1-D4	K1MN96B00005	96P CONNECTOR	4	
SD46	K1KB09AA0213	9P CONNECTOR	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
SS11	K1KA02A00626	2P CONNECTOR	1	
SS12	K1KA10AA0194	10P CONNECTOR	1	
SS23	K1KA12AA0194	12P CONNECTOR	1	
SS34	K1KA03AA0193	3P CONNECTOR	1	
SS53A-6A	K1MN13BA0258	13P CONNECTOR	4	
SU1-U4	K1MN96B00005	96P CONNECTOR	4	
SU45	K1KB09AA0213	9P CONNECTOR	1	
SW2500	K0F162B00002	SWITCH	1	△
SW3753-57	EVQPC105K	SWITCH	5	
T6602	ETS25AZ169AD	SWITCHING TRANS	1	
TU3200	ENG7701GF	TUNER	1	PAVCCZ △
TU8301	ENV77M05D8F	TUNER	1	PAVCCZ TH-42PX70B/E △
VR6000	EVMEASA00B14	CONTROL 10KOHMB 0.3W	1	
VR6600	EVMEASA00B13	CONTROL 1KOHMB 0.3W	1	
VR6602	EVMEASA00B53	CONTROL 5KOHMB 0.3W	1	
X1100	H0J100500035	CRYSTAL	1	
X2010	H0J245500082	CRYSTAL	1	
X4500	H0J270500113	CRYSTAL	1	
X8001	H0J270500061	CRYSTAL	1	
X8301	H0J204500006	CRYSTAL	1	PAVCCZ TH-42PX70B/E
X9000	H2D100500004	CRYSTAL	1	
X9200	H0J200500038	CRYSTAL	1	
ZA0001	K4AZ01D00004	TERMINAL	1	PAVCCZ
ZA0002	K4CD08000002	AV TERMINAL	1	
ZA0004, 05	K4AZ01D00004	TERMINAL	2	PAVCCZ
ZA0006, 07	K4CD08000002	AV TERMINAL	2	
ZA3001-08	K4CD08000002	AV TERMINAL	8	
ZA5501-03	K4CZ01000027	COMPATIBLE WITH JALCO K9	3	
ZA6001, 02	K4CD01000011	AV TERMINAL	2	
ZA6005	K4CD01000011	AV TERMINAL	1	
ZA6401-03	K4CD01000011	AV TERMINAL	3	
ZA7101-04	K4AD01Z00001	TERMINAL	4	
ZA7201-04	K4AD01Z00001	TERMINAL	4	
ZA9001	K4CD01000011	AV TERMINAL	1	
C404	F0CZ2335A097	E 0.033UF, 200V	1	
C406	F1E2J4730001	C 0.047PF, , 600V	1	
C407	F2B2W220A032	C 22UF, 450V	1	△
C408	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C410	FIJ1E105A080	E 1 UF 25V	1	
C413	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C420	FIJ1E105A080	E 1 UF 25V	1	
C421	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C423	ECJ1VB1H472K	C 4700PF, K, 50V	1	
C425	FIJ1E105A080	E 1 UF 25V	1	
C426	ECJ1VC1H471J	C 470PF, J, 50V	1	
C427	FIH1C105A071	C 1UF, K, 16V	1	
C428	ECJ1XC1H221J	C 220PF, J, 50V	1	
C429	F1E2J4730001	C 0.047PF, , 600V	1	
C431	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C432, 33	FIH1C105A071	C 1UF, K, 16V	2	
C435	ECJ1XC1H101J	C 100PF, J, 50V	1	
C436	FIH1C105A071	C 1UF, K, 16V	1	
C437	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C443, 44	ECKD3A102KBP	C 1000PF, K, 1KV	2	
C445	FIH1C105A071	C 1UF, K, 16V	1	
C446	F2B2W3910010	C 390UF, 450V	1	△
C450	ECJ1VB1H103K	C 0.001UF, K, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C451	ECKD3A101KBP	C 100PF, K, 1KV	1	
C457	ECWH12333RHV	P 0.013UF, J, 1.2KV	1	
C462	F1J1E105A080	E 1 UF 25V	1	
C463	F1H1H2200008	E 22UF, 50V	1	
C467	F1BAF221A107	C 220UF, 250V	1	△
C468	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C469	F1BAF221A107	C 220UF, 250V	1	△
C470	F0CAF335A080	C 0.033UF, 250V	1	△
C472	F1BAF221A107	C 220UF, 250V	1	△
C474,75	F1BAF221A107	C 220UF, 250V	2	△
C478	F1BAF221A107	C 220UF, 250V	1	△
C492	ECA1HM100	E 10UF, 50V	1	
C493	ECA1HM470	E 47UF, 50V	1	
C493	F2A1H4700057	E 47UF, 50V	1	
C497	F2A1H4700057	E 47UF, 50V	1	
C501,02	ECJ1VB1H103K	C 0.001UF, K, 50V	2	
C504	F1H1C105A071	C 1UF, K, 16V	1	
C505	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C506	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C507	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C509	ECA1EHG101	E 100UF, 25V	1	
C511	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C515	F2A1A1220015	E 1200UF, 10V	1	
C516	ECJ1VB1C474K	C 0.47UF, K, 16V	1	
C517	F2A1E221A096	E 220UF, 25V	1	
C518,19	F1H1C105A071	C 1UF, K, 16V	2	
C520	F0C2E683A160	E 0.068UF, 250V	1	
C521	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C522	F1E2E1030002	C 0.010PF, , 600V	1	
C523	F1J1E105A080	E 1 UF 25V	1	
C526	ECJ1VB1H223K	C 0.22UF, K, 50V	1	
C528	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C529	ECJ2FB1C475K	C 47UF, K, 16V	1	
C530	ECJ1VB1E333K	C 0.033UF, K, 25V	1	
C531	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C534	F1H1H471A792	E 470UF, 50V	1	
C546,47	ECJ1VB1H102K	C 1000PF, K, 50V	2	
C552	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C554	F1H1C105A071	C 1UF, K, 16V	1	
C555	F2A2C4710003	E 470UF, 160V	1	△
C556	F2A1E3320039	E 3300PF, 25V	1	
C558	F2A1E4710065	E 470UF, 25V	1	
C559	F2A1A1020084	E 1000UF, 10V	1	
C562	F1H1H223A219	E 0.022UF, 50V	1	
C571	ECJ1VC1H330J	C 33PF, J, 50V	1	
C574	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C577	F2A2A330A022	E 33UF, 100V	1	△
C581	ECJ2VB1H223K	C 0.022UF, K, 50V	1	
C583	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C584	ECJ2VB1H223K	C 0.022UF, K, 50V	1	
C585	F1H1H223A219	E 0.022UF, 50V	1	
C587	ECJ1VB1H332K	C 3300PF, K, 50V	1	
C590	ECJ1XB1H104K	C 10PF, J, 50V	1	
C601	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C603	F1J1E105A080	E 1 UF 25V	1	
C604,05	F2A2D1510008	E 150UF, 200V	2	△
C607	F1H1C105A071	C 1UF, K, 16V	1	
C610	F1J1E105A080	E 1 UF 25V	1	
C611	F2B2T1420003	E 142UF, 220V	1	△
C612	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C616	ECKD3A102KBP	C 1000PF, K, 1KV	1	
C619	F1H1C105A071	C 1UF, K, 16V	1	
C620	F1J1E105A080	E 1 UF 25V	1	
C623	ECA1HM100	E 10UF, 50V	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
C624	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C625	F2A1H1000083	E 10UF, 50V	1	
C626	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C627	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C630,31	ECJ1VB1H103K	C 0.001UF, K, 50V	2	
C632	ECJ2XC1H330J	C 33PF, J, 50V	1	
C639	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C640	ECJ1VC1H330J	C 33PF, J, 50V	1	
C641	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C650,51	ECJ1VB1E104K	C 0.10UF, K, 25V	2	
C653	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C657	ECJ1VB1H102K	C 1000PF, K, 50V	1	
C658	F1J1E105A080	E 1 UF 25V	1	
C660	ECJ2FB1C225K	C 22UF, K, 16V	1	
C661	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C662	ECJ2VB1H103K	C 0.01UF, K, 50V	1	
C665	ECJ1XC1H101J	C 100PF, J, 50V	1	
C666	ECJ1VB1H103K	C 0.001UF, K, 50V	1	
C667,68	ECJ1VB1H102K	C 1000PF, K, 50V	2	
C670	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C671	ECJ2VB1E104K	C 0.1UF, K, 25V	1	
C672	ECJ1VB1E104K	C 0.10UF, K, 25V	1	
C673	F1E2J4730001	C 0.047PF, , 600V	1	
D401	B0FBAT000006	DIODE	1	△
D404	B0EBKT000007	DIODE	1	△
D407,08	B0ACD0000010	DIODE	2	
D411	B0BB17000009	DIODE	1	
D415	B0JAME000099	DIODE	1	
D416	B0HAMP000067	DIODE	1	
D418	B0BC8R100013	ZENER DIODE	1	
D419,20	B0EAMR000009	DIODE	2	
D423	MA188	DIODE	1	
D425	MA188	DIODE	1	
D429	B0EAKT000048	DIODE	1	
D431	B0JCDD000002	DIODE	1	
D433	B0BC01400033	ZENER DIODE	1	
D435	B0EAKT000048	DIODE	1	
D436	B0AACK000004	DIODE	1	
D436	MA165TA5	DIODE	1	
D438	B0BC02000014	ZENER DIODE	1	
D439	B0EAKT000048	DIODE	1	
D441	B0HAMM000122	DIODE	1	
D444	B0HAMM000122	DIODE	1	
D445	MTZJ10B	ZENER DIODE	1	
D501	B0EAMR000010	DIODE	1	
D503	B0AACK000004	DIODE	1	
D503	MA165TA5	DIODE	1	
D504	B0AACK000004	DIODE	1	
D504	MA165TA5	DIODE	1	
D506	B0ACD0000010	DIODE	1	
D507,08	B0BC7R400023	ZENER DIODE	2	
D509	B0JANG000018	DIODE	1	
D511	B0JAML000011	DIODE	1	
D512	B0ACD0000010	DIODE	1	
D516-18	B0BA03300004	ZENER DIODE	3	
D520	B0ACD0000010	DIODE	1	
D521	B0JAME000099	DIODE	1	
D522,23	B0JCDD000002	DIODE	2	
D524	B0AACK000004	DIODE	1	
D524	MA165TA5	DIODE	1	
D531	B0HBSN000013	DIODE	1	
D535	MA188	DIODE	1	
D536	B0JBSG000026	DIODE	1	
D538	B0BC5R100039	ZENER DIODE	1	
D539,40	B0HARR000019	DIODE	2	
D543	B0BC01400033	ZENER DIODE	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
D544,45	BOBA02100001	ZENER DIODE	2	
D546	BOBA02800001	ZENER DIODE	1	
D549	B0BC02500008	ZENER DIODE	1	
D569,70	BOBA05100010	ZENER DIODE	2	
D579	BOAAC0000004	DIODE	1	
D582	MAZ705600F	ZENER DIODE	1	
D584	MAZ706200F	ZENER DIODE	1	
D586	BOHAMP000067	DIODE	1	
D598	B0BC5R100039	ZENER DIODE	1	
D599	B0JCND000009	DIODE	1	
D600	B0BC7R400023	ZENER DIODE	1	
D601	B0BC5R100039	ZENER DIODE	1	
D602	B0BC8R100013	ZENER DIODE	1	
D603	BOBA01900005	ZENER DIODE	1	
D701,02	B0BC5R100039	ZENER DIODE	2	
D703	BOEAKT000048	DIODE	1	
F403	K5G631B00007	FUSE	1	△
IC401	CNC1S171R	IC	1	△
IC403	CNC1S171R	IC	1	△
IC406	C0DBZZZ00082	IC	1	
IC408	B3PBA0000459	IC	1	△
IC409	MIP3E30MPSCF	IC	1	△
IC411	C0DAEMZ00001	IC	1	
IC412	CNC1S171R	IC	1	△
IC501	C2ABDB000114	IC	1	
IC502	COEBH0000210	IC	1	
IC504	C0DAEMZ00001	IC	1	
IC505	B3PBA0000459	IC	1	△
IC506	C0DAEMZ00001	IC	1	
IC507	B3PBA0000459	IC	1	△
IC508	C0DAEMZ00001	IC	1	
IC509	COBBA000039	IC	1	
IC510	C0DBAZG00034	IC	1	
IC511-13	C0DAEMZ00001	IC	3	
IC520	C9ZB00000561	IC	1	
L403	EXCELSA35	BEAD CHOKE	1	
L404,05	G0B123K00004	CHOKE COIL	2	△
L406	J0JCC0000004	CHIP INDUCTOR	1	
L410	G0B353D00002	CHOKE COIL	1	△
L511	G0A470ZA0035	CHOKE COIL	1	
L512	G0C4R7JA0021	PEAKING COIL	1	
L514	G0A100GA0013	CHOKE COIL	1	
L515	J0JKB0000037	FLAT CORE	1	
L518	J0JCC0000004	CHIP INDUCTOR	1	
P2	K1KA02A00626	2P CONNECTOR	1	
P5	K1KB23A00004	23P CONNECTOR	1	
P9	K1KA03A00537	3P CONNECTOR	1	
P11	K1KA02A00626	2P CONNECTOR	1	
P12	K1KA08A00514	8P CONNECTOR	1	
P25	K1KA13AA0194	13P CONNECTOR	1	
PMM1	TMME047	CLAMPER	1	
PMM2,M3	TMM7464-2	CLAMPER	2	
PMM5	TMM7464-2	CLAMPER	1	
PMM6-M8	TMME260	CLAMPER	3	
PR401	K5Y502BA0001	FUSE	1	△
PR402	ERBSE0R50U	FUSE	1	△
PR501	ERBSE0R50U	FUSE	1	△
PR505	ERBSE5R00U	FUSE	1	△
PR509	ERBSE0R50U	FUSE	1	△
PR601	K5G312B00012	FUSE	1	△
Q401	B1CHND000004	TRANSISTOR	1	
Q402	B1CBGD000001	FET	1	
Q404	B1BCCF000022	TRANSISTOR	1	
Q406	B1DEHQ000014	TRANSISTOR	1	△
Q407	B1HFCFA00021	TRANSISTOR	1	
Q408,09	B1DHCD000034	TRANSISTOR	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
Q410	2SD1819ARL	TRANSISTOR	1	
Q411	B1HFCFA00021	TRANSISTOR	1	
Q412,13	B1DEGQ000070	TRANSISTOR	2	△
Q420	2SD1819ARL	TRANSISTOR	1	
Q422	B1CBGD000001	FET	1	
Q501,02	2SD1820A0L	TRANSISTOR	2	
Q507	B1DAGQ000013	TRANSISTOR	1	
Q508	B1HBCFA00033	TRANSISTOR	1	
Q509	B1HDCFA00001	TRANSISTOR	1	
Q510	B1DFDD000019	TRANSISTOR	1	
Q517	B1HBCFA00033	TRANSISTOR	1	
Q520	B1HBCFA00033	TRANSISTOR	1	
Q521	B1CBGD000001	FET	1	
Q524	B1CFGF000008	TRANSISTOR	1	
Q525	B1CBGD000001	FET	1	
Q527	B1CERM000012	FET	1	
Q530	B1ADCF000111	TRANSISTOR	1	
Q535	2SD1819ARL	TRANSISTOR	1	
Q537	B1DFDD000019	TRANSISTOR	1	
Q538	B1CBGD000001	FET	1	
Q540	B1DFDD000019	TRANSISTOR	1	
Q541	B1CBGD000001	FET	1	
Q553	2SD1819ARL	TRANSISTOR	1	
Q554	B1CHND000004	TRANSISTOR	1	
Q555,56	B1CFRD000018	FET	2	
Q563	2SD1819ARL	TRANSISTOR	1	
Q564,65	B1ADCF000111	TRANSISTOR	2	
Q566	2SD1819ARL	TRANSISTOR	1	
Q569	B1CBGD000001	FET	1	
R401	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R402	ERJ6GEYG821	M 820 OHM, J, 1/10W	1	
R403	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R404	ERJ6GEYG153	M 15KOHM, J, 1/10W	1	
R405	D0B1825JA033	M1.22MOHM, J, 0.05 W	1	△
R406	ERX12SJ4R7	M 4.7 OHM, J, 1/2W	1	
R407	D1AB2203A023	CHIP RESISTOR	1	
R408	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R409	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R410	D1AB2203A023	CHIP RESISTOR	1	
R411	ERF5TJ100	W 10 OHM, J, 5W	1	△
R414	ERJ8GEYJ153	M 15KOHM, J, 1/8W	1	
R415	D1AB2203A023	CHIP RESISTOR	1	
R417	D1AB4303A023	CHIP RESISTOR	1	
R418	ERJ6GEYJ6R8V	M 6.8 OHM, J, 1/10W	1	
R419	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R421	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R422	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R423	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R424	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R425	ERJ6ENF9101	M 18KOHM, 1/10W	1	
R426	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R428	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R429	ERJ6GEYJ4R7	M 4.7 OHM, J, 1/10W	1	
R430	D1AB4303A023	CHIP RESISTOR	1	
R431	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R432	D1AB4303A023	CHIP RESISTOR	1	
R433	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R436	ERJ8GEYJ153	M 15KOHM, J, 1/8W	1	
R437	ERJ6GEYG183	M 18KOHM, J, 1/10W	1	
R438	ERJ6GEYG331	M 330 OHM, G, 1/10W	1	
R439	ERG12SJ120	M 12 OHM, J, 1/2W	1	
R440	ERJ8GEYJ474	M 470KOHM, J, 1/8W	1	
R441,42	D1AB6803A023	CHIP RESISTOR	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R443	EVMAASA00B23	CONTROL 2KOHMB	1	
R444	ERJ6GEYF123	M 12KOHM, J, 1/10W	1	
R445	D1AB6803A023	CHIP RESISTOR	1	
R448, 49	D0XGR12J0001	M 0.12OHM, J, 5W	2	
R450	ERJ6GEYJ4R7	M 4.7 OHM, J, 1/10W	1	
R451	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R452	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R454	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R455	ERJ6GEYF123	M 12KOHM, J, 1/10W	1	
R456	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R458	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R459	ERJ6ENF5602	M 56KOHM, 1/10W	1	
R460	ERDS2TC0	C 0 OHM, 1/4W	1	
R461	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R463	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R464	ERJ6ENF3302	M 33KOHM, 1/10W	1	
R467	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R468, 69	ERX12SJ1R0	M 0.1 OHM, J, 1/2W	2	
R471	ERJ8GEYJ332	M 3.3KOHM, J, 1/8W	1	
R472-74	D1AB5603A023	CHIP RESISTOR	3	
R476, 77	ERJ14YJ181	M 181 OHM, J, 1/4W	2	
R478	ERJ8GEYJ220	M 22 OHM, J, 1/8W	1	
R482	ERJ8GEYJ220	M 22 OHM, J, 1/8W	1	
R483	D0BF334JA030	CHIP RESISTOR	1	△
R484	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R485	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R488	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R490	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R491	ERJ6GEYG821	M 820 OHM, J, 1/10W	1	
R493	ERG12SJ120	M 12 OHM, J, 1/2W	1	
R498	ERG3SJ101	M 100 OHM, J, 3W	1	
R500	ERJ6GEYJ224	M 220KOHM, J, 1/10W	1	
R501	ERJ6GEYG154	M 150KOHM, J, 1/10W	1	
R502, 03	ERJ6GEYJ224	M 220KOHM, J, 1/10W	2	
R505	ERJ8GEYJ330	M 33 OHM, J, 1/8W	1	
R507	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R508	ERJ6GEYG182	M 1.8KOHM, J, 1/10W	1	
R510	ERJ8GEY0R00	M 0 OHM, 1/8W	1	
R512	ERJ6GEYG823	M 82KOHM, J, 1/10W	1	
R513	ERJ6GEYG332	M 3.3KOHM, J, 1/10W	1	
R514	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R518	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R519	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R520	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R523	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R524	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R526, 27	ERJ6ENF1803	M 180KOHM, 1/10W	2	
R528	ERJ6GEYJ4R7	M 4.7 OHM, J, 1/10W	1	
R529	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R530, 31	ERJ6RBD333	M 33KOHM, J, 1/10W	2	
R532	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R533	ERJ6ENF1803	M 180KOHM, 1/10W	1	
R534	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R537	ERJ6ENF1003	M 100KOHM, 1/10W	1	
R538	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R539	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R540, 41	ERJ6GEYG105	M 1MOHM, J, 1/10W	2	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R542	ER0S2CKF2202	M 22KOHM, F, 1/4W	1	
R543	ERJ6ENF3902	M 39KOHM, 1/10W	1	
R545	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R546	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R547	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R550	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R551	ERJ6GEYF151	M 150 OHM, F, 1/10W	1	
R553	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R555	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R556	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R557, 58	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R559	ERJ6ENF8201	M 8.2KOHM, 1/10W	1	
R560	ERJ6ENF9101	M 9.1KOHM, 1/10W	1	
R561	ERJ6ENF5101	M 5.1KOHM, 1/10W	1	
R562	ERJ6ENF4701	M 4.7KOHM, 1/10W	1	
R563	ERJ6GEYJ2R2	M 2.2 OHM, J, 1/10W	1	
R564	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R565, 66	ERJ6GEYG105	M 1MOHM, J, 1/10W	2	
R567, 68	ERJ8GEYJ105	M 1MOHM, J, 1/8W	2	
R569	ERJ6ENF3302	M 33KOHM, 1/10W	1	
R570	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R571	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R572, 73	ERJ6GEYG102	M 1KOHM, J, 1/10W	2	
R574	ERJ6GEYG331	M 330 OHM, G, 1/10W	1	
R576	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R579	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R581	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R582	ERJ6ENF1002	M 10KOHM, 1/10W	1	
R584	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R585	ERJ6GEYF333	M 33KOHM, J, 1/10W	1	
R586	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R587	ERJ8RSJR16V	M 16 OHM, 1/8W	1	
R592	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R593	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R594	ERJ6GEYF151	M 150 OHM, F, 1/10W	1	
R595	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R596	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R597, 98	ERJ6ENF3302	M 33KOHM, 1/10W	2	
R599, 00	ERJ8ENF3900	M 390 OHM, 1/8W	2	
R601	ERJ6GEYJ471	M 470 OHM, J, 1/10W	1	
R603	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R604	ERJ6RBD303	M 30KOHM, J, 1/10W	1	
R605	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R606	ERJ6ENF1201	M 1.2KOHM, 1/10W	1	
R607	ERJ6ENF2202	M 2.2KOHM, 1/10W	1	
R608	ERJ8GEYJ332	M 3.3KOHM, J, 1/8W	1	
R609	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R610	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R611	ERDS2FJ101	C 100 OHM, J, 1/4W	1	
R612	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	1	
R613	ERJ6ENF2402	M 24KOHM, 1/10W	1	
R614	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R616, 17	ERJ6GEYJ223	M 22KOHM, J, 1/10W	2	
R618	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R619	ERJ8RQFR39	M 0.39OHM, J, 1/8W	1	
R620	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R622	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R624	ERX2SJR22P	M0.22 OHM, J, 2W	1	
R625	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R626	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R627	ERJ6GEYJ752	M 7.5KOHM, J, 1/10W	1	
R628	EVMAASA00B33	CONTROL 3KOHMB	1	
R629	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R630	ERJ6GEYF472	M 4.7KOHM, F, 1/10W	1	
R631	ERJ8GEYJ333	M 33KOHM, J, 1/8W	1	
R632	ERJ6GEYG221	M 220 OHM, J, 1/10W	1	
R633	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R634	ERJ8RQFR39V	M 0.39OHM, J, 1/8W	1	PAVCCZ P-BOARD PART
R635	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R636	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R637	ERJ8RQFR39	M 0.39OHM, J, 1/8W	1	
R639, 40	ERJ8RQFR39	M 0.39OHM, J, 1/8W	2	
R641	ERJ6GEYF473	M 47KOHM, J, 1/10W	1	
R642-44	ERJ8RQFR39	M 0.39OHM, J, 1/8W	3	
R645	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	1	
R646, 47	ERJ14YJ330	M 33 OHM, J, 1/4W	2	
R648	ERJ6ENF1603	M 160KOHM, 1/10W	1	
R649	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R650	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R651	ERJ6ENF1002	M 10KOHM, 1/10W	1	
R652	ERJ6GEYF123	M 12KOHM, J, 1/10W	1	
R653	ERJ6ENF3302	M 33KOHM, 1/10W	1	
R654	ERJ6GEYJ223	M 22KOHM, J, 1/10W	1	
R655	ERJ8RSJR16V	M 16 OHM, 1/8W	1	
R656	ERJ6ENF1803	M 180KOHM, 1/10W	1	
R657	ERJ6GEYF561	M 560 OHM, F, 1/10W	1	
R658	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R659	ERJ6RBD303	M 30KOHM, J, 1/10W	1	
R660	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R661	EVMAASA00B53	CONTROL 5KOHMB	1	
R662	ERJ6ENF1503	M 150KOHM, 1/10W	1	
R664	ERJ6ENF9101	M 9.1KOHM, 1/10W	1	
R665	EVMAASA00B23	CONTROL 2KOHMB	1	
R669	ERJ6ENF1503	M 150KOHM, 1/10W	1	
R670	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R671	ERJ6RBD751	M 750 OHM, J, 1/10W	1	
R672, 73	ERJ6GEYG102	M 1KOHM, J, 1/10W	2	
R674	ERJ8GEYJ333	M 33KOHM, J, 1/8W	1	
R675	ERJ6ENF2202	M 2.2KOHM, 1/10W	1	
R676	ERJ8GEYJ333	M 33KOHM, J, 1/8W	1	
R677	ERJ6GEYJ474	M 470KOHM, J, 1/10W	1	
R678-80	ERJ8RSJR16V	M 16 OHM, 1/8W	3	
R682	ERJ6ENF2002	M 20KOHM, 1/10W	1	
R683	ERJ14YJ330	M 33 OHM, J, 1/4W	1	
R684, 85	ERJ6GEYG102	M 1KOHM, J, 1/10W	2	
R686	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R687	ERJ6GEYG104	M 100KOHM, J, 1/10W	1	
R688	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R689	ERJ8GEYJ472	M 4.7KOHM, J, 1/8W	1	
R690	ERJ6GEYJ47R	M 4.7 OHM, J, 1/10W	1	
R691	ERJ6GEYG105	M 1MOHM, J, 1/10W	1	
R693	ERJ6GEYJ100V	M 10 OHM, J, 1/10W	1	
R695	ERJ6RBD123V	M 12KOHM, 1/10W	1	
R696	ERJ6GEYJ100V	M 10 OHM, J, 1/10W	1	
R697	ERJ6GEYJ47R	M 4.7 OHM, J, 1/10W	1	
R698	ERJ8RSJR16V	M 16 OHM, 1/8W	1	

Ref. No.	Part No.	Part Name & Description	Pcs	Remarks
R699	ERJ8GEYJ105	M 1MOHM, J, 1/8W	1	
R700, 01	ERJ6ENF1503	M 150KOHM, 1/10W	2	
R702	ERJ6ENF1102	M 11KOHM, 1/10W	1	
R707, 08	ERJ6GEYG102	M 1KOHM, J, 1/10W	2	
R709, 10	ERJ6GEYJ101V	M 100 OHM, J, 1/10W	2	
R711, 12	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	2	
R713	ERJ6GEYG152	M 1.5KOHM, J, 1/10W	1	
R714	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R715	ERJ6ENF3301	M 3.3KOHM, 1/10W	1	
R716	ERJ6GEYOR00V	M 0 OHM, 1/10W	1	
R717	ERJ6GEYG122	M 1.2KOHM, J, 1/10W	1	
R718	ERJ6GEYG103	M 10KOHM, J, 1/10W	1	
R719	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
R720	ERJ6GEYG152	M 1.5KOHM, J, 1/10W	1	
R721	ERJ6GEYOR00V	M 0 OHM, 1/10W	1	
R722-24	ERJ6GEYG102	M 1KOHM, J, 1/10W	3	
R726, 27	ERJ6GEYG222	M 2.2KOHM, J, 1/10W	2	
R729	ERJ6GEYOR00V	M 0 OHM, 1/10W	1	
R730-38	ERJ8GEYJ105	M 1MOHM, J, 1/8W	9	
R739	ERJ6ENF1003	M 100KOHM, 1/10W	1	
R740	ERJ6GEYJ243	M 24KOHM, J, 1/10W	1	
R741	ERJ8GEYJ205	M 2MOHM, J, 1/8W	1	
R742	ERJ6GEYG102	M 1KOHM, J, 1/10W	1	
RL401-03	K6B1CGA00055	REALY	3	△
S401, 02	J0LT00000009	SWITCH	2	△
T401	G4D4A0000122	SWITCHING TRANS	1	
T402	G4D1A0000128	SWITCHING TRANS	1	△
T404	ETS42LB11GAD	SWITCHING TRANS	1	△
T410	G4D2A0000283	SWITCHING TRANS	1	△
T601	G4D2A0000284	SWITCHING TRANS	1	
W13	ERJ6GEYOR00V	M 0 OHM, 1/10W	1	
W46	ERJ6GEYOR00V	M 0 OHM, 1/10W	1	
X501	H2B400400021	CRYSTAL	1	
Z1-Z3	K4ZZ01000206	TERMINAL	3	
ZN401, 02	D4EAD6210001	VARISTOR	2	△
ZN403	ERZVGAD681T2	VARISTOR	1	△
ZN404.405	ERZVA7D511	VARISTOR	2	△