

Service  
Service  
Service



Philips Consumer Lifestyle

# Service Manual

## PRODUCT INFORMATION

- This product meets the requirements regarding interference suppression on radio and TV.
- After the product has been repaired, it should function properly and has to meet the safety requirements as officially laid down at this moment.

## ASSEMBLY & DISASSEMBLY ADVICE

- To remove the back plate assy, first remove the rubber screw hole cover and the screw in the back plate.
- To open the cleaner, first remove the 6 screws and then gently open it up by using a screwdriver between both body sides at the front of the cleaner to unsnap both parts from each other.

## REPAIR INSTRUCTIONS

- No specific issues

## OPTIONAL (accessories)

- No specific issues

## TECHNICAL INFORMATION

- Adapter AC / DC : 100 - 240 V  
21V DC - 200 mA
- Rechargeable batteries : 12 x NiMH
- Run time : 11 min.
- Charging time : 16-18 hours
- Charge indicator : LED
- Charging base : Standing, also wall mountable, incl. accessory storage
- Air flow system : Cyclonic action
- Accessories : Telescopic stick, Floor nozzle, crevice and brush
- Application environment : Dry
- Filter : 2-stage type, HEPA
- Dust capacity : 450 ml

Pos	Service code	Description	
1	4222 459 45531	Accessory holder	Titanium Grey
2	4222 459 45513	Wall mount	Titanium Grey
3	4222 459 45514	Charging base assy	Titanium Grey
4	4222 459 45527	Nozzle release button	Deep red
5	4222 459 45515	Inner filter HEPA	
6	4222 459 45516	Mesh filter assy	Titanium Grey
7	4222 459 45528	Dust case assy	Transp. Fresh red
8	4222 459 45518	Stream control assy	Titanium Grey
9	4222 459 45519	Nose piece	Titanium Grey
10	4222 459 45529	Floor nozzle	Titanium Grey
11	4222 459 45521	Crevice tool	Titanium Grey
12	4222 459 45522	Small brush	Titanium Grey
13	4222 459 45530	Handle assy	Titanium Grey
14	4222 459 45525	Switch cover	Warm Titanium
15	4222 459 45526	Back plate assy	Warm Titanium
16	4222 459 45541	Handle hold tube assy	
17	4322 004 20130	Filter brush	
18	4222 459 45536	Charger WE	
	4222 459 45537	Charger UK/HK	
	4222 459 45538	Charger Korea	
	4222 459 45539	Charger Taiwan	
	4222 459 45540	Charger PRC	
	4222 459 54651	Adaptor SSC 4W (21 V / 4 W / 190 mA)	

## Electrical diagram



