

PARTS LIST

PARTS REPLACEMENT

Replacement parts which have these special safety characteristics identified in this manual; electrical components having such features are identified by  and shaded areas in the Replacement Parts Lists and Schematic Diagrams. The use of a substitute replacement part which does not have the same safety characteristic as the factory recommended replacement parts shown in this service manual may create shock, fire or other hazards.

"HOW TO ORDER REPLACEMENT PARTS"

To have your order filled promptly and correctly, please furnish the following informations.

- | | |
|-----------------|----------------|
| 1. MODEL NUMBER | 2. REF. NO. |
| 3. PART NO. | 4. DESCRIPTION |

★ MARK: SPARE PARTS-DELIVERY SECTION

Ref. No.	Part No.	★	Description	Code
----------	----------	---	-------------	------

PRINTED WIRING BOARD ASSEMBLIES

(NOT REPLACEMENT ITEM)

DUNTKC856FM01	—	INVERTER Unit	—
DUNTKC857WE04	—	SUB Unit	—
DUNTKC858WE04	—	OPERATION Unit	—
DUNTKC859WE04	—	R/C, LED Unit	—
DUNTKC860FM03	—	MAIN Unit	—

LCD PANEL

NOTE: THE PARTS HERE SHOWN ARE SUPPLIED AS AN ASSEMBLY BUT NOT INDEPENDENTLY.

RLCDA025WJZZ	J	20" LCD Panel Unit	DB
--------------	---	--------------------	----

DUNTKC856FM01

INVERTER UNIT

TRANSISTORS

Q6700	VS2SC5886A+-1Y	2SC5886A	
Q6701	VS2SC5886A+-1Y	2SC5886A	
Q6702	VS2SA1530AR-1Y	J 2SA1530AR	AB
Q6703	VS2SC5886A+-1Y	2SC5886A	
Q6704	VS2SC5886A+-1Y	2SC5886A	
Q6705	VS2SA1530AR-1Y	J 2SA1530AR	AB
Q6706	VSUPA606T/-1Y	J UPA606T	AD
Q6707	VS2SC5886A+-1Y	2SC5886A	
Q6708	VS2SC5886A+-1Y	2SC5886A	
Q6709	VS2SA1530AR-1Y	J 2SA1530AR	AB
Q6710	VS2SC5886A+-1Y	2SC5886A	
Q6711	VS2SC5886A+-1Y	2SC5886A	
Q6712	VS2SA1530AR-1Y	J 2SA1530AR	AB
Q6713	VSUPA606T/-1Y	J UPA606T	AD
Q6714	VS2SC5886A+-1Y	2SC5886A	
Q6715	VS2SC5886A+-1Y	2SC5886A	
Q6716	VS2SA1530AR-1Y	J 2SA1530AR	AB
Q6717	VSUPA606T/-1Y	J UPA606T	AD

DIODES

D6700	VHDDAN202K/-1Y	J Diode	AB
D6701	VHDDAN202K/-1Y	J Diode	AB

Ref. No.	Part No.	★	Description	Code
D6702	VHDMA157A/-1Y	J	Diode	AC
D6703	VHDMA157A/-1Y	J	Diode	AC
D6704	VHDDAN202K/-1Y	J	Diode	AB
D6705	VHDDAN202K/-1Y	J	Diode	AB
D6707	VHDMA157A/-1Y	J	Diode	AC
D6708	VHDMA157A/-1Y	J	Diode	AC
D6709	VHDDAN202K/-1Y	J	Diode	AB
D6710	VHDMA157A/-1Y	J	Diode	AC
D6711	VHDDAN202K/-1Y	J	Diode	AB

COILS

L6700	RCiLPA373WJZZ	Coil
L6701	RCiLPA373WJZZ	Coil
L6702	RCiLPA373WJZZ	Coil
L6703	RCiLPA373WJZZ	Coil
L6704	RCiLPA373WJZZ	Coil

TRANSFORMERS

△ T6700	RTRNZA075WJZZ	Transformer
△ T6701	RTRNZA075WJZZ	Transformer
△ T6702	RTRNZA075WJZZ	Transformer
△ T6703	RTRNZA075WJZZ	Transformer
△ T6704	RTRNZA075WJZZ	Transformer

CAPACITORS

C6700	RC-FZA116WJZZ	0.27	250V	Film	
C6703	VCKYCY1CB333KY	J 0.033	16V	Ceramic	AA
C6704	RC-EZA465WJZZ	1000	16V	Electrolytic	
C6705	RC-FZA116WJZZ	0.27	250V	Film	
C6708	VCKYCY1CB333KY	J 0.033	16V	Ceramic	AA
C6709	RC-EZA465WJZZ	1000	16V	Electrolytic	
C6710	RC-KZ0072TAZZY	J 1	25V	Ceramic	AC
C6711	RC-KZ0072TAZZY	J 1	25V	Ceramic	AC
C6712	RC-FZA116WJZZ	0.27	250V	Film	
C6715	VCKYCY1CB333KY	J 0.033	16V	Ceramic	AA
C6716	RC-EZA465WJZZ	1000	16V	Electrolytic	
C6717	RC-FZA116WJZZ	0.27	250V	Film	
C6720	VCKYCY1CB333KY	J 0.033	16V	Ceramic	AA
C6721	RC-EZA465WJZZ	1000	16V	Electrolytic	
C6722	RC-KZ0072TAZZY	J 1	25V	Ceramic	AC
C6723	RC-KZ0072TAZZY	J 1	25V	Ceramic	AC
C6724	RC-FZA116WJZZ	0.27	250V	Film	
C6727	VCKYCY1CB333KY	J 0.033	16V	Ceramic	AA
C6728	RC-EZA465WJZZ	1000	16V	Electrolytic	
C6729	RC-KZ0072TAZZY	J 1	25V	Ceramic	AC

RESISTORS

R6700	VRD-RA2EE182JY	J 1.8k	1/4W	Carbon	AA
R6701	VRS-TW2ED122JY	J 1.2k	1/4W	Metal Oxide	AA
R6702	VRS-CY1JF103JY	J 10k	1/16W	Metal Oxide	AA
R6703	VRD-RA2BE333JY	J 33k	1/8W	Carbon	AA
R6704	VRD-RA2EE182JY	J 1.8k	1/4W	Carbon	AA
R6705	VRS-TW2ED122JY	J 1.2k	1/4W	Metal Oxide	AA
R6706	VRS-CY1JF103JY	J 10k	1/16W	Metal Oxide	AA
R6707	VRS-CY1JF333JY	J 33k	1/16W	Metal Oxide	AA
R6708	VRS-CY1JF471JY	J 470	1/16W	Metal Oxide	AA
R6709	VRS-CY1JF824JY	J 820k	1/16W	Metal Oxide	AA
R6710	VRS-CY1JF471JY	J 470	1/16W	Metal Oxide	AA
R6711	VRS-CY1JF824JY	J 820k	1/16W	Metal Oxide	AA
R6712	VRS-CY1JF562JY	J 5.6k	1/16W	Metal Oxide	AA
R6713	VRS-CY1JF562JY	J 5.6k	1/16W	Metal Oxide	AA
R6714	VRD-RA2EE182JY	J 1.8k	1/4W	Carbon	AA
R6715	VRS-TW2ED122JY	J 1.2k	1/4W	Metal Oxide	AA
R6716	VRS-CY1JF103JY	J 10k	1/16W	Metal Oxide	AA
R6717	VRS-CY1JF333JY	J 33k	1/16W	Metal Oxide	AA
R6718	VRD-RA2EE182JY	J 1.8k	1/4W	Carbon	AA
R6719	VRS-TW2ED122JY	J 1.2k	1/4W	Metal Oxide	AA
R6720	VRS-CY1JF103JY	J 10k	1/16W	Metal Oxide	AA
R6721	VRS-CY1JF333JY	J 33k	1/16W	Metal Oxide	AA
R6722	VRS-CY1JF471JY	J 470	1/16W	Metal Oxide	AA
R6723	VRS-CY1JF824JY	J 820k	1/16W	Metal Oxide	AA
R6724	VRS-CY1JF471JY	J 470	1/16W	Metal Oxide	AA
R6725	VRS-CY1JF824JY	J 820k	1/16W	Metal Oxide	AA
R6726	VRD-RA2BE562JY	J 5.6k	1/8W	Carbon	AA
R6727	VRD-RA2BE562JY	J 5.6k	1/8W	Carbon	AA

Ref. No.	Part No.	★	Description	Code
DUNTKC856FM01				
INVERTER UNIT (Continued)				
R6728	VRD-RA2EE182JY	J	1.8k 1/4W Carbon	AA
R6729	VRS-TW2ED122JY	J	1.2k 1/4W Metal Oxide	AA
R6730	VRS-CY1JF103JY	J	10k 1/16W Metal Oxide	AA
R6731	VRS-CY1JF333JY	J	33k 1/16W Metal Oxide	AA
R6732	VRS-CY1JF471JY	J	470 1/16W Metal Oxide	AA
R6733	VRS-CY1JF824JY	J	820k 1/16W Metal Oxide	AA
R6734	VRS-CY1JF562JY	J	5.6k 1/16W Metal Oxide	AA
R6743	VRS-CY1JF563JY	J	56k 1/16W Metal Oxide	AA
R6744	VRS-TW2ED561JY	J	560 1/4W Metal Oxide	AA
R6745	VRS-TW2ED561JY	J	560 1/4W Metal Oxide	AA
R6746	VRS-TW2ED561JY	J	560 1/4W Metal Oxide	AA
R6747	VRS-TW2ED561JY	J	560 1/4W Metal Oxide	AA
R6748	VRS-TW2ED561JY	J	560 1/4W Metal Oxide	AA

MISCELLANEOUS PARTS

△ F6700	QFS-ZA002WJZZ	J	Fuse, 1.25A/250V	AD
△ F6701	QFS-ZA002WJZZ	J	Fuse, 1.25A/250V	AD
△ F6702	QFS-ZA002WJZZ	J	Fuse, 1.25A/250V	AD
△ F6703	QFS-ZA002WJZZ	J	Fuse, 1.25A/250V	AD
△ F6704	QFS-ZA002WJZZ	J	Fuse, 1.25A/250V	AD
P6700	QPLGNA391WJZZ		Plug, 2-pin	
P6701	QPLGNA391WJZZ		Plug, 2-pin	
P6702	QPLGNA391WJZZ		Plug, 2-pin	
P6703	QPLGNA391WJZZ		Plug, 2-pin	
P6704	QPLGNA391WJZZ		Plug, 2-pin	
SC6701	QSOCZ1338CEZZ	J	Socket, 13-pin	AD

Ref. No.	Part No.	★	Description	Code
DUNTKC857WE04				
SUB UNIT				
INTEGRATED CIRCUITS				
IC3301	VHiAN17821A-1	J	AN17821A	AH
IC7701	VHiSTRW67652E		I.C.	
IC7702	RH-FXA003WJZZ	J	PC123Y82	AD
IC7703	RH-FXA003WJZZ	J	PC123Y82	AD
IC7704	VHiSE005N++-F		I.C.	
IC7705	VHiKA7809AP-1	J	KIA7809API	AE
IC7706	VHiPQ050ES1-1+		PQ050ES1MXP	

TRANSISTORS

Q3300	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q3305	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q3600	VSKRC102S/-1Y	J	KRC102S	AA
Q3601	VSKRC102S/-1Y	J	KRC102S	AA
Q3901	VS2SA1530AR-1Y	J	2SA1530AR	AB
Q3902	VS2SA1530AR-1Y	J	2SA1530AR	AB
Q3903	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q3904	VS2SD1306-E-1Y	J	2SD1306-E	AC
Q3905	VS2SD1306-E-1Y	J	2SD1306-E	AC
Q3906	VS2SD1306-E-1Y	J	2SD1306-E	AC
Q3907	VS2SD1306-E-1Y	J	2SD1306-E	AC
Q3908	VS2SA1530AR-1Y	J	2SA1530AR	AB
Q3909	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q7701	VS2SA1013//1E+	J	2SA1013	AD
Q7702	VSKRC104S/-1Y	J	KRC104S	AA
Q7703	VS2SB1443TV1E+	J	2SB1443TV	AE
Q7704	VS2SB1443TV1E+	J	2SB1443TV	AE
Q7706	VSKRC101S/-1Y		KRC101S	
Q7707	VSKRC104S/-1Y	J	KRC104S	AA
Q7708	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q7710	VSKRA102S/-1Y	J	KRA102S	AA
Q7711	VS2SB1443TV1E+	J	2SB1443TV	AE
Q7712	VSKRC104S/-1Y	J	KRC104S	AA
Q7713	VS2SA1530AR-1Y	J	2SA1530AR	AB
Q7714	VSKRC102S/-1Y	J	KRA102S	AA

DIODES

D3300	VHDDAN202K/-1Y	J	Diode	AB
D3301	RH-EX0621GEZZY	J	Zener Diode	AB
D3604	RH-EX0652GEZZY	J	Zener Diode, 18V	AB
D3605	RH-EX0652GEZZY	J	Zener Diode, 18V	AB
D3901	VHDDAN202K/-1Y	J	Diode	AB
D3903	VHD1SS119//1Y	J	Diode	AA
D3908	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D3911	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D3912	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D3913	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D3914	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D3915	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D3916	RH-EX0612GEZZY	J	Zener Diode	AB
D5000	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D5001	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D5002	RH-EX0630GEZZY	J	Zener Diode, 9.1V	AA
D7701	RH-DX0476CEZZ	J	Diode	AG
D7703	VHDSF30JC6+1E		Diode	
D7705	RH-DX0490CEZZY	J	Diode	AC
D7706	RH-DX0490CEZZY	J	Diode	AC
D7707	RH-DX0321CEZZY	J	Diode	AC
D7708	RH-DX0066GEZZY	J	Diode	AC
D7709	VHD1SS244//1Y	J	Diode	AB
D7710	VHD1SS244//1Y	J	Diode	AB
D7711	VHD1SS244//1Y	J	Diode	AB
D7713	VHDSF30JC6+1E		Diode	
D7714	RH-DXA059WJZZ		Diode	
D7715	RH-DX0461CEZZ	J	Diode	AG
D7716	VHD10ELS4//1Y	J	Diode	AD
D7717	VHD10ELS4//1Y	J	Diode	AD
D7721	VHD1SS119//1Y	J	Diode	AA
D7722	VHD1SS119//1Y	J	Diode	AA
D7723	VHD1SS119//1Y	J	Diode	AA
D7725	RH-EX0618GEZZY	J	Zener Diode, 6.2V	AB

Ref. No.	Part No.	★	Description	Code	Ref. No.	Part No.	★	Description	Code
DUNTKC857WE04					C7728	RC-EZA153WJZZ+	470	10V Electrolytic	
SUB UNIT (Continued)					C7729	RC-EZA172WJZZ	J 1000	25V Electrolytic	AE
D7729	RH-EX0640GEZZY	J	Zener Diode	AA	C7731	VCEA4A1CN226M+	22	16V Electrolytic	
VA7701	RH-VXA022WJZZ		Varistor		C7732	VCEA4A1AN227M+	220	10V Electrolytic	
COILS					C7733	VCEA4A1CN226M+	22	16V Electrolytic	
L7701	RCiLFA161WJZZ		Coil		C7736	VCEA0A1HW227M+	J 220	50V Electrolytic	AB
L7702	RCiLFA162WJZZ		Coil		C7737	VCEA4A1CN107M+	J 100	16V Electrolytic	AB
L7703	RCiLP0175CEZZ+	J	Coil	AD	C7738	VCEA4A1CN107M+	J 100	16V Electrolytic	AB
L7704	RCiLPA308WJZZ		Coil		C7739	VCEA4A1HN225M+	J 2.2	50V Electrolytic	AC
TRANSFORMER					C7740	VCQYTA1HM104J+	J 0.1	50V Mylar	AB
T7701	RTRNWA152WJZZ		Transformer		C7741	VCEA0A1EW227M+	J 220	25V Electrolytic	AB
CAPACITORS					C7742	VCEA0A1AW227M+	J 220	10V Electrolytic	AB
C3305	VCEA0A1CW108M+	J 1000	16V Electrolytic	AD	C7743	VCEA4A1CN106M+	10	16V Electrolytic	
C3306	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	C7744	VCEA4A1CN106M+	10	16V Electrolytic	
C3307	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	C7745	VCEA0A1CW476M+	J 47	16V Electrolytic	AB
C3308	VCEAEA1HW105M+	J 1	50V Electrolytic	AB	RJ1	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C3309	VCEAEA1HW105M+	J 1	50V Electrolytic	AB	RJ2	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C3310	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	RJ3	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C3313	VCEAEA1HW225M+	J 2.2	50V Electrolytic	AB	RJ5	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C3314	VCEAEA1HW225M+	J 2.2	50V Electrolytic	AB	R3302	VRN-VV3DB1ROJ	J 1	2W Metal Film	AB
C3317	VCEAEA1HB102KY	J 2.2	50V Electrolytic	AB	R3304	VRS-CY1JF153JY	J 15k	1/16W Metal Oxide	AA
C3318	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	R3306	VRS-CY1JF223JY	J 22k	1/16W Metal Oxide	AA
C3319	VCEAEA1CW476M+	J 47	16V Electrolytic	AB	R3307	VRS-CY1JF682JY	J 6.8k	1/16W Metal Oxide	AA
C3320	VCEAEA1CW476M+	J 47	16V Electrolytic	AB	R3311	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3321	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	R3312	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3322	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	R3313	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3323	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	R3315	VRS-CY1JF681JY	J 680	1/16W Metal Oxide	AA
C3324	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	R3316	VRS-CY1JF681JY	J 680	1/16W Metal Oxide	AA
C3604	VCKYCY1HB332KY	J 3300p	50V Ceramic	AA	R3317	VRS-CY1JF124JY	J 120k	1/16W Metal Oxide	AA
C3605	VCKYCY1HB332KY	J 3300p	50V Ceramic	AA	R3321	VRD-RA2BE272JY	J 2.7k	1/8W Carbon	AA
C3901	VCEAEA0JW107M+	J 100	6.3V Electrolytic	AB	R3322	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
C3902	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3323	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
C3903	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3324	VRS-CY1JF124JY	J 120k	1/16W Metal Oxide	AA
C3904	VCEAEA1CW476M+	J 47	16V Electrolytic	AB	R3325	VRD-RA2BE683JY	J 68k	1/8W Carbon	AA
C3905	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	R3326	VRD-RM2HD220JY	J 22	1/2W Carbon	AA
C3906	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	R3327	VRD-RM2HD220JY	J 22	1/2W Carbon	AA
C3907	VCEAEA0JW476M+	J 47	6.3V Electrolytic	AB	R3607	VRS-CY1JF153JY	J 15k	1/16W Metal Oxide	AA
C3908	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3608	VRS-CY1JF153JY	J 15k	1/16W Metal Oxide	AA
C3909	VCCCCY1HH331JY	J 330p	50V Ceramic	AA	R3902	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C3910	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	R3905	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C3911	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	R3906	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3912	VCCCCY1HH331JY	J 330p	50V Ceramic	AA	R3907	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
C3913	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3908	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3914	VCCCCY1HH221JY	J 220p	50V Ceramic	AA	R3909	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3915	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3910	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3916	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3911	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C3917	VCCCCY1HH221JY	J 220p	50V Ceramic	AA	R3912	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
C3918	VCEAEA1CW106M+	J 10	16V Electrolytic	AB	R3913	VRD-RA2BE271JY	J 270	1/8W Carbon	AA
C5001	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3914	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C5002	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	R3915	VRS-CY1JF271JY	J 270	1/16W Metal Oxide	AA
C7701	RC-FZA022WJZZ	J 0.22	275V Film	AD	R3916	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C7702	RC-FZA022WJZZ	J 0.22	275V Film	AD	R3917	VRS-CY1JF823JY	J 82k	1/16W Metal Oxide	AA
C7703	RC-EZA556WJZZ	150	400V Electrolytic		R3918	VRS-CY1JF271JY	J 270	1/16W Metal Oxide	AA
C7704	RC-FZA180WJZZ	0.1	580V Film		R3919	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C7705	RC-KZA305WJZZ	560p	2kV Ceramic		R3920	VRS-CY1JF271JY	J 270	1/16W Metal Oxide	AA
C7706	RC-KZ0105GEZZ	J 2200p	250V Ceramic	AD	R3921	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C7707	RC-KZ0103GEZZ	J 1000p	250V Ceramic	AD	R3922	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
C7708	VCEA4A1CN226M+	22	16V Electrolytic		R3923	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
C7709	VCQYTA1HM152J+	J 1500p	50V Mylar	AA	R3924	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
C7711	VCKYPA1HB471K+	J 470p	50V Ceramic	AA	R3925	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
C7712	VCEA4A1VN476M+	47	35V Electrolytic		R3926	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C7713	VCEA4A1VN106M+	10	35V Electrolytic		R3927	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
C7715	VCQYTA1HM104J+	J 0.1	50V Mylar	AB	R3928	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C7720	RC-EZA155WJZZ	J 2200	10V Electrolytic	AE	R3929	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
C7721	RC-EZA168WJZZ+	220	25V Electrolytic		R3930	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
C7722	RC-EZA172WJZZ	J 1000	25V Electrolytic	AE	R3931	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
C7723	RC-EZA184WJZZ+	100	50V Electrolytic		R3933	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
C7724	VCEA4A1AN108M	J 1000	10V Electrolytic	AD	R3934	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
C7725	RC-EZA173WJZZ	1500	25V Electrolytic		R3935	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
C7727	RC-EZA173WJZZ	1500	25V Electrolytic		R3936	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
					R3937	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
					R3938	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA

Ref. No.	Part No.	★	Description	Code
DUNTKC857WE04				
SUB UNIT (Continued)				
R3939	VRD-RA2BE220JY	J 22	1/8W Carbon	AA
R3940	VRD-RA2BE102JY	J 1k	1/8W Carbon	AA
R3941	VRD-RA2BE750JY	J 75	1/8W Carbon	AA
R3942	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R5000	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
R5001	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
R5005	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
R5008	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R5009	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R5010	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R5012	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R5014	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R5015	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R5016	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
R5017	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
R7702	RR-HZ0014GEZZY	J		AE
R7703	VRN-VV3AB1R0J	J 1	1W Metal Film	AA
R7704	VRN-VV3ABR82J	J 0.82	1W Metal Film	AA
R7705	RR-DZA030WJZZ		180k 2W	
R7706	VRD-RM2HD220JY	J 22	1/2W Carbon	AA
R7707	RR-DZA033WJZZ		180k 3W	
R7708	RR-DZA033WJZZ		180k 3W	
R7709	VRW-KP3HC3R3K	J 3.3	5W Cement	AC
R7710	VRD-RM2HD102JY	J 1k	1/2W Carbon	AA
R7711	VRS-CY1JF222JY	J 2.2k	1/16W Metal Oxide	AA
R7712	VRD-RM2HD220JY	J 22	1/2W Carbon	AA
R7713	VRD-RA2BE562JY	J 5.6k	1/8W Carbon	AA
R7714	VRD-RA2BE102JY	J 1k	1/8W Carbon	AA
R7715	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R7716	VRN-VV3ABR22J	J 0.22	1W Metal Film	AA
R7717	VRN-SV2HC1R0J	J 1	1/2W Metal Film	AA
R7718	VRD-RM2HD221JY	J 220	1/2W Carbon	AA
R7719	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
R7720	VRS-CY1JF271JY	J 270	1/16W Metal Oxide	AA
R7721	VRD-RA2BE102JY	J 1k	1/8W Carbon	AA
R7722	VRN-SV2HC1R0J	J 1	1/2W Metal Film	AA
R7726	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R7728	VRN-RA2BK221FY		220 1/8W Metal Film	
R7729	VRD-RA2BE222JY	J 2.2k	1/8W Carbon	AA
R7730	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R7732	VRD-RM2HD221JY	J 220	1/2W Carbon	AA
R7733	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
R7735	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
R7738	VRS-CY1JF563JY	J 56k	1/16W Metal Oxide	AA
R7739	VRD-RM2HD222JY	J 2.2k	1/2W Carbon	AA
R7740	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
R7741	VRS-CY1JF182JY	J 1.8k	1/16W Metal Oxide	AA
R7742	VRD-RA2BE223JY	J 22k	1/8W Carbon	AA
R7743	VRS-CY1JF563JY	J 56k	1/16W Metal Oxide	AA
R7744	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R7745	VRD-RA2EE102JY	J 1k	1/4W Carbon	AA
R7746	VRS-VV3AB560J	J 56	1W Metal Oxide	AA
R7747	VRD-RA2BE101JY	J 100	1/8W Carbon	AA
R7748	VRD-RA2BE102JY	J 1k	1/8W Carbon	AA
R7749	VRD-RA2BE102JY	J 1k	1/8W Carbon	AA

MISCELLANEOUS PARTS

△ F7701	QFS-C3229CEZZ	J	Fuse, 3.15A/250V	AD
FH7701	QFSHD1017CEZZ+	J	Fuse Holder	AC
FH7702	QFSHD1018CEZZ+	J	Fuse Holder	AC
JB206	RBLN-0090GEZZY	J	Ferrite Bead	AB
JB210	RBLN-0090GEZZY	J	Ferrite Bead	AB
FB7702	RBLN-0020CEZZ	J	Ferrite Bead	AB
FB7704	RBLN-0090GEZZY	J	Ferrite Bead	AB
J3701	QJAKJ0101SEZZ	J	Jack, Headphone	AE
J3901	QJAKFA031WJZZ		Jack, Audio Out (L/R)	
J5000	QSOCD0439CEZZ	J	Socket S-Video	AF
J5001	QJAKGA067WJZZ		Jack, Audio (L/R)/Video	
P3301	QPLGN0442CEZZ	J	Plug, 4-pin (TS)	AB
P3601	QPLGZ1338CEZZ	J	Plug, 13-pin (MF)	AE
P3901	QCNCMA012WJZZ	J	Plug, 15-pin (MB)	AD

Ref. No.	Part No.	★	Description	Code
P3902	QCNCMA250WJZZ		Plug, 23-pin	
P7701	QCNCMA012WJZZ	J	Plug, 15-pin	AD
SC3601	QSOCN0895REZZ	J	Socket, 8-pin	AC
SC3901	QSOCZA056WJZZ		Socket, AV-IN1 (21-pin Euro-SCART)	
CN7701	QSOCMA003WJZZ	J	Socket, 2-pin	AD
RDA3301	PRDARA176WJFW		Heat Sink, for IC3301	
RDA7701	PRDARA158WJFW		Heat Sink, for IC7701	
RDA7702	PRDARA159WJFW		Heat Sink, for D7703/D7713	
	LX-BZ3100CEF7		Screw, x3	

Ref. No.	Part No.	★	Description	Code
DUNTC858WE04				
OPERATION UNIT				
DIODES				
D4201	RH-EX0646GEZZY	J	Zener Diode	AA
D4202	RH-EX0604GEZZY	J	Zener Diode	AB
D4203	RH-EX0604GEZZY	J	Zener Diode	AB
RESISTORS				
R4201	VRS-CY1JF122JY	J	1.2k 1/16W Metal Oxide	AA
R4202	VRS-CY1JF471JY	J	470 1/16W Metal Oxide	AA
R4203	VRS-CY1JF122JY	J	1.2k 1/16W Metal Oxide	AA
R4204	VRS-CY1JF471JY	J	470 1/16W Metal Oxide	AA
R4205	VRS-CY1JF332JY	J	3.3k 1/16W Metal Oxide	AA
SWITCHES				
S4201	QSW-P0614CEZZ	J	MAIN POWER	AF
SW4202	QSW-K0003AJZZ+	J	CH(✓)	AB
SW4203	QSW-K0003AJZZ+	J	CH(∧)	AB
SW4204	QSW-K0003AJZZ+	J	TV/VIDEO	AB
SW4205	QSW-K0003AJZZ+	J	MENU	AB
SW4206	QSW-K0003AJZZ+	J	VOL(+)	AB
SW4207	QSW-K0003AJZZ+	J	VOL(-)	AB
MISCELLANEOUS PARTS				
SC4201	QSOCN0596REZZ	J	Socket, 5-pin	AB

Ref. No.	Part No.	★	Description	Code
DUNTKC859WE04				
R/C, LED UNIT				
TRANSISTORS				
Q4001	VSKRC104S//1Y	J	KRC104S	AA
Q4002	VSKRC104S//1Y	J	KRC104S	AA
Q4004	VSKRC104S//1Y	J	KRC104S	AA
Q4005	VSKRC104S//1Y	J	KRC104S	AA
DIODES				
D4001	RH-PXA014WJZZ+	J	Photodiode	AD
D4002	RH-PXA014WJZZ+	J	Photodiode	AD
D4004	RH-EX0640GEZZY	J	Zener Diode	AA
D4005	RH-EX0640GEZZY	J	Zener Diode	AA
D4007	RH-EX0640GEZZY	J	Zener Diode	AA
D4008	RH-PXA088WJZZ		Photodiode	
CAPACITORS				
C4001	VCEAEA1CW106M+	J	10 16V Electrolytic	AB
C4002	VCEAEA1CW106M+	J	10 16V Electrolytic	AB
C4003	VCEAEA0JW107M+	J	100 6.3V Electrolytic	AB
C4004	VCKYCY1HF103ZY	J	0.01 50V Ceramic	AA
RESISTORS				
R4001	VRS-CY1JF331JY	J	330 1/16W Metal Oxide	AA
R4002	VRS-CY1JF681JY	J	680 1/16W Metal Oxide	AA
R4003	VRS-CY1JF472JY	J	4.7k 1/16W Metal Oxide	AA
R4006	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA
R4007	VRS-CY1JF331JY	J	330 1/16W Metal Oxide	AA
R4010	VRS-CY1JF333JY	J	33k 1/16W Metal Oxide	AA
MISCELLANEOUS PARTS				
SC4001	QSOCN0896REZZ	J	Socket, 8-pin	AC
RMC4001	RRMCUA034WJQZ	J	R/C Receiver	AE
	LHLDZA486WJZZ		LED Holder	

Ref. No.	Part No.	★	Description	Code
----------	----------	---	-------------	------

DUNTKC860FM03

MAIN UNIT

TUNER

NOTE: THE PARTS HERE SHOWN ARE SUPPLIED AS AN ASSEMBLY BUT NOT INDEPENDENTLY.

TU201 VTUVT1Y5ED501 Tuner

INTEGRATED CIRCUITS

IC101	VHiM24C64WN-1Y	J	M24C64-WMN6T	AL
IC151	VHi39VF01WH-1Q		I.C.	
IC501	RH-iXB219WJZZQ		I.C.	
IC701	VHiLM1117MJ-1Y	J	LM1117MPX-ADJ	AF
IC702	VHiMM1563DF-1Y	J	MM1563DFBE	AE
IC703	VHiLM1117MJ-1Y	J	LM1117MPX-ADJ	AF
IC704	VHiBA05FP+-1Y	J	BA05FP-E2	AF
IC751	VHiNJ79M08D-1Y	J	NJM79M08DL1A	AF
IC801	RH-iX3251CEZZY		TDA9178T/N1	
IC1101	VHiBD8120FP-1Y	J	BD8120FP	AX
IC1201	RH-iXA370WJZZQ	J	LR38819	AY
IC2201	VHiTLVDF84B-1Y	J	THC63LVDF84B	AT

TRANSISTORS

Q101	VSFMMT718//-1Y	J	FMMT718	AE
Q102	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q103	VSFMMT718//-1Y	J	FMMT718	AE
Q104	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q105	VSUM5K1NTR+-1Y	J	UM5K1NTR	AC
Q201	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q202	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q205	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q701	VSDTA144EE/-1Y	J	DTA144EE	AA
Q702	VSDTA124EE/-1Y	J	DTA124EE	AB
Q751	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q752	VS2SA1530AR-1Y	J	2SA1530AR	AB
Q753	VSDTC144EE/-1Y	J	DTC144EE	AA
Q754	VSFMMT718//-1Y	J	FMMT718	AE
Q755	VSDTC144EE/-1Y	J	DTC144EE	AA
Q756	VSDTC144EE/-1Y	J	DTC144EE	AA
Q757	VSDTC144EE/-1Y	J	DTC144EE	AA
Q758	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q759	VSDTA144EE/-1Y	J	DTA144EE	AA
Q801	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q802	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q803	VS2SC3928AR-1Y	J	2SC3928AR	AB
Q1105	VS2SC4520//-1Y	J	2SC4520	AE
Q1106	VS2SA1729//-1Y	J	2SA1729	AF

DIODES

D101	VHDHSU119//-1Y	J	Diode	AB
D202	RH-EXA101WJZZY	J	Zener Diode	AB
D203	VHDBR481K+-1Y	J	Diode	AD
D204	VHD1SS390+-1Y	J	Diode	AB
D205	VHDHSU119//-1Y	J	Diode	AB
D206	VHDHSU119//-1Y	J	Diode	AB
D701	VHDHSU119//-1Y	J	Diode	AB
D702	VHDHSU119//-1Y	J	Diode	AB
D703	VHDHSU119//-1Y	J	Diode	AB
D751	RH-EXA099WJZZY		Zener Diode	
D755	VHDBR481K+-1Y	J	Diode	AD
D756	VHDHSU119//-1Y	J	Diode	AB
D757	VHDHSU119//-1Y	J	Diode	AB
D759	VHD1SS250//1EY	J	Diode	AB
D1103	VHD1SS250//1EY	J	Diode	AB
D1104	VHD1SS250//1EY	J	Diode	AB
D1201	VHDHSU119//-1Y	J	Diode	AB
D1202	VHDHSU119//-1Y	J	Diode	AB

PACKAGED CIRCUITS

X101	RCRSAA058WJZZ		Crystal	
X501	RCRSAA037WJZZ	J	Crystal	AE

FILTER AND COILS

L201	VPCNNR56JR41NY		Peaking 0.56μH	
------	----------------	--	----------------	--

Ref. No.	Part No.	★	Description	Code
----------	----------	---	-------------	------

L202	RCiLPA143WJZZY	J	Coil	AD
L751	RCiLPA143WJZZY	J	Coil	AD
L752	VPCNN470J5R4NY	J	Peaking 47μH	AB
L2201	VPCNN2R7JR85NY	J	Peaking 2.7μH	AB
L2202	VPCNN2R7JR85NY	J	Peaking 2.7μH	AB
SF201	RFiLCA102WJZZ		S.A.W Filter	
SF202	RFiLCA103WJZZ		S.A.W Filter	
SF203	RFiLCA182GEZZ		S.A.W Filter	

CAPACITORS

C101	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C102	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C104	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C106	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C107	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C109	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C110	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C111	VCEAPF0JW227MY	J	220 6.3V Electrolytic	AD
C113	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C116	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C117	VCEAPF0JW107MY	J	100 6.3V Electrolytic	AC
C118	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C119	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C121	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C122	VCKYCY1CF224ZY	J	0.22 16V Ceramic	AB
C123	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C124	VCEAPF0JW107MY	J	100 6.3V Electrolytic	AC
C126	VCEAPF1CW106MY	J	10 16V Electrolytic	AB
C127	VCKYCY1CB223KY	J	0.022 16V Ceramic	AB
C128	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C151	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C152	VCEAPF1CW106MY	J	10 16V Electrolytic	AB
C161	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C162	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C163	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C201	VCEAPF1CW106MY	J	10 16V Electrolytic	AB
C202	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C203	VCKYCY1HF333ZY		0.033 50V Ceramic	
C204	VCEAPF1CW476MY	J	47 16V Electrolytic	AC
C205	VCEAPF1CW476MY	J	47 16V Electrolytic	AC
C206	VCEAPF0JW227MY	J	220 6.3V Electrolytic	AD
C207	VCEAPF1HW225MY	J	2.2 50V Electrolytic	AB
C208	VCKYCY1HB103KY	J	0.01 50V Ceramic	AA
C213	VCKYCY1HB103KY	J	0.01 50V Ceramic	AA
C215	VCEAPF1CW106MY	J	10 16V Electrolytic	AB
C216	VCEAPF1HW225MY	J	2.2 50V Electrolytic	AB
C217	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C218	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C220	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C301	VCEAPF1HW475MY	J	4.7 50V Electrolytic	AC
C302	VCKYCY1HB392KY	J	3900p 50V Ceramic	AA
C303	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C304	VCEAPF1HW225MY	J	2.2 50V Electrolytic	AB
C305	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C306	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C331	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C332	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C358	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C359	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C360	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C361	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C362	VCKYTV1EB474KY	J	0.47 25V Ceramic	AC
C363	VCKYTV1EB474KY	J	0.47 25V Ceramic	AC
C364	RC-KZ0072TAZZY	J	1 25V Ceramic	AC
C365	RC-KZ0072TAZZY	J	1 25V Ceramic	AC
C366	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C367	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C368	VCKYTV1EB474KY	J	0.47 25V Ceramic	AC
C369	VCKYTV1EB474KY	J	0.47 25V Ceramic	AC
C408	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C409	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C410	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C411	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA
C412	VCCCCY1HH101JY	J	100p 50V Ceramic	AA
C413	VCKYCY1EF104ZY	J	0.1 25V Ceramic	AA

Ref. No.	Part No.	★	Description	Code	Ref. No.	Part No.	★	Description	Code
DUNTKC860FM03									
MAIN UNIT (Continued)									
C414	VCKYCY1HB103KY	J 0.01	50V Ceramic	AA	C761	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C415	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C763	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C416	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C764	VCEASN1HN475MY	J 4.7	50V Electrolytic	AC
C417	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C765	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C418	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C766	VCEAPF0JW227MY	J 220	6.3V Electrolytic	AD
C419	VCCCCY1HH101JY	J 100p	50V Ceramic	AA	C801	VCEAPF1HW105MY	J 1	50V Electrolytic	AB
C420	VCEAPF1CW106MY	J 10	16V Electrolytic	AB	C802	VCKYCY1HB682KY	J 6800p	50V Ceramic	AA
C421	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C803	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB
C501	VCEAPF0JW226MY	J 22	6.3V Electrolytic	AB	C804	VCEAPF1CW106MY	J 10	16V Electrolytic	AB
C504	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C805	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C505	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C806	VCKYCY1CF334ZY	J 0.33	16V Ceramic	AB
C506	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C807	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C507	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C808	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C510	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C809	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C511	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C810	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C512	VCEAPF0JW226MY	J 22	6.3V Electrolytic	AB	C811	VCCCCY1HH220JY	J 22p	50V Ceramic	AA
C513	VCEAPF1CW106MY	J 10	16V Electrolytic	AB	C812	VCCCCY1HH220JY	J 22p	50V Ceramic	AA
C514	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C813	VCCCCY1HH220JY	J 22p	50V Ceramic	AA
C515	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	C814	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C517	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C815	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C518	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA	C816	VCEAPF1CW106MY	J 10	16V Electrolytic	AB
C519	VCCCCY1HH8R0DY	J 8.0p	50V Ceramic	AA	C817	RC-KZ0074TAZZY	J 10	6.3V Ceramic	AF
C520	VCCCCY1HH8R0DY	J 8.0p	50V Ceramic	AA	C818	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C521	VCEAPF0JW226MY	J 22	6.3V Electrolytic	AB	C819	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C522	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C820	VCEAPF1CW476MY	J 47	16V Electrolytic	AC
C523	VCEAPF0JW226MY	J 22	6.3V Electrolytic	AB	C821	VCKYCY1HB102KY	J 1000p	50V Ceramic	AA
C524	VCEAPF0JW226MY	J 22	6.3V Electrolytic	AB	C822	VCEAPF0JW107MY	J 100	6.3V Electrolytic	AC
C525	VCEAPF0JW226MY	J 22	6.3V Electrolytic	AB	C823	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C535	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C825	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C536	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C826	VCEAPF1CW106MY	J 10	16V Electrolytic	AB
C547	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C827	RC-KZ0074TAZZY	J 10	6.3V Ceramic	AF
C548	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C828	RC-KZ0074TAZZY	J 10	6.3V Ceramic	AF
C549	VCEAPF0JW107MY	J 100	6.3V Electrolytic	AC	C829	RC-KZ0074TAZZY	J 10	6.3V Ceramic	AF
C550	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C830	VCCCCY1HH470JY	J 47p	50V Ceramic	AA
C551	VCEAPF0JW107MY	J 100	6.3V Electrolytic	AC	C831	VCCCCY1HH470JY	J 47p	50V Ceramic	AA
C552	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C832	VCCCCY1HH470JY	J 47p	50V Ceramic	AA
C554	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C833	VCKYCY1HB271KY	J 270p	50V Ceramic	AA
C556	VCEAPF0JW107MY	J 100	6.3V Electrolytic	AC	C834	VCKYCY1HB271KY	J 270p	50V Ceramic	AA
C557	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C835	VCKYCY1HB271KY	J 270p	50V Ceramic	AA
C558	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C1104	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C570	VCKYCY1CB333KY	J 0.033	16V Ceramic	AA	C1106	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C571	VCCCCY1HH100DY	J 10p	50V Ceramic	AA	C1107	RC-KZA041WJZZY	J 10	10V Ceramic	AC
C574	VCKYCY1CB333KY	J 0.033	16V Ceramic	AA	C1108	VCCCCY1HH560JY	J 56p	50V Ceramic	AB
C575	VCKYCY1CB333KY	J 0.033	16V Ceramic	AA	C1109	RC-KZA041WJZZY	J 10	10V Ceramic	AC
C576	VCCCCY1HH100DY	J 10p	50V Ceramic	AA	C1110	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C578	VCKYCY1CB333KY	J 0.033	16V Ceramic	AA	C1113	VCKYCY1HB103KY	J 0.01	50V Ceramic	AA
C579	VCKYCY1CB223KY	J 0.022	16V Ceramic	AB	C1116	VCKYTV1CB105KY	J 1	16V Ceramic	AC
C580	VCKYCY1CB333KY	J 0.033	16V Ceramic	AA	C1117	VCKYTV1CB105KY	J 1	16V Ceramic	AC
C581	VCCCCY1HH100DY	J 10p	50V Ceramic	AA	C1118	VCKYCY1EB104KY	J 0.1	25V Ceramic	AB
C582	VCKYCY1CB333KY	J 0.033	16V Ceramic	AA	C1119	RC-KZA041WJZZY	J 10	10V Ceramic	AC
C701	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C1120	VCEASN1HN106MY	J 10	50V Electrolytic	AC
C702	VCEAPF1CW476MY	J 47	16V Electrolytic	AC	C1202	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C703	VCEAPF0JW107MY	J 100	6.3V Electrolytic	AC	C1203	RC-KZ0117TAZZY	J 4.7	6.3V Ceramic	AD
C704	VCEAPF1CW476MY	J 47	16V Electrolytic	AC	C1210	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C709	VCEAPF1CW106MY	J 10	16V Electrolytic	AB	C1213	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C710	VCEAPF1CW476MY	J 47	16V Electrolytic	AC	C1214	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C711	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C1215	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C712	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C1216	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C720	VCEAPF1CW106MY	J 10	16V Electrolytic	AB	C2201	VCEAPF1CW106MY	J 10	16V Electrolytic	AB
C721	VCKYCY1HB471KY	J 470p	50V Ceramic	AA	C2202	VCKYCY1HB103KY	J 0.01	50V Ceramic	AA
C722	VCEAPF1CW476MY	J 47	16V Electrolytic	AC	C2203	VCEAPF1CW106MY	J 10	16V Electrolytic	AB
C723	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	C2204	VCKYCY1HB103KY	J 0.01	50V Ceramic	AA
C724	VCEAPF1CW106MY	J 10	16V Electrolytic	AB	C2205	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA
C725	VCKYCY1CF224ZY	J 0.22	16V Ceramic	AB	C2206	VCCCCY1HH470JY	J 47p	50V Ceramic	AA
C751	VCEASN1HN225MY	J 2.2	50V Electrolytic	AB	RESISTORS				
C752	VCEAPF1CW106MY	J 10	16V Electrolytic	AB	R101	VRS-CY1JF332JY	J 3.3k	1/16W Metal Oxide	AA
C753	VCEAPF1CW107MY	J 100	16V Electrolytic	AC	R102	VRS-CY1JF332JY	J 3.3k	1/16W Metal Oxide	AA
C754	VCKYCY1EF104ZY	J 0.1	25V Ceramic	AA	R103	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
C758	RC-KZ0075TAZZY	J 2.2	16V Ceramic	AC	R104	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
C759	VCEASN1HN225MY	J 2.2	50V Electrolytic	AB	R105	VRS-CY1JF153JY	J 15k	1/16W Metal Oxide	AA
C760	VCEAPF1CW107MY	J 100	16V Electrolytic	AC	R106	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
					R107	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
					R108	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
					R109	VRS-CY1JF222JY	J 2.2k	1/16W Metal Oxide	AA

Ref. No.	Part No.	★	Description	Code
DUNTKC860FM03				
MAIN UNIT (Continued)				
R111	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R113	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R114	VRS-CY1JF2R2JY	J 2.2	1/16W Metal Oxide	AA
R115	VRS-CY1JF2R2JY	J 2.2	1/16W Metal Oxide	AA
R116	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R117	VRS-CY1JF2R2JY	J 2.2	1/16W Metal Oxide	AA
R118	VRS-CY1JF2R2JY	J 2.2	1/16W Metal Oxide	AA
R119	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R120	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R122	VRS-CY1JF153JY	J 15k	1/16W Metal Oxide	AA
R123	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
R124	VRS-CY1JF154JY	J 150k	1/16W Metal Oxide	AA
R125	VRS-CY1JF332JY	J 3.3k	1/16W Metal Oxide	AA
R126	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R127	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R129	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R131	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R132	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R133	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R134	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R136	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R137	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R138	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R139	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R140	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R141	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R142	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R143	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R144	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R145	VRS-CY1JF332JY	J 3.3k	1/16W Metal Oxide	AA
R146	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R147	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R148	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R149	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R151	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R152	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R161	VRS-CY1JF332JY	J 3.3k	1/16W Metal Oxide	AA
R201	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R202	VRS-CY1JF122JY	J 1.2k	1/16W Metal Oxide	AA
R203	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R204	VRS-CY1JF122JY	J 1.2k	1/16W Metal Oxide	AA
R205	VRS-CY1JF122JY	J 1.2k	1/16W Metal Oxide	AA
R206	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
R207	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R208	VRS-CY1JF392JY	J 3.9k	1/16W Metal Oxide	AA
R209	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R210	VRS-CY1JF153JY	J 15k	1/16W Metal Oxide	AA
R211	VRS-CY1JF332JY	J 3.3k	1/16W Metal Oxide	AA
R212	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R217	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
R218	VRS-CY1JF681JY	J 680	1/16W Metal Oxide	AA
R219	VRS-CJ1JF102JY	J 1k	1/16W Metal Oxide	AA
R220	VRS-CY1JF122JY	J 1.2k	1/16W Metal Oxide	AA
R221	VRS-CY1JF122JY	J 1.2k	1/16W Metal Oxide	AA
R224	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R237	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R301	VRS-CY1JF391JY	J 390	1/16W Metal Oxide	AA
R302	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R303	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R304	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R305	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R306	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R362	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R363	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R364	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R365	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R366	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R367	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R368	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R369	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R370	VRD-RA2BE103JY	J 10k	1/8W Carbon	AA

Ref. No.	Part No.	★	Description	Code
R371	VRD-RA2BE103JY	J 10k	1/8W Carbon	AA
R423	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R544	VRS-CY1JF823JY	J 82k	1/16W Metal Oxide	AA
R548	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R549	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R550	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R551	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R552	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R553	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R554	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R557	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R558	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R559	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R570	VRS-CY1JF100JY	J 10	1/16W Metal Oxide	AA
R571	VRS-CY1JF470JY	J 47	1/16W Metal Oxide	AA
R573	VRS-CY1JF100JY	J 10	1/16W Metal Oxide	AA
R574	VRS-CY1JF470JY	J 47	1/16W Metal Oxide	AA
R575	VRS-CY1JF100JY	J 10	1/16W Metal Oxide	AA
R576	VRS-CY1JF470JY	J 47	1/16W Metal Oxide	AA
R577	VRS-CY1JF123JY	J 12k	1/16W Metal Oxide	AA
R701	VRS-CY1JF121JY	J 120	1/16W Metal Oxide	AA
R702	VRS-CY1JF271JY	J 270	1/16W Metal Oxide	AA
R704	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R705	VRS-CY1JF000JY	J 0	1/16W Metal Oxide	AA
R709	VRS-TW2HF000JY	J 0	1/2W Metal Oxide	AA
R710	VRS-CY1JF271JY	J 270	1/16W Metal Oxide	AA
R711	VRS-CY1JF471JY	J 470	1/16W Metal Oxide	AA
R718	VRS-VV3AB270J	J 27	1W Metal Oxide	AA
R751	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R752	VRS-CY1JF272JY	J 2.7k	1/16W Metal Oxide	AA
R753	VRS-TW2ED102JY	J 1k	1/4W Metal Oxide	AA
R754	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R755	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R757	VRS-TW2ED103JY	J 10k	1/4W Metal Oxide	AA
R761	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R762	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R764	VRS-CY1JF223JY	J 22k	1/16W Metal Oxide	AA
R766	VRS-TW2HF330JY	J 33	1/2W Metal Oxide	AA
R767	VRS-TW2HF472JY	J 4.7k	1/2W Metal Oxide	AA
R769	VRS-CY1JF562JY	J 5.6k	1/16W Metal Oxide	AA
R801	VRS-CY1JF102JY	J 1k	1/16W Metal Oxide	AA
R802	VRS-CY1JF123JY	J 12k	1/16W Metal Oxide	AA
R803	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R804	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R805	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R806	VRS-CY1JF105JY	J 1M	1/16W Metal Oxide	AA
R807	VRS-CY1JF393JY	J 39k	1/16W Metal Oxide	AA
R808	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R809	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R810	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R811	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R812	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R813	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R814	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R815	VRS-CY1JF100JY	J 10	1/16W Metal Oxide	AA
R816	VRS-CY1JF273JY	J 27k	1/16W Metal Oxide	AA
R817	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
R819	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R820	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R821	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R822	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R823	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R824	VRS-CY1JF472JY	J 4.7k	1/16W Metal Oxide	AA
R825	VRS-CY1JF103JY	J 10k	1/16W Metal Oxide	AA
R826	VRS-CY1JF104JY	J 100k	1/16W Metal Oxide	AA
R827	VRS-CY1JF473JY	J 47k	1/16W Metal Oxide	AA
R828	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R829	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R830	VRS-CY1JF101JY	J 100	1/16W Metal Oxide	AA
R831	VRS-CY1JF121JY	J 120	1/16W Metal Oxide	AA
R832	VRS-CY1JF121JY	J 120	1/16W Metal Oxide	AA
R833	VRS-CY1JF121JY	J 120	1/16W Metal Oxide	AA
R834	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
R835	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA
R836	VRS-CY1JF750JY	J 75	1/16W Metal Oxide	AA

Ref. No.	Part No.	★	Description	Code	Ref. No.	Part No.	★	Description	Code
DUNTKC860FM03					FB532	RBLN-0062TAZZY	J	Ferrite Bead	AB
MAIN UNIT (Continued)					FB533	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1101	VRS-CY1JF273JY	J	27k 1/16W Metal Oxide	AA	FB535	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1102	VRS-CY1JF472JY	J	4.7k 1/16W Metal Oxide	AA	FB801	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1103	VRS-CY1JF472JY	J	4.7k 1/16W Metal Oxide	AA	FB802	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1104	VRS-CY1JF103JY	J	10k 1/16W Metal Oxide	AA	FB803	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1112	VRS-CY1JF181JY	J	180 1/16W Metal Oxide	AA	FB804	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1113	VRS-CY1JF102JY	J	1k 1/16W Metal Oxide	AA	FB805	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1114	VRS-CY1JF181JY	J	180 1/16W Metal Oxide	AA	FB806	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1117	VRS-TW2HF5R6JY	J	5.6 1/2W Metal Oxide	AA	FB807	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1118	VRS-TW2HF5R6JY	J	5.6 1/2W Metal Oxide	AA	FB808	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1121	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA	FB809	RBLN-0062TAZZY	J	Ferrite Bead	AB
R1122	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA	FB1201	RBLN-0083GEZZY	J	Ferrite Bead	AB
R1123	VRS-TW2HF000JY	J	0 1/2W Metal Oxide	AA	P2002	QPLGNA144WJZZY	J	Plug, 20-pin	AF
R1124	VRS-TW2HF101JY	J	100 1/2W Metal Oxide	AA	SC102	QCNCWA010WJZZY	J	Connector, 15-pin	AE
R1126	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA	SC104	QCNCWA010WJZZY	J	Connector, 15-pin	AE
R1128	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA	SC105	QSOCN0596REZZ	J	Socket, 5-pin	AB
R1129	VRS-CY1JF103JY	J	10k 1/16W Metal Oxide	AA	SC106	QCNCWA251WJZZY	J	Connector, 23-pin	
R1130	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA	SC1201	QSOCNA002WJPZY	J	Socket, 20-pin	AD
R1203	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA	SC1202	QSOCN0687FJZZY	J	Socket, 50-pin	AF
R1204	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA	SC1203	QSOCN0206FJZZY	J	Socket, 30-pin	AF
R1205	VRK-CD1JJ220JY	J	22 1/16W Metal Compo.	AC	TP101	QLUGHA006WJZZY	J	Lug	AC
R1206	VRK-CD1JJ220JY	J	22 1/16W Metal Compo.	AC	TP102	QLUGHA006WJZZY	J	Lug	AC
R1207	VRK-CD1JJ220JY	J	22 1/16W Metal Compo.	AC					
R1208	VRS-CY1JF220JY	J	22 1/16W Metal Oxide	AA					
R1209	VRS-CY1JF220JY	J	22 1/16W Metal Oxide	AA					
R1210	VRS-CA1JF220JY	J	22 1/16W Metal Oxide	AA					
R1211	VRS-CA1JF101JY	J	100 1/16W Metal Oxide	AA					
R1214	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1215	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1216	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1217	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1218	VRS-CY1JF220JY	J	22 1/16W Metal Oxide	AA					
R1223	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA					
R1230	VRS-CY1JF472JY	J	4.7k 1/16W Metal Oxide	AA					
R1240	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1241	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1242	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R1243	VRS-CY1JF000JY	J	0 1/16W Metal Oxide	AA					
R2203	VRS-CB1JF470JY	J	47 1/16W Metal Oxide	AA					
R2204	VRS-CB1JF470JY	J	47 1/16W Metal Oxide	AA					
R2205	VRS-CB1JF470JY	J	47 1/16W Metal Oxide	AA					
R2206	VRS-CB1JF470JY	J	47 1/16W Metal Oxide	AA					
R2207	VRS-CB1JF470JY	J	47 1/16W Metal Oxide	AA					
R2208	VRS-CB1JF470JY	J	47 1/16W Metal Oxide	AA					
R2224	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R2225	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R2226	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R2227	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R2228	VRS-CY1JF101JY	J	100 1/16W Metal Oxide	AA					
R2232	VRS-CY1JF100JY	J	10 1/16W Metal Oxide	AA					
R2233	VRS-CY1JF103JY	J	10k 1/16W Metal Oxide	AA					
MISCELLANEOUS PARTS									
FB101	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB102	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB103	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB104	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB105	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB106	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB107	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB108	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB109	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB151	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB201	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB204	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB401	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB501	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB502	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB504	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB507	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB508	RBLN-0062TAZZY	J	Ferrite Bead	AB					
FB531	RBLN-0062TAZZY	J	Ferrite Bead	AB					

Ref. No.	Part No.	★	Description	Code
----------	----------	---	-------------	------

CABINET AND MECHANICAL PARTS

1	CCABAA703WJ01		Cabinet A Ass'y	
1-1	<i>Not Available</i>	—	Cabinet A	—
1-2	HDECQA452WJSA		R/C-LED Cover	
1-3	HDECQA459WJSA		LED Cover	
1-4	HDECQA478WJSA		Leg Cover, x2	
1-5	XEBSN30P08000	J	Screw, x1	AA
2	CCABBA456WJ01		Cabinet B Ass'y	
2-1	<i>Not Available</i>	—	Cabinet B	—
2-2	GLEGGA042WJZZ		Rubber Leg, x2	
2-3	LANGFA085WJFW	J	Kensington Angle	AC
2-4	LANGTA155WJFW		Reinforcement Angle	
2-5	PZETKA109WJZZ		Insulating Spacer, x1	
2-6	XEBSN30P08000	J	Screw, x1	AA
3	CDAi-A140WJ01		Stand Ass'y	
3-1	CDAi-A140WJ02		Stand Base Ass'y	
3-1-1	GDai-A140WJSA		Stand Base	
3-1-2	GLEGGA041WJSA		Rubber Leg, x2	
3-1-3	PSPAZA083WJZZ	J	Spacer, x2	AB
3-2	GCOVAB023WJSA		Stand Cover	
3-3	XESSN40P10000	J	Screw, x8	AB
4	CCOVAA976WJ01		Top Cover Ass'y	
4-1	<i>Not Available</i>	—	Top Cover	—
4-2	JBTN-A353WJSA		Operation Button	
4-3	JBTN-A354WJSA		Power Button	
4-4	MSPRCA014WJFW	J	Spring, for Power Button	AB
4-5	XEBSN30P08000	J	Screw, x1	AA
5	<i>Not Available</i>	—	20" LCD Panel Unit Ass'y	—
5-1	RLCDDTA025WJZZ	J	20" LCD Panel Unit	DB
5-2	<i>Not Available</i>	—	Back Shield Ass'y	
5-2-1	PSLDMA495WJFW		Back Shield	
5-2-2	LHLDZA412WJKZ	J	Lamp Holder-L(Bottom)	AG
5-2-3	LHLDZA413WJKZ	J	Lamp Holder-R(Bottom)	AF
5-2-4	PMLT-A150WJZZ	J	Light Shielding Spacer, x2	AD
5-2-5	PSHEPA226WJZZ	J	Reflection Sheet	AN
5-2-6	TCAUZA031WJZZ	J	Caution Label	AB
5-3	KLMP-A046WJZZ	J	Lamp Unit, x5	AV
5-4	LHLDZA414WJKZ	J	Lamp Holder-L(Top)	AL
5-5	LHLDZA415WJKZ	J	Lamp Holder-R(Top)	AL
5-6	PCOVUA048WJZZ	J	Diffusion Plate	AY
5-7	PSHEPA231WJZZ	J	Reflection/deflection Sheet	BB
5-8	PSHEPA233WJZZ	J	Diffusion Sheet	AM
5-9	PSPAZA447WJZZ	J	Spacer, x1	AC
5-10	QCNW-C947WJQZ		Connecting Cord	
5-11	XBPS726P05J00	J	Screw, x3	AA
6	GCOVAA984WJKA		Bass-Conne Cover	
7	LCHSMA146WJKA		Chassis Frame	
8	LX-BZ3442CEF9	J	Screw, x4	AB
9	PSPAZA614WJZZ		Spacer, x1	
10	PSPAZA615WJZZ		Spacer, x1	
11	PSPAZA640WJKZ		Spacer, x1	
12	PSPAZA641WJKZ		Spacer, x1	
13	PSPAZA642WJKZ		Spacer, x1	
14	QCNW-B813WJPZ		Connecting Cord	
15	QCNW-B814WJPZ		Connecting Cord	
16	QCNW-C853WJQZ		Connecting Cord	
17	QCNW-C948WJQZ		Connecting Cord	
18	QCNW-C949WJQZ		Connecting Cord	
19	QEARPA125WJFW		Grounding Part, x1	
20	QEARZA041WJZZ	J	Grounding Part, x1	AE
21	RCORFA032WJZZ	J	Core, x1	AK
22	TLABMB271WJZZ		Model Label (LC-20SH1E/E(F)/E(K))	
22	TLABMB473WJZZ		Model Label (LC-20SH1E(I))	
23	<i>Not Available</i>	—	Serial No. Label	—
24	VSP1104PB038A		Speaker, x2	

Ref. No.	Part No.	★	Description	Code
----------	----------	---	-------------	------

25	XEBS940P20000	J	Screw, x5	AB
26	XEBSN30P08000	J	Screw, x7	AA
27	XEBSN40P10000	J	Screw, x8	AB
28	XHBS830P10000		Screw, x2	
29	XHPS730P08WS0		Screw, x7	
30	TLABZA792WJZZ		EICTA Label	



Ref. No.	Part No.	★	Description	Code
SUPPLIED ACCESSORIES				
△ X1	QACCB A016WJPZ	J	AC Cord (LC-20SH1E(K))	AR
△ X1	QACCKA006WJPZ	J	AC Cord (LC-20SH1E/E(F)/E(I))	AL
X2	RRMCGA339WJSA		Wireless remote control	
X3	TiNS-B517WJZZ		Operation Manual	
X4	TiNS-B634WJZZ		Instruction Book (LC-20SH1E/E(F))	
X5	TiNS-B635WJZZ		Instruction Book (LC-20SH1E)	
X6	TGAN-1688CEN1	J	Guarantee Card (LC-20SH1E(K))	AN
X7	Not Available	—	"AA" size Battery, x2	—

Ref. No.	Part No.	★	Description	Code
PACKING PARTS (NOT REPLACEMENT ITEM)				
S1	SPAKCB640WJZZ	—	Packing Case	—
S2	SPAKPA188WJZZ	—	Wrapping Paper	—
S3	SPAKXA620WJZZ	—	Buffer Material	—
S4	SSAKAA010WJZZ	—	Polyethylene Bag (E(K)/E(I)x1, E(F)x2, Ex3)	—
S5	TLABKA002WJZZ	—	Carton Label, x1	—
S6	TLABN0134BMZZ	—	SEES No. Label, x2	—

SERVICE JIGS (USE FOR SERVICING)

QCNW-A553WJZZ	J	Extension Cable, 30-pin (SC1203-LCD)	BA
QCNW-A556WJZZ	J	Extension Cable, 50-pin (SC1202-LCD)	AU
QCNW-A555WJZZ	J	Extension Cable, 20-pin (SC1201-LCD)	AU
QCNW-D444WJZZ		Extension Cable, 5-pin (SC4201-SC105)	
QCNW-D445WJZZ		Extension Cable, 8-pin (SC4001-SC3601)	

Supplied Accessories

AC cord	Wireless remote control	Operation manual	"AA" size batteries (x2)
X1  *Product shape may vary from country to country.	X2 	X3 	X7 

PACKING OF THE SET

